

The following is a list of the 6200+ additional built-in constants in Quartus Forth. Where applicable, values are shown either as hex or decimal values, or as 32-bit four-character IDs. Double-cell values are shown with a trailing dot. For example:

```
500000. mdmDefCmdTimeOut
```

Structure offsets are in the format

```
StructureName.offsetName.
```

Bit-fields (used in a few structures) are handled specially. Three associated constants with `.shift`, `.mask`, and `.size` suffixes are provided for each bit-field, for example:

```
15 DateType.month.mask
 4 DateType.month.size
 5 DateType.month.shift
 0 DateType.month
```

This structure offset is named `DateType.month`. It is stored as a bit-field, occupying 4 bits starting at bit 5.

To access a bit-field value:

1. Fetch the value
2. **RSHIFT** with the associated `.shift` constant
3. **AND** with the associated `.mask` constant

(`.size` values are provided for all bit-fields for completeness, but they are not required to read data from a bit-field.)

```
1126 sysNumTraps
 0 ErrExceptionType.nextP
 4 ErrExceptionType.state
52 ErrExceptionType.err

 0 SysAlarmTriggeredParamType.ref
 4 SysAlarmTriggeredParamType.alarmSeconds
 8 SysAlarmTriggeredParamType.purgeAlarm
 9 SysAlarmTriggeredParamType.padding

 0 SysDisplayAlarmParamType.ref
 4 SysDisplayAlarmParamType.alarmSeconds
 8 SysDisplayAlarmParamType.soundAlarm
 9 SysDisplayAlarmParamType.padding

 0 almProcCmdTriggered
 1 almProcCmdRescheduled
(hex) 8000 almProcCmdCustom
(hex) 8000 almProcAlarmCardNo
 0 addrLookupName
 1 addrLookupFirstName
 2 addrLookupCompany
 3 addrLookupAddress
 4 addrLookupCity
 5 addrLookupState
 6 addrLookupZipCode
 7 addrLookupCountry
 8 addrLookupTitle
 9 addrLookupCustom1
10 addrLookupCustom2
11 addrLookupCustom3
12 addrLookupCustom4
13 addrLookupNote
14 addrLookupWork
15 addrLookupHome
```

```
16 addrLookupFax
17 addrLookupOther
18 addrLookupEmail
19 addrLookupMain
20 addrLookupPager
21 addrLookupMobile
22 addrLookupSortField
23 addrLookupListPhone
24 addrLookupFieldCount
255 addrLookupNoField
12 addrLookupStringLength

 0 AddrLookupParamsType.title
 4 AddrLookupParamsType.pasteButtonText
 8 AddrLookupParamsType.lookupString
20 AddrLookupParamsType.field1
21 AddrLookupParamsType.field2
22 AddrLookupParamsType.field2Optional
23 AddrLookupParamsType.userShouldInteract
24 AddrLookupParamsType.formatStringP
28 AddrLookupParamsType.resultStringH
32 AddrLookupParamsType.uniqueID

(hex) 8001 prefAppLaunchCmdSetActivePanel
 0 PrefActivePanelParamsType.activePanel

 0 mailPriorityHigh
 1 mailPriorityNormal
 2 mailPriorityLow

 0 MailAddRecordParamsType.secret
 1 MailAddRecordParamsType.signature
 2 MailAddRecordParamsType.confirmRead
 3 MailAddRecordParamsType.confirmDelivery
 4 MailAddRecordParamsType.priority
 5 MailAddRecordParamsType.padding
 6 MailAddRecordParamsType.subject
10 MailAddRecordParamsType.from
14 MailAddRecordParamsType.to
18 MailAddRecordParamsType.cc
22 MailAddRecordParamsType.bcc
26 MailAddRecordParamsType.replyTo
30 MailAddRecordParamsType.body

 0 MsgInboxCategory
 1 MsgOutboxCategory
 2 MsgDeletedCategory
 3 MsgFiledCategory
 4 MsgDraftCategory

 0 MsgAddRecordParamsType.category
 2 MsgAddRecordParamsType.edit
 3 MsgAddRecordParamsType.signature
 4 MsgAddRecordParamsType.subject
 8 MsgAddRecordParamsType.from
12 MsgAddRecordParamsType.to
16 MsgAddRecordParamsType.replyTo
20 MsgAddRecordParamsType.body

 0 BitmapVersionZero
 1 BitmapVersionOne
 2 BitmapVersionTwo
 3 BitmapVersionThree
 0 BitmapCompressionTypeScanLine
 1 BitmapCompressionTypeRLE
 2 BitmapCompressionTypePackBits
 3 BitmapCompressionTypeEnd
100 BitmapCompressionTypeBest
255 BitmapCompressionTypeNone
 0 pixelFormatIndexed
 1 pixelFormat565
 2 pixelFormat565LE
 3 pixelFormatIndexedLE
72 kDensityLow
108 kDensityOneAndAHalf
144 kDensityDouble
216 kDensityTriple
(hex) 120 kDensityQuadruple

 0 RGBColorType.index
 1 RGBColorType.r
 2 RGBColorType.g
 3 RGBColorType.b

 0 BitmapDirectInfoType.redBits
 1 BitmapDirectInfoType.greenBits
 2 BitmapDirectInfoType.blueBits
 3 BitmapDirectInfoType.reserved
 4 BitmapDirectInfoType.transparentColor

 0 ColorTableType.numEntries
```

0	HDSelectorBmpGetNextBitmapAnyDensity	10010	sysResIDSndCardInsert
1	HDSelectorBmpGetVersion	10011	sysResIDSndCardRemove
2	HDSelectorBmpGetCompressionType	10020	sysResIDSndSyncStart
3	HDSelectorBmpGetDensity	10021	sysResIDSndSyncStop
4	HDSelectorBmpSetDensity	0	sysResIDSysPrefMain
5	HDSelectorBmpGetTransparentValue	1	sysResIDSysPrefPassword
6	HDSelectorBmpSetTransparentValue	2	sysResIDSysPrefFindStr
7	HDSelectorBmpCreateBitmapV3	3	sysResIDSysPrefCalibration
8	HDSelectorWinSetCoordinateSystem	4	sysResIDDLkUserInfo
9	HDSelectorWinGetCoordinateSystem	5	sysResIDDLkLocalPC
10	HDSelectorWinScalePoint	6	sysResIDDLkCondFilterTab
11	HDSelectorWinUnscalePoint	7	sysResIDModemMgrPref
12	HDSelectorWinScaleRectangle	8	sysResIDDLkLocalPCAddr
13	HDSelectorWinUnscaleRectangle	9	sysResIDDLkLocalPCMask
14	HDSelectorWinScreenGetAttribute	10	sysResIDButton1Param
15	HDSelectorWinPaintTiledBitmap	11	sysResIDButton2Param
16	HDSelectorWinGetSupportedDensity	12	sysResIDButton3Param
17	HDSelectorEvtGetPenNative	13	sysResIDButton4Param
18	HDSelectorWinScaleCoord	14	sysResIDCalcButtonParam
19	HDSelectorWinUnscaleCoord	15	sysResIDCradleParam
20	HDSelectorWinPaintRoundedRectangleFrame	16	sysResIDModemParam
21	HDSelectorInvalid	17	sysResIDAntennaButtonParam
(hex) 200	hardKeyMin	17	sysResIDPrefUIColorTableBase
767	hardKeyMax	18	sysResIDPrefUIColorTable1
40	mdmMaxStringSize	19	sysResIDPrefUIColorTable2
81	mdmCmdBufSize	21	sysResIDPrefUIColorTable4
81	mdmRespBufSize	25	sysResIDPrefUIColorTable8
8	mdmCmdSize	26	sysResIDSysPrefPasswordHint
500000.	mdmDefCmdTimeOut	27	sysResIDSysPrefPasswordHash
4	mdmDefDTWaitSec	1	sysResIDFlashMgrWorkspace
70	mdmDefDCWaitSec	(hex) 2710	sysResIDHwrFlashIdent
1	mdmDefSpeakerVolume	1	sysFtrIDOEMSysHideBatteryGauge
1	mdmResetStrInCmdBuf	1	sysFtrIDKeyboardActive
0	mdmVolumeOff	1	sysActivateStatusFeatureIndex
1	mdmVolumeLow	0	sysActivateNeedGeorgeQuery
2	mdmVolumeMed	1	sysActivateNeedMortyQuery
3	mdmVolumeHigh	2	sysActivateFullyActivated
0	mdmStageInvalid	64	sysMaxUserDomainNameLength
1	mdmStageReserved	1	sysClipperPQACardNoIndex
2	mdmStageFindingModem	2	sysClipperPQADbIDIndex
3	mdmStageInitializing	0	AbsRectType.left
4	mdmStageDialing	2	AbsRectType.top
5	mdmStageWaitingForCarrier	4	AbsRectType.right
6	mdmStageHangingUp	6	AbsRectType.bottom
0	MdmInfoType.portID	0	PointType.x
2	MdmInfoType.initialBaud	2	PointType.y
6	MdmInfoType.cmdTimeOut	0	RectangleType.topLeft
10	MdmInfoType.dtWaitSec	4	RectangleType.extent
12	MdmInfoType.dcdWaitSec	20	fntTabChrWidth
14	MdmInfoType.volume	-1	fntMissingChar
16	MdmInfoType.pulse	0	FontDensityTag.density
17	MdmInfoType.hwHShake	2	FontDensityTag.glyphBitsOffset
18	MdmInfoType.autoBaud	0	stdFont
19	MdmInfoType.telConnection	1	boldFont
20	MdmInfoType.canProcP	2	largeFont
24	MdmInfoType.userRef	6	ledFont
28	MdmInfoType.cmdBuf	7	largeBoldFont
109	MdmInfoType.respBuf	128	fntAppFontCustomBase
190	MdmInfoType.connectBaud	4	checkboxFont
194	MdmInfoType.curStage	4	kWinVersion
195	MdmInfoType.strInCmdBuf	0	winUp
(hex) 2710	sysResIDBootReset	1	winDown
10001	sysResIDBootInitCode	2	winLeft
10100	sysResIDBootSysCodeStart	3	winRight
10102	sysResIDBootSysCodeMin	0	screenFormat
10200	sysResIDBootUICodeStart	1	genericFormat
10203	sysResIDBootUICodeMin	2	nativeFormat
10300	sysResIDProdUpdCodeStart	0	winLockCopy
19000	sysResIDBootHAL	1	winLockErase
19100	sysResIDBootHALCodeStart	2	winLockDontCare
19000	sysResIDBitmapSplash	0	winScreenModeGetDefaults
19001	sysResIDBitmapConfirm	1	winScreenModeGet
0	sysResIDAppPrefs	2	winScreenModeSetToDefaults
0	sysResIDExtPrefs	3	winScreenModeSet
(hex) 2710	sysResIDFeatures	4	winScreenModeGetSupportedDepths
10001	sysResIDOverlayFeatures	5	winScreenModeGetSupportsColor
(hex) 2710	sysResIDGrfTemplate	0	winPaletteGet
(hex) 2710	sysResIDGrfDictionary	1	winPaletteSet
(hex) 2710	sysResIDGrfDefaultMacros	2	winPaletteSetToDefault
1	sysResIDDefaultDB	3	winPaletteInit
(hex) 2710	sysResIDCompressedDB	0	winPaint
20001	sysResIDOEMDBVersion	1	winErase
(hex) 2710	sysResIDButtonDefaults	2	winMask
(hex) 2710	sysResIDSndInfo	3	winInvert
10001	sysResIDSndWarning	4	winOverlay
10003	sysResIDSndStartUp	5	winPaintInverse
10004	sysResIDSndAlarm		
10005	sysResIDSndConfirmation		
10006	sysResIDSndClick		

6	winSwap	(hex) 1100	sysEventFirstWebLibEvent
0	blackPattern	(hex) 6000	sysEventFirstUserEvent
1	whitePattern	32767	sysEventLastUserEvent
2	grayPattern	1	shiftKeyMask
3	customPattern	2	capsLockMask
4	lightGrayPattern	4	numLockMask
5	darkGrayPattern	8	commandKeyMask
0	noPattern	16	optionKeyMask
170	grayHLinePattern	32	controlKeyMask
85	grayHLinePatternOdd	64	autoRepeatKeyMask
0	noUnderline	128	doubleTapKeyMask
1	grayUnderline	(hex) 100	poweredOnKeyMask
2	solidUnderline	(hex) 200	appEvtHookKeyMask
3	colorUnderline	(hex) 400	libEvtHookKeyMask
-1	WinUseTableIndexes	1544	virtualKeyMask
0	kCoordinatesNative	-1	evtWaitForever
72	kCoordinatesStandard	0	evtNoWait
108	kCoordinatesOneAndAHalf	0	GenericEventType.datum
144	kCoordinatesDouble	0	PenUpEventType.start
216	kCoordinatesTriple	4	PenUpEventType.end
(hex) 120	kCoordinatesQuadruple	0	KeyDownEventType.chr
0	winScreenWidth	2	KeyDownEventType.keyCode
1	winScreenHeight	4	KeyDownEventType.modifiers
2	winScreenRowBytes	0	WinEnterEventType.enterWindow
3	winScreenDepth	4	WinEnterEventType.exitWindow
4	winScreenAllDepths	0	WinExitEventType.enterWindow
5	winScreenDensity	4	WinExitEventType.exitWindow
6	winScreenPixelFormat	0	TSMConfirmType.yomiText
7	winScreenResolutionX	4	TSMConfirmType.formID
8	winScreenResolutionY	0	TSMFepButtonType.buttonID
6	kFixedBias	0	TSMFepModeEventType.mode
63	kFixedFractionMask	0	SysEventType.eType
32	kFixedOneHalf	2	SysEventType.penDown
5	DrawStateStackSize	3	SysEventType.tapCount
255	FrameBitsType.bits.cornerDiam.mask	4	SysEventType.screenX
8	FrameBitsType.bits.cornerDiam.size	6	SysEventType.screenY
8	FrameBitsType.bits.cornerDiam.shift	8	SysEventType.data
0	FrameBitsType.bits.cornerDiam	0	SysEventStoreType.event
7	FrameBitsType.bits.reserved_3.mask	24	SysEventStoreType.id
3	FrameBitsType.bits.reserved_3.size	0	nilEvent
5	FrameBitsType.bits.reserved_3.shift	1	penDownEvent
0	FrameBitsType.bits.reserved_3	2	penUpEvent
1	FrameBitsType.bits.threeD.mask	3	penMoveEvent
1	FrameBitsType.bits.threeD.size	4	keyDownEvent
4	FrameBitsType.bits.threeD.shift	5	winEnterEvent
0	FrameBitsType.bits.threeD	6	winExitEvent
3	FrameBitsType.bits.shadowWidth.mask	7	ctlEnterEvent
2	FrameBitsType.bits.shadowWidth.size	8	ctlExitEvent
2	FrameBitsType.bits.shadowWidth.shift	9	ctlSelectEvent
0	FrameBitsType.bits.shadowWidth	10	ctlRepeatEvent
3	FrameBitsType.bits.width.mask	11	lstEnterEvent
2	FrameBitsType.bits.width.size	12	lstSelectEvent
0	FrameBitsType.bits.width.shift	13	lstExitEvent
0	FrameBitsType.bits.width	14	popSelectEvent
0	noFrame	15	fldEnterEvent
1	simpleFrame	16	fldHeightChangedEvent
1	rectangleFrame	17	fldChangedEvent
18	simple3DFrame	18	tblEnterEvent
1025	roundFrame	19	tblSelectEvent
1794	boldRoundFrame	20	daySelectEvent
517	popupFrame	21	menuEvent
770	dialogFrame	22	appStopEvent
517	menuFrame	23	frmLoadEvent
255	winDefaultDepthFlag	24	frmOpenEvent
0	WinLineType.x1	25	frmGotoEvent
2	WinLineType.y1	26	frmUpdateEvent
4	WinLineType.x2	27	frmSaveEvent
6	WinLineType.y2	28	frmCloseEvent
50	insPtBlinkInterval	29	frmTitleEnterEvent
2	insPtWidth	30	frmTitleSelectEvent
0	sysEventNilEvent	31	tblExitEvent
1	sysEventPenDownEvent	32	sclEnterEvent
2	sysEventPenUpEvent	33	sclExitEvent
3	sysEventPenMoveEvent	34	sclRepeatEvent
4	sysEventKeyDownEvent	35	tsmConfirmEvent
5	sysEventWinEnterEvent	36	tsmFepButtonEvent
6	sysEventWinExitEvent	37	tsmFepModeEvent
22	sysEventAppStopEvent	38	attnIndicatorEnterEvent
35	sysEventTsmConfirmEvent	39	attnIndicatorSelectEvent
36	sysEventTsmFepButtonEvent	(hex) 800	menuCmdBarOpenEvent
37	sysEventTsmFepModeEvent	2049	menuOpenEvent
38	sysEventFrmTitleChangedEvent		
(hex) 800	sysEventNextUIEvent		
(hex) 1000	sysEventFirstINetLibEvent		

2050 menuCloseEvent	6 lstSelect.selection
2051 frmGadgetEnterEvent	
2052 frmGadgetMiscEvent	0 lstExit.listID
(hex) 1000 firstINetLibEvent	2 lstExit.pList
(hex) 1100 firstWebLibEvent	
(hex) 6000 firstUserEvent	0 lstEnter.listID
32767 lastUserEvent	2 lstEnter.pList
	6 lstEnter.selection
0 gadgetMisc.gadgetID	
2 gadgetMisc.gadgetP	0 fldExit.fieldID
6 gadgetMisc.selector	2 fldExit.pField
8 gadgetMisc.dataP	
0 gadgetEnter.gadgetID	0 fldChanged.fieldID
2 gadgetEnter.gadgetP	2 fldChanged.pField
0 menuOpen.menuRscID	0 fldHeightChanged.fieldID
2 menuOpen.cause	2 fldHeightChanged.pField
	6 fldHeightChanged.newHeight
	8 fldHeightChanged.currentPos
0 menuCmdBarOpen.preventFieldButtons	
1 menuCmdBarOpen.reserved	0 fldEnter.fieldID
	2 fldEnter.pField
0 sclRepeat.scrollBarID	0 ctlExit.controlID
2 sclRepeat.pScrollBar	2 ctlExit.pControl
6 sclRepeat.value	
8 sclRepeat.newValue	
10 sclRepeat.time	0 ctlRepeat.controlID
	2 ctlRepeat.pControl
	6 ctlRepeat.time
	10 ctlRepeat.value
0 sclExit.scrollBarID	
2 sclExit.pScrollBar	0 ctlSelect.controlID
6 sclExit.value	2 ctlSelect.pControl
8 sclExit.newValue	6 ctlSelect.on
	7 ctlSelect.reserved1
0 sclEnter.scrollBarID	8 ctlSelect.value
2 sclEnter.pScrollBar	
0 popSelect.controlID	0 ctlEnter.controlID
2 popSelect.controlP	2 ctlEnter.pControl
6 popSelect.listID	
8 popSelect.listP	
12 popSelect.selection	0 EventType.eType
14 popSelect.priorSelection	2 EventType.penDown
	3 EventType.tapCount
	4 EventType.screenX
	6 EventType.screenY
0 menu.itemID	8 EventType.data
0 daySelect.pSelector	
4 daySelect.selection	0 memIDPtr
6 daySelect.useThisDate	1 memIDHandle
7 daySelect.reserved1	(hex) 100 memNewChunkFlagPreLock
	(hex) 200 memNewChunkFlagNonMovable
0 attnIndicatorSelect.formID	(hex) 400 memNewChunkFlagAtStart
	(hex) 800 memNewChunkFlagAtEnd
0 attnIndicatorEnter.formID	1 memDebugModeCheckOnChange
	2 memDebugModeCheckOnAll
0 frmTitleSelect.formID	4 memDebugModeScrambleOnChange
	8 memDebugModeScrambleOnAll
0 frmTitleEnter.formID	16 memDebugModeFillFree
	32 memDebugModeAllHeaps
0 frmUpdate.formID	64 memDebugModeRecordMinDynHeapFree
2 frmUpdate.updateCode	15 dmRecAttrCategoryMask
	16 dmRecNumCategories
0 frmClose.formID	16 dmCategoryLength
	255 dmAllCategories
0 frmGoto.formID	0 dmUnfiledCategory
2 frmGoto.recordNum	(hex) FFFF dmMaxRecordIndex
4 frmGoto.matchPos	128 dmRecAttrDelete
6 frmGoto.matchLen	64 dmRecAttrDirty
8 frmGoto.matchFieldNum	32 dmRecAttrBusy
10 frmGoto.matchCustom	16 dmRecAttrSecret
	240 dmAllRecAttrs
0 frmOpen.formID	32 dmSysOnlyRecAttrs
	32 dmDBNameLength
0 frmLoad.formID	1 dmHdrAttrResDB
	2 dmHdrAttrReadOnly
0 tblSelect.tableID	4 dmHdrAttrAppInfoDirty
2 tblSelect.pTable	8 dmHdrAttrBackup
6 tblSelect.row	16 dmHdrAttrOKToInstallNewer
8 tblSelect.column	32 dmHdrAttrResetAfterInstall
	64 dmHdrAttrCopyPrevention
0 tblExit.tableID	128 dmHdrAttrStream
2 tblExit.pTable	(hex) 100 dmHdrAttrHidden
6 tblExit.row	(hex) 200 dmHdrAttrLaunchableData
8 tblExit.column	(hex) 400 dmHdrAttrRecyclable
	(hex) 800 dmHdrAttrBundle
0 tblEnter.tableID	(hex) 8000 dmHdrAttrOpen
	(hex) 8FFF dmAllHdrAttrs
2 tblEnter.pTable	(hex) 8001 dmSysOnlyHdrAttrs
6 tblEnter.row	1 dmRecordIDReservedRange
8 tblEnter.column	0 dmDefaultRecordsID
	0 dmUnusedRecordID
0 lstSelect.listID	1 dmModeReadOnly
2 lstSelect.pList	

```

2 dmModeWrite
3 dmModeReadWrite
4 dmModeLeaveOpen
8 dmModeExclusive
16 dmModeShowSecret

0 DmSearchStateType.info

0 SortRecordInfoType.attributes
1 SortRecordInfoType.uniqueID

1 dmSeekForward
-1 dmSeekBackward
(hex) A800 sysLibTrapBase
(hex) A800 sysLibTrapName
(hex) A801 sysLibTrapOpen
(hex) A802 sysLibTrapClose
(hex) A803 sysLibTrapSleep
(hex) A804 sysLibTrapWake
(hex) A805 sysLibTrapCustom
100 sysTicksPerSecond
0 sysAppLaunchCmdNormalLaunch
1 sysAppLaunchCmdFind
2 sysAppLaunchCmdGoTo
3 sysAppLaunchCmdSyncNotify
4 sysAppLaunchCmdTimeChange
5 sysAppLaunchCmdSystemReset
6 sysAppLaunchCmdAlarmTriggered
7 sysAppLaunchCmdDisplayAlarm
8 sysAppLaunchCmdCountryChange
9 sysAppLaunchCmdSyncRequestLocal
9 sysAppLaunchCmdSyncRequest
10 sysAppLaunchCmdSaveData
11 sysAppLaunchCmdInitDatabase
12 sysAppLaunchCmdSyncCallApplicationV10
13 sysAppLaunchCmdPanelCalledFromApp
14 sysAppLaunchCmdReturnFromPanel
15 sysAppLaunchCmdLookup
16 sysAppLaunchCmdSystemLock
17 sysAppLaunchCmdSyncRequestRemote
18 sysAppLaunchCmdHandleSyncCallApp
19 sysAppLaunchCmdAddRecord
20 sysSvcLaunchCmdSetServiceID
21 sysSvcLaunchCmdGetServiceID
22 sysSvcLaunchCmdGetServiceList
23 sysSvcLaunchCmdGetServiceInfo
24 sysAppLaunchCmdFailedAppNotify
25 sysAppLaunchCmdEventHook
26 sysAppLaunchCmdExgReceiveData
27 sysAppLaunchCmdExgAskUser
30 sysDialLaunchCmdDial
31 sysDialLaunchCmdHangUp
39 sysDialLaunchCmdLast
40 sysSvcLaunchCmdGetQuickEditLabel
49 sysSvcLaunchCmdLast
50 sysAppLaunchCmdURLParams
51 sysAppLaunchCmdNotify
52 sysAppLaunchCmdOpenDB
53 sysAppLaunchCmdAntennaUp
54 sysAppLaunchCmdGoToURL
55 sysAppLaunchNppiNoUI
56 sysAppLaunchNppiUI
57 sysAppLaunchCmdExgPreview
58 sysAppLaunchCmdCardLaunch
59 sysAppLaunchCmdExgGetData
60 sysAppLaunchCmdAttention
61 sysAppLaunchPnpsPreLaunch
63 sysAppLaunchCmdMultimediaEvent
(hex) 8000 sysAppLaunchCmdCustomBase
1 sysAppLaunchFlagNewThread
2 sysAppLaunchFlagNewStack
4 sysAppLaunchFlagNewGlobals
8 sysAppLaunchFlagUIApp
16 sysAppLaunchFlagSubCall
128 sysAppLaunchFlagDataRelocated
144 sysAppLaunchFlagPrivateSet

0 SysAppLaunchCmdSaveDataType.uiComing
1 SysAppLaunchCmdSaveDataType.reserved1

0 SysAppLaunchCmdSystemResetType.hardReset
1 SysAppLaunchCmdSystemResetType.createDefaultDB

0 SysAppLaunchCmdInitDatabaseType.dbP
4 SysAppLaunchCmdInitDatabaseType.creator
8 SysAppLaunchCmdInitDatabaseType.type
12 SysAppLaunchCmdInitDatabaseType.version

0 SysAppLaunchCmdSyncCallApplicationTypeV10.action
2 SysAppLaunchCmdSyncCallApplicationTypeV10.paramSize
4 SysAppLaunchCmdSyncCallApplicationTypeV10.paramP

8 SysAppLaunchCmdSyncCallApplicationTypeV10.remoteSocket
9 SysAppLaunchCmdSyncCallApplicationTypeV10.tid
10 SysAppLaunchCmdSyncCallApplicationTypeV10.handled
11 SysAppLaunchCmdSyncCallApplicationTypeV10.reserved1

0 SysAppLaunchCmdHandleSyncCallAppType.pbSize
2 SysAppLaunchCmdHandleSyncCallAppType.action
4 SysAppLaunchCmdHandleSyncCallAppType.paramP
8 SysAppLaunchCmdHandleSyncCallAppType.dwParamSize
12 SysAppLaunchCmdHandleSyncCallAppType.dlRefP
16 SysAppLaunchCmdHandleSyncCallAppType.handled
17 SysAppLaunchCmdHandleSyncCallAppType.reserved1
18 SysAppLaunchCmdHandleSyncCallAppType.replyErr
20 SysAppLaunchCmdHandleSyncCallAppType.dwReserved1
24 SysAppLaunchCmdHandleSyncCallAppType.dwReserved2

0 SysAppLaunchCmdFailedAppNotifyType.creator
4 SysAppLaunchCmdFailedAppNotifyType.type
8 SysAppLaunchCmdFailedAppNotifyType.result

0 SysAppLaunchCmdOpenDBType.cardNo
2 SysAppLaunchCmdOpenDBType.dbID

0 SysAppLaunchCmdCardType.err
2 SysAppLaunchCmdCardType.volRefNum
4 SysAppLaunchCmdCardType.path
8 SysAppLaunchCmdCardType.startFlags

1 sysAppLaunchStartFlagAutoStart
2 sysAppLaunchStartFlagNoUISwitch
4 sysAppLaunchStartFlagNoAutoDelete

0 SysAppLaunchCmdPnpsType.error
2 SysAppLaunchCmdPnpsType.volRefNum
4 SysAppLaunchCmdPnpsType.slotLibRefNum
6 SysAppLaunchCmdPnpsType.slotRefNum

0 SysAppInfoType.cmd
2 SysAppInfoType.cmdPBP
6 SysAppInfoType.launchFlags
8 SysAppInfoType.taskID
12 SysAppInfoType.codeH
16 SysAppInfoType.dbP
20 SysAppInfoType.stackP
24 SysAppInfoType.globalsChunkP
28 SysAppInfoType.memOwnerID
30 SysAppInfoType.dmAccessP
34 SysAppInfoType.dmLastErr
36 SysAppInfoType.errExceptionP
40 SysAppInfoType.a5Ptr
44 SysAppInfoType.stackEndP
48 SysAppInfoType.globalEndP
52 SysAppInfoType.rootP
56 SysAppInfoType.extraP

0 SysLibTblEntryType.dispatchTblP
4 SysLibTblEntryType.globalsP
8 SysLibTblEntryType.dbID
12 SysLibTblEntryType.codeRscH

0 sysDbgCommLibraryRefNum
(hex) C0FF sysDbgCommPortID
(hex) FFFF sysInvalidReNum

0 SysAppPrefs.priority
2 SysAppPrefs.stackSize
6 SysAppPrefs.minHeapSpace

1 sysExtPrefsVers
1 sysExtPrefsNoOverlayFlag

0 SysExtPrefsType.version
2 SysExtPrefsType.flags

1 sysFtrNumROMVersion
2 sysFtrNumProcessorID
(hex) FFFF0000 sysFtrNumProcessorMask
(hex) 10000 sysFtrNumProcessor328
(hex) 20000 sysFtrNumProcessorEZ
(hex) 30000 sysFtrNumProcessorVZ
(hex) 40000 sysFtrNumProcessorSuperVZ
(hex) 100000 sysFtrNumProcessorARM720T
(hex) 110000 sysFtrNumProcessorARM7TDMI
(hex) 120000 sysFtrNumProcessorARM920T
(hex) 130000 sysFtrNumProcessorARM922T
(hex) 140000 sysFtrNumProcessorARM925
(hex) 150000 sysFtrNumProcessorStrongARM
(hex) 160000 sysFtrNumProcessorXscale
(hex) 170000 sysFtrNumProcessorARM710A
(hex) 1000000 sysFtrNumProcessorx86
(hex) FFF00000 sysFtrNumProcessor68KIfZero
(hex) F00000 sysFtrNumProcessorARMIfNotZero

```

2	sysFtrNumProductID	2	serStatusRtsOn
3	sysFtrNumBacklight	4	serStatusDsrOn
4	sysFtrNumEncryption	8	serStatusBreakSigOn
1	sysFtrNumEncryptionMaskDES	1	serDevCradlePort
5	sysFtrNumCountry	2	serDevRS232Serial
6	sysFtrNumLanguage	4	serDevIRDACapable
7	sysFtrNumDisplayDepth	8	serDevModemPort
8	sysFtrNumHwrMiscFlags	16	serDevCncMgrVisible
9	sysFtrNumHwrMiscFlagsExt	32	serDevConsolePort
10	sysFtrNumIntlMgr	64	serDevUSBCapable
11	sysFtrNumEncoding		
12	sysFtrDefaultFont	0	DeviceInfoType.serDevCreator
13	sysFtrDefaultBoldFont	4	DeviceInfoType.serDevFtrInfo
14	sysFtrNumGremlinsSupportGlobals	8	DeviceInfoType.serDevMaxBaudRate
15	sysFtrNumVendor	12	DeviceInfoType.serDevHandshakeBaud
16	sysFtrNumCharEncodingFlags	16	DeviceInfoType.serDevPortInfoStr
17	sysFtrNumNotifyMgrVersion	20	DeviceInfoType.reserved
18	sysFtrNumOEMROMVersion		
20	sysFtrNumOEMCompanyID	0	serFncUndefined
21	sysFtrNumOEMDeviceID		
22	sysFtrNumOEMHALID	0	SrmOpenConfigType.baud
23	sysFtrNumDefaultCompression	4	SrmOpenConfigType.function
24	sysFtrNumWinVersion	8	SrmOpenConfigType.drivrDataP
25	sysFtrNumAccessorTrapPresent	12	SrmOpenConfigType.drivrDataSize
0	sysROMStageDevelopment	14	SrmOpenConfigType.sysReserved1
1	sysROMStageAlpha	18	SrmOpenConfigType.sysReserved2
2	sysROMStageBeta		
3	sysROMStageRelease		
0	sysBatteryKindAlkaline	0	serTransferFirstReserved
1	sysBatteryKindNiCad	1	serUSBInterruptMode
2	sysBatteryKindLiIon	2	serUSBBulkMode
3	sysBatteryKindRechAlk		
4	sysBatteryKindNiMH	0	SrmCallbackEntryType.funcP
5	sysBatteryKindLiIon1400	4	SrmCallbackEntryType.userRef
255	sysBatteryKindLast		
0	sysBatteryStateNormal	0	serCtlFirstReserved
1	sysBatteryStateLowBattery	1	serCtlSetBaudRate
2	sysBatteryStateCritBattery	2	serCtlGetBaudRate
3	sysBatteryStateShutdown	3	serCtlSetFlags
		4	serCtlGetFlags
		5	serCtlSetCtsTimeout
0	SysDBListItemType.name	6	serCtlGetCtsTimeout
32	SysDBListItemType.creator	7	serCtlStartBreak
36	SysDBListItemType.type	8	serCtlStopBreak
40	SysDBListItemType.version	9	serCtlStartLocalLoopback
42	SysDBListItemType.dbID	10	serCtlStopLocalLoopback
46	SysDBListItemType.cardNo	11	serCtlIrDAEnable
48	SysDBListItemType.iconP	12	serCtlIrDADisable
		13	serCtlRxEnable
		14	serCtlRxDisable
0	SysMailboxMsgType.data	15	serCtlEmuSetBlockingHook
		16	serCtlUserDef
0	sysEvGroupSignalConstant	17	serCtlGetOptimalTransmitSize
1	sysEvGroupSignalPulse	18	serCtlSetDTRAsserted
0	sysEvGroupWaitOR	19	serCtlGetDTRAsserted
1	sysEvGroupWaitAND	20	serCtlSetYieldPortCallback
0	sysFileDescStdIn	21	serCtlSetYieldPortRefCon
64	sysMaxHSIResponseSize		
(hex) 2580	sysHSISerialInquiryBaud	(hex) 7000	serCtlSystemReserved
6	sysHSISerialInquiryStringLen	(hex) 8000	serCtlCustom
3	sysHSISerialInterChrTimeout	(hex) 8001	serCtlLAST
11	sysHSISerialInquiryTimeout	(hex) 7000	serCtlSystemStart
		(hex) 8000	serCtlCustomStart
0	SysHSIResponseType.responseBuffer		
64	SysHSIResponseType.responseLength	0	sysSerialInstall
		1	sysSerialOpen
1	sysFtrNewSerialPresent	2	sysSerialOpenBkgnd
2	sysFtrNewSerialVersion	3	sysSerialClose
2	serMgrVersion	4	sysSerialSleep
(hex) 8000	serPortLocalHotSync	5	sysSerialWake
(hex) 8000	serPortCradlePort	6	sysSerialGetDeviceCount
(hex) 8001	serPortIrPort	7	sysSerialGetDeviceInfo
(hex) 8002	serPortConsolePort	8	sysSerialGetStatus
(hex) 8003	serPortCradleRS232Port	10	sysSerialControl
(hex) 8004	serPortCradleUSBPort	11	sysSerialSend
(hex) C000	serPortIDMask	12	sysSerialSendWait
1	serSettingsFlagStopBitsM	13	sysSerialSendCheck
0	serSettingsFlagStopBits1	14	sysSerialSendFlush
1	serSettingsFlagStopBits2	15	sysSerialReceive
2	serSettingsFlagParityOnM	16	sysSerialReceiveWait
4	serSettingsFlagParityEvenM	17	sysSerialReceiveCheck
8	serSettingsFlagXonXoffM	18	sysSerialReceiveFlush
16	serSettingsFlagRTSAutoM	19	sysSerialSetRcvBuffer
32	serSettingsFlagCTSAutoM	20	sysSerialRcvWindowOpen
192	serSettingsFlagBitsPerCharM	21	sysSerialRcvWindowClose
0	serSettingsFlagBitsPerChar5	22	sysSerialSetWakeUpHandler
64	serSettingsFlagBitsPerChar6	23	sysSerialPrimeWakeUpHandler
128	serSettingsFlagBitsPerChar7	24	sysSerialOpenV4
192	serSettingsFlagBitsPerChar8	25	sysSerialOpenBkgndV4
(hex) 100	serSettingsFlagFlowControlIn	26	sysSerialCustomControl
(hex) 200	serSettingsFlagRTSInactive	26	maxSerialSelector
(hex) 1D0	serDefaultSettings	1	kCncProfileNotifyCurrentVersion
500	serDefaultCTSTimeout		
1	serStatusCtsOn	0	CncProfileNotifyDetailsTag.version
		2	CncProfileNotifyDetailsTag.profileID

6	CncProfileNotifyDetailsTag.deviceKind	19	kCncParamReservedBit19
8	CncProfileNotifyDetailsTag.request	20	kCncParamReservedBit20
	0	21	kCncParamReservedBit21
	0	22	kCncParamReservedBit22
(hex) 8000	kCncNotifyBecomeCurrentModifier	23	kCncParamReservedBit23
(hex) 4000	kCncNotifyAlertUserModifier	24	kCncParamReservedBit24
(hex) C000	kNotifyRequestModifiersMask	25	kCncParamReservedBit25
	1	26	kCncParamReservedBit26
	2	27	kCncParamReservedBit27
	3	28	kCncParamReservedBit28
	4	29	kCncParamReservedBit29
	0	30	kCncParamReservedBit30
(hex) 8000	kCncParamThirdPartiesRange	31	kCncParamReservedBit31
	0	2047	kCncParamSystemFlagsNum
(hex) 4000	kCncParamVariableLength	2047	kCncParamSystemFlags
	2047	4	kCncParamSystemFlagsSize
(hex) 7800	kCncParamTypeMask	0	kCncParamReadOnly
	0	1	kCncParamReadOnlySize
	8	1	kCncParamInvisible
	0	1	kCncParamInvisibleSize
(hex) 800	kCncParamUInt8	2	kCncParamNonEditable
(hex) 1000	kCncParamUInt16	1	kCncParamNonEditableSize
(hex) 1800	kCncParamUInt32	3	kCncParamNoDetails
	1	1	kCncParamNoDetailsSize
	1	4	kCncParamLocked
	2	1	kCncParamLockedSize
	4	20530	kCncParamBluetoothDeviceAddr
(hex) 4800	kCncParamString	8	kCncParamBluetoothDeviceAddrSize
(hex) 5000	kCncParamBuffer	18483	kCncParamBluetoothDeviceName
	0	249	kCncParamBluetoothDeviceNameMaxSize
(hex) 40001.	kCncMgrVersion	6228	kCncParamSerialPortFlags
	22	4	kCncParamSerialPortFlagsSize
	81	6234	kCncParamTTType
	8	4	kCncParamTTTypeSize
	81	6235	kCncParamTTCreator
	0	4	kCncParamTTCreatorSize
	1	18524	kCncParam_PSDName
	2	32	kCncParam_PSDNameSize
	3	6237	kCncParam_PSDCreator
	0	4	kCncParam_PSDCreatorSize
	1	6238	kCncParam_PSDType
	2	4	kCncParam_PSDTypeSize
	4	20580	kCncParam_PSDParameterBuffer
	0	1	sysTrapCncMgrProfileSettingGet
	0	2	sysTrapCncMgrProfileSettingSet
18433	kCncParamName	3	sysTrapCncMgrProfileGetCurrent
	22	4	sysTrapCncMgrProfileSetCurrent
6146	kCncParamPort	5	sysTrapCncMgrProfileGetIDFromName
	4	6	sysTrapCncMgrProfileCreate
6147	kCncParamBaud	7	sysTrapCncMgrProfileDelete
	4	8	sysTrapCncMgrProfileGetIDFromIndex
4100	kCncParamVolume	9	sysTrapCncMgrProfileGetIndex
	2	10	sysTrapCncMgrProfileCount
4101	kCncParamFlowControl	11	sysTrapCncMgrProfileOpenDB
	2	12	sysTrapCncMgrProfileCloseDB
6150	kCncParamTimeOut	22	cncProfileNameSize
	4	1	lmChoiceLocale
18439	kCncParamInitString	5	lmChoiceCountryName
	81	6	lmChoiceDateFormat
18440	kCncParamResetString	7	lmChoiceLongDateFormat
	81	8	lmChoiceTimeFormat
4105	kCncParamDeviceKind	9	lmChoiceWeekStartDay
	2	10	lmChoiceTimeZone
4107	kCncParamCountryIndex	11	lmChoiceNumberFormat
	2	12	lmChoiceCurrencyName
2060	kCncParamDialingMode	13	lmChoiceCurrencySymbol
	1	14	lmChoiceUniqueCurrencySymbol
2061	kCncParamVersion	15	lmChoiceCurrencyDecimalPlaces
	1	16	lmChoiceMeasurementSystem
6158	kCncParamReceiveTimeOut	(hex) FFFF	lmAnyCountry
	4	(hex) FFFF	lmAnyLanguage
20495	kCncParamIntlModemResetStringList	19	kMaxCountryNameLen
(hex) 5010	kCncParamIntlModemCountryStringList	19	kMaxCurrencyNameLen
	0	5	kMaxCurrencySymbolLen
	1	0	lmInit
	2	1	lmGetNumLocales
	3	2	lmLocaleToIndex
	4	3	lmGetLocaleSetting
	5	3	lmMaxRoutineSelector
	6	0	LmLocaleType.language
	7	2	LmLocaleType.country
	8	0	tfColon
	9	1	tfColonAMPM
	10	2	tfColon24h
	11	3	tfDot
	12	4	tfDotAMPM
	13	5	tfDot24h
	14	6	tfHoursAMPM
	15	7	tfHours24h
	16	8	tfComma24h
	17		
	18		

0 dsNone	8 august
1 dsUSA	9 september
2 dsAustralia	10 october
3 dsWesternEuropean	11 november
4 dsMiddleEuropean	12 december
5 dsEasternEuropean	0 dom1stSun
6 dsGreatBritain	1 dom1stMon
7 dsRumania	2 dom1stTue
8 dsTurkey	3 dom1stWen
9 dsAustraliaShifted	4 dom1stThu
0 dfMDYWithSlashes	5 dom1stFri
1 dfDMYWithSlashes	6 dom1stSat
2 dfDMYWithDots	7 dom2ndSun
3 dfDMYWithDashes	8 dom2ndMon
4 dfYMDWithSlashes	9 dom2ndTue
5 dfYMDWithDots	10 dom2ndWen
6 dfYMDWithDashes	11 dom2ndThu
7 dfMDYLongWithComma	12 dom2ndFri
8 dfDMYLong	13 dom2ndSat
9 dfDMYLongWithDot	14 dom3rdSun
10 dfDMYLongNoDay	15 dom3rdMon
11 dfDMYLongWithComma	16 dom3rdTue
12 dfYMDLongWithDot	17 dom3rdWen
13 dfYMDLongWithSpace	18 dom3rdThu
14 dfMYMed	19 dom3rdFri
15 dfMYMedNoPost	20 dom3rdSat
16 dfMDYWithDashes	21 dom4thSun
	22 dom4thMon
0 DateTimeType.second	23 dom4thTue
2 DateTimeType.minute	24 dom4thWen
4 DateTimeType.hour	25 dom4thThu
6 DateTimeType.day	26 dom4thFri
8 DateTimeType.month	27 dom4thSat
10 DateTimeType.year	28 domLastSun
12 DateTimeType.weekDay	29 domLastMon
	30 domLastTue
0 TimeType.hours	31 domLastWen
1 TimeType.minutes	32 domLastThu
	33 domLastFri
-1 noTime	34 domLastSat
	94 dateTemplateChar
127 DateType.year.mask	48 dateTemplateDayNum
7 DateType.year.size	49 dateTemplateDOWNName
9 DateType.year.shift	50 dateTemplateMonthName
0 DateType.year	51 dateTemplateMonthNum
	52 dateTemplateYearNum
15 DateType.month.mask	115 dateTemplateShortModifier
4 DateType.month.size	114 dateTemplateRegularModifier
5 DateType.month.shift	108 dateTemplateLongModifier
0 DateType.month	122 dateTemplateLeadZeroModifier
	0 dbgCtlNotHandled
31 DateType.day.mask	1 dbgCtlHandled
5 DateType.day.size	0 dbgCtlAllHandlersID
0 DateType.day.shift	31 dbgCtlHandlerNameLen
0 DateType.day	15 dbgCtlHandlerVerLen
	(hex) 8000 dbgCtlFirstCustomOp
9 timeStringLength	
9 dateStringLength	0 DbgCtlHandlerInfoType.handlerFuncP
15 longDateStrLength	4 DbgCtlHandlerInfoType.version
19 dowDateStringLength	8 DbgCtlHandlerInfoType.enabled
25 dowLongDateStrLength	9 DbgCtlHandlerInfoType.name
50 timeZoneStringLength	41 DbgCtlHandlerInfoType.ver
(hex) 770 firstYear	57 DbgCtlHandlerInfoType.reserved1
128 numberOfYears	58 DbgCtlHandlerInfoType.dwReserved
2031 lastYear	
1 secondsInSeconds	0 DbgCtlEnumInfoType.enumFuncP
60 minutesInSeconds	4 DbgCtlEnumInfoType.callbackDataP
60 hoursInMinutes	
(hex) E10 hoursInSeconds	1 dbgCtlOpEnumHandlers
24 hoursPerDay	2 dbgCtlOpGetHandlerInfo
86400 daysInSeconds	3 dbgCtlOpEnableHandler
7 daysInWeek	4 dbgCtlOpDisableHandler
365 daysInYear	5 dbgCtlOpGetEnabledStatus
366 daysInLeapYear	6 dbgCtlOpGetVersion
1461 daysInFourYears	7 dbgCtlOpLAST
12 monthsInYear	9 exgSeparatorChar
(hex) B69F maxDays	(hex) FFFB exgRegCreatorID
(hex) F0C3EFFF maxSeconds	(hex) FFFC exgRegSchemeID
0 sunday	(hex) FFFD exgRegExtensionID
1 monday	(hex) FFFE exgRegTypeID
2 tuesday	0 exgDataPrefVersion
3 wednesday	20 exgTitleBufferSize
4 thursday	20 exgMaxTitleLen
5 friday	80 exgMaxTypeLength
6 saturday	80 exgMaxDescriptionLength
1 january	1 exgLibCtlGetTitle
2 february	2 exgLibCtlGetVersion
3 march	3 exgLibCtlGetPreview
4 april	4 exgLibCtlReserved4
5 may	(hex) 8000 exgLibCtlSpecificOp
6 june	0 exgLibAPIVersion
7 july	1 exgUnwrap



2	exgNoAsk	(hex) A817	exgLibTrapReserved9
4	exgGet	(hex) A818	exgLibTrapReserved10
0	exgPreviewQuery	(hex) A819	exgLibTrapLast
1	exgPreviewShortString	0	fileNullHandle
2	exgPreviewLongString	(hex) 80000000.	fileModeReadOnly
4	exgPreviewDraw	(hex) 40000000.	fileModeReadWrite
8	exgPreviewDialog	(hex) 20000000.	fileModeUpdate
(hex) 400	exgPreviewFirstUser	(hex) 10000000.	fileModeAppend
(hex) 8000	exgPreviewLastUser	(hex) 80000000.	fileModeLeaveOpen
		(hex) 40000000.	fileModeExclusive
0	ExgGoToType.dbCardNo	(hex) 20000000.	fileModeAnyTypeCreator
2	ExgGoToType.dbID	(hex) 10000000.	fileModeTemporary
6	ExgGoToType.recordNum	(hex) 80000000.	fileModeDontOverwrite
8	ExgGoToType.uniqueID	(hex) FF800000.	fileModeAllFlags
12	ExgGoToType.matchCustom	1	fileOriginBeginning
		2	fileOriginCurrent
0	ExgSocketType.libraryRef	3	fileOriginEnd
2	ExgSocketType.socketRef	0	fileOpNone
6	ExgSocketType.target	1	fileOpDestructiveReadMode
10	ExgSocketType.count	2	fileOpGetEOFStatus
14	ExgSocketType.length	6	fileOpGetCreatedStatus
18	ExgSocketType.time	7	fileOpGetOpenDbRef
22	ExgSocketType.appData	8	fileOpFlush
26	ExgSocketType.goToCreator	9	fileOpLAST
30	ExgSocketType.goToParams	(hex) 2008000.	flpVersion
1	ExgSocketType.localMode.mask	0	flpToNearest
1	ExgSocketType.localMode.size	1	flpTowardZero
15	ExgSocketType.localMode.shift	3	flpUpward
46	ExgSocketType.localMode	2	flpDownward
1	ExgSocketType.packetMode.mask	48	flpModeMask
1	ExgSocketType.packetMode.size	4	flpModeShift
14	ExgSocketType.packetMode.shift	(hex) 8000	flpInvalid
46	ExgSocketType.packetMode	(hex) 4000	flpOverflow
1	ExgSocketType.noGoTo.mask	(hex) 2000	flpUnderflow
1	ExgSocketType.noGoTo.size	(hex) 1000	flpDivByZero
13	ExgSocketType.noGoTo.shift	(hex) 800	flpInexact
46	ExgSocketType.noGoTo	0	flpEqual
1	ExgSocketType.noStatus.mask	1	flpLess
1	ExgSocketType.noStatus.size	2	flpGreater
12	ExgSocketType.noStatus.shift	3	flpUnordered
46	ExgSocketType.noStatus		
1	ExgSocketType.preview.mask	0	sfpe_64_bits.high
1	ExgSocketType.preview.size	4	sfpe_64_bits.low
11	ExgSocketType.preview.shift		
46	ExgSocketType.preview	1	FlpDoubleBits.sign.mask
2047	ExgSocketType.reserved.mask	1	FlpDoubleBits.sign.size
11	ExgSocketType.reserved.size	31	FlpDoubleBits.sign.shift
0	ExgSocketType.reserved.shift	0	FlpDoubleBits.sign
46	ExgSocketType.reserved		
48	ExgSocketType.description	2047	FlpDoubleBits.exp.mask
52	ExgSocketType.type	11	FlpDoubleBits.exp.size
56	ExgSocketType.name	20	FlpDoubleBits.exp.shift
		0	FlpDoubleBits.exp
0	exgAskDialog	(hex) FFFFFF.	FlpDoubleBits.manH.mask
1	exgAskOk	20	FlpDoubleBits.manH.size
2	exgAskCancel	0	FlpDoubleBits.manH.shift
		0	FlpDoubleBits.manH
0	ExgAskParamType.socketP		
4	ExgAskParamType.result		
5	ExgAskParamType.reserved	4	FlpDoubleBits.manL
0	ExgDialogInfoType.version	0	sysFloatBase10Info
2	ExgDialogInfoType.db	1	sysFloatFToA
6	ExgDialogInfoType.categoryIndex	2	sysFloatAToF
		3	sysFloatCorrectedAdd
0	ExgPreviewInfoType.version	4	sysFloatCorrectedSub
2	ExgPreviewInfoType.socketP	5	sysFloatVersion
6	ExgPreviewInfoType.op	5	flpMaxFloatSelector
8	ExgPreviewInfoType.string	0	sysFloatEm_fp_round
12	ExgPreviewInfoType.size	1	sysFloatEm_fp_get_fpscr
16	ExgPreviewInfoType.bounds	2	sysFloatEm_fp_set_fpscr
24	ExgPreviewInfoType.types	3	sysFloatEm_f_utof
26	ExgPreviewInfoType.error	4	sysFloatEm_f_itof
		5	sysFloatEm_f_ulltof
(hex) A805	exgLibTrapHandleEvent	6	sysFloatEm_f_lltof
(hex) A806	exgLibTrapConnect	7	sysFloatEm_d_utof
(hex) A807	exgLibTrapAccept	8	sysFloatEm_d_itof
(hex) A808	exgLibTrapDisconnect	9	sysFloatEm_d_ulltod
(hex) A809	exgLibTrapPut	10	sysFloatEm_d_lltod
(hex) A80A	exgLibTrapGet	11	sysFloatEm_f_ftof
(hex) A80B	exgLibTrapSend	12	sysFloatEm_d_dtof
(hex) A80C	exgLibTrapReceive	13	sysFloatEm_f_ftof
(hex) A80D	exgLibTrapControl	14	sysFloatEm_f_qtof
(hex) A80E	exgLibTrapRequest	15	sysFloatEm_d_dtof
(hex) A80F	exgLibTrapReserved1	16	sysFloatEm_d_qtod
(hex) A810	exgLibTrapReserved2	17	sysFloatEm_f_ftof
(hex) A811	exgLibTrapReserved3	18	sysFloatEm_f_ftoi
(hex) A812	exgLibTrapReserved4	19	sysFloatEm_f_ftoull
(hex) A813	exgLibTrapReserved5	20	sysFloatEm_f_ftoll
(hex) A814	exgLibTrapReserved6	21	sysFloatEm_d_dtou
(hex) A815	exgLibTrapReserved7	22	sysFloatEm_d_dtoi
(hex) A816	exgLibTrapReserved8	23	sysFloatEm_d_dtoull

24	sysFloatEm_d_dtoll	881	hostSelectorClock
25	sysFloatEm_f_cmp	882	hostSelectorCTime
26	sysFloatEm_f_cmpe	884	hostSelectorGMTIME
27	sysFloatEm_f_feq	885	hostSelectorLocalTime
28	sysFloatEm_f_fne	886	hostSelectorMkTime
29	sysFloatEm_f_flt	887	hostSelectorStrftime
30	sysFloatEm_f_fle	888	hostSelectorTime
31	sysFloatEm_f_fgt	(hex) 380	hostSelectorOpenDir
32	sysFloatEm_f_fge	897	hostSelectorReadDir
33	sysFloatEm_f_fun	899	hostSelectorCloseDir
34	sysFloatEm_f_for	916	hostSelectorRmdir
35	sysFloatEm_d_cmp	935	hostSelectorTruncate
36	sysFloatEm_d_cmpe	938	hostSelectorMkdir
37	sysFloatEm_d_feq	939	hostSelectorStat
38	sysFloatEm_d_fne	942	hostSelectorUTime
39	sysFloatEm_d_flt	943	hostSelectorGetFileAttr
40	sysFloatEm_d_fle	(hex) 3B0	hostSelectorSetFileAttr
41	sysFloatEm_d_fgt	(hex) 400	hostSelectorGremlinIsRunning
42	sysFloatEm_d_fge	1025	hostSelectorGremlinNumber
43	sysFloatEm_d_fun	1026	hostSelectorGremlinCounter
44	sysFloatEm_d_for	1027	hostSelectorGremlinLimit
45	sysFloatEm_f_neg	1028	hostSelectorGremlinNew
46	sysFloatEm_f_add	(hex) 500	hostSelectorImportFile
47	sysFloatEm_f_mul	1281	hostSelectorExportFile
48	sysFloatEm_f_sub	1282	hostSelectorSaveScreen
49	sysFloatEm_f_div	1283	hostSelectorImportFileWithID
50	sysFloatEm_d_neg	(hex) 580	hostSelectorExgLibOpen
51	sysFloatEm_d_add	1409	hostSelectorExgLibClose
52	sysFloatEm_d_mul	1410	hostSelectorExgLibSleep
53	sysFloatEm_d_sub	1411	hostSelectorExgLibWake
54	sysFloatEm_d_div	1412	hostSelectorExgLibHandleEvent
		1413	hostSelectorExgLibConnect
		1414	hostSelectorExgLibAccept
0	GrfMatchType.glyphID	1415	hostSelectorExgLibDisconnect
1	GrfMatchType.unCertainty	1416	hostSelectorExgLibPut
		1417	hostSelectorExgLibGet
4	grfMaxMatches	1418	hostSelectorExgLibSend
		1419	hostSelectorExgLibReceive
0	GrfMatchInfoType.numMatches	1420	hostSelectorExgLibControl
2	GrfMatchInfoType.match	1421	hostSelectorExgLibRequest
		(hex) 600	hostSelectorGetPreference
1	grfVirtualSequence	1537	hostSelectorSetPreference
2	grfShiftSequence	(hex) 700	hostSelectorLogFile
3	grfSpecialSequence	1793	hostSelectorSetLogFileSize
1	grfTempShiftPunctuation	(hex) 800	hostSelectorSessionCreate
2	grfTempShiftExtended	2049	hostSelectorSessionOpen
3	grfTempShiftUpper	2050	hostSelectorSessionClose
4	grfTempShiftLower	2051	hostSelectorSessionQuit
64	grfExpansionSequence	2052	hostSelectorSignalSend
68	expandDateChar	2053	hostSelectorSignalWait
84	expandTimeChar	2054	hostSelectorSignalResume
83	expandStampChar	2055	hostSelectorSessionSave
8	grfNameLength	(hex) 900	hostSelectorTraceInit
(hex) FFFF	grfNoShortCut	2305	hostSelectorTraceClose
(hex) 100	hostSelectorGetHostVersion	2306	hostSelectorTraceOutputT
257	hostSelectorGetHostID	2307	hostSelectorTraceOutputTL
258	hostSelectorGetHostPlatform	2308	hostSelectorTraceOutputVT
259	hostSelectorIsSelectorImplemented	2309	hostSelectorTraceOutputVTL
260	hostSelectorGestalt	2310	hostSelectorTraceOutputB
261	hostSelectorIsCallingTrap	(hex) 980	hostSelectorDbgSetDataBreak
(hex) 200	hostSelectorProfileInit	2433	hostSelectorDbgClearDataBreak
513	hostSelectorProfileStart	(hex) A00	hostSelectorSlotMax
514	hostSelectorProfileStop	2561	hostSelectorSlotRoot
515	hostSelectorProfileDump	2562	hostSelectorSlotHasCard
516	hostSelectorProfileCleanup	(hex) B00	hostSelectorGetFile
517	hostSelectorProfileDetailFn	2817	hostSelectorPutFile
518	hostSelectorProfileGetCycles	2818	hostSelectorGetDirectory
769	hostSelectorFClose	3071	hostSelectorLastTrapNumber
770	hostSelectorFEOF		0 HostDIRType._field
772	hostSelectorFFlush		0 HostDirEntType.d_name
773	hostSelectorFGetC		0 HostFILEType._field
774	hostSelectorFGetPos		0 HostGremlinInfoType.fFirstGremlin
775	hostSelectorFGetS	4	HostGremlinInfoType.fLastGremlin
776	hostSelectorFOpen	8	HostGremlinInfoType.fSaveFrequency
777	hostSelectorFPrintF	12	HostGremlinInfoType.fSwitchDepth
778	hostSelectorFPutC	16	HostGremlinInfoType.fMaxDepth
779	hostSelectorFPutS	20	HostGremlinInfoType.fAppNames
780	hostSelectorFRead		0 HostStatType.st_dev_
781	hostSelectorRemove	4	HostStatType.st_ino_
782	hostSelectorRename	8	HostStatType.st_mode_
783	hostSelectorFreopen	12	HostStatType.st_nlink_
(hex) 310	hostSelectorFScanF	16	HostStatType.st_uid_
785	hostSelectorFSeek	20	HostStatType.st_gid_
786	hostSelectorFSetPos	24	HostStatType.st_rdev_
787	hostSelectorFTell	28	HostStatType.st_atime_
788	hostSelectorFWrite	32	HostStatType.st_mtime_
789	hostSelectorTmpFile	36	HostStatType.st_ctime_
790	hostSelectorTmpNam		
791	hostSelectorGetEnv		
792	hostSelectorMalloc		
793	hostSelectorRealloc		
794	hostSelectorFree		
(hex) 370	hostSelectorAscTime		

40	HostStatType.st_size_	(hex) 8006	irSetSupported
44	HostStatType.st_blksize_	(hex) 8007	irSuppressScanning
48	HostStatType.st_blocks_	(hex) 8008	irRestoreScanning
52	HostStatType.st_flags_		
	0		IrStatsType.recLineErrors
	4		IrStatsType.crcErrors
	8	(hex) A80F	irLibTrapBind
12	HostTmType.tm_hour_	(hex) A810	irLibTrapUnBind
16	HostTmType.tm_mon_	(hex) A811	irLibTrapDiscoverReq
20	HostTmType.tm_year_	(hex) A812	irLibTrapConnectIrLap
24	HostTmType.tm_wday_	(hex) A813	irLibTrapDisconnectIrLap
28	HostTmType.tm_yday_	(hex) A814	irLibTrapConnectReq
32	HostTmType.tm_isdst_	(hex) A815	irLibTrapConnectRsp
	0	(hex) A816	irLibTrapDataReq
	4	(hex) A817	irLibTrapLocalBusy
	8	(hex) A818	irLibTrapMaxTxSize
	0	(hex) A819	irLibTrapMaxRxSize
	1	(hex) A81A	irLibTrapSetDeviceInfo
	2	(hex) A81B	irLibTrapIsNoProgress
	3	(hex) A81C	irLibTrapIsRemoteBusy
	4	(hex) A81D	irLibTrapIsMediaBusy
	5	(hex) A81E	irLibTrapIsIrLapConnected
	6	(hex) A81F	irLibTrapTestReq
	7	(hex) A820	irLibTrapIAS_Add
	8	(hex) A821	irLibTrapIAS_Query
	9	(hex) A822	irLibTrapIAS_SetDeviceName
	10	(hex) A823	irLibTrapIAS_Next
	11	(hex) A824	irLibTrapIrOpen
(hex) 4000	hostSignalUser	(hex) A825	irLibTrapHandleEvent
	1	(hex) A826	irLibTrapWaitForEvent
	2	(hex) A827	irLibTrapLast
	3		IR_CHAR_ISO_8859_1
	4		IR_CHAR_ISO_8859_2
	5		IR_CHAR_ISO_8859_3
	6		IR_CHAR_ISO_8859_4
	7		IR_CHAR_ISO_8859_5
	8		IR_CHAR_ISO_8859_6
	9		IR_CHAR_ISO_8859_7
	10		IR_CHAR_ISO_8859_8
	11		IR_CHAR_ISO_8859_9
	0		ListEntry.Flink
	1		ListEntry.Blink
	2		IrPacket.node
	3		IrPacket.buff
	4		IrPacket.len
	5		IrPacket.origin
	6		IrPacket.headerLen
	7		IrPacket.header
	8		IrPacket.reserved
	9		IrDeviceInfo.hDevice
	10		IrDeviceInfo.len
	11		IrDeviceInfo.xid
	12		IrDeviceList.nItems
	13		IrDeviceList.reserved
	14		IrDeviceList.dev
	15		IrCallbackParms.event
	16		IrCallbackParms.reserved1
	17		IrCallbackParms.rxBuff
	18		IrCallbackParms.rxBuff
	19		IrCallbackParms.rxBuff
	20		IrCallbackParms.rxBuff
	21		IrCallbackParms.packet
	22		IrCallbackParms.deviceList
	23		IrCallbackParms.status
	24		IrCallbackParms.reserved2
	25		hconnect.lLsap
	26		hconnect.rLsap
	27		hconnect.flags
	28		hconnect.reserved
	29		hconnect.callBack
	30		hconnect.packet
	31		hconnect.packets
	32		hconnect.sendCredit
	33		hconnect.availCredit
	34		hconnect.dataOff
	35		IrIasAttribute.name
	36		IrIasAttribute.len
	37		IrIasAttribute.reserved1
	38		IrIasAttribute.value
	39		IrIasAttribute.valLen
	40		IrIasAttribute.reserved2
(hex) 8001	irGetScanningMode		IrIasObject.name
(hex) 8002	irSetScanningMode		IrIasObject.len
(hex) 8003	irGetStatistics		IrIasObject.nAttribs
(hex) 8004	irSetSerialMode		IrIasObject.attribs
(hex) 8005	irSetBaudMask		

0	IrIasQuery.queryLen	2	netSocketNoticeEvent
1	IrIasQuery.reserved	3	netSocketNoticeMailbox
2	IrIasQuery.queryBuf	4	netSocketNoticeCallback
6	IrIasQuery.resultBufSize	5	netSocketNoticeWake
8	IrIasQuery.resultLen	0	SysNotifyNetSocketType.socketRef
10	IrIasQuery.listLen	2	SysNotifyNetSocketType.condition
12	IrIasQuery.offset	0	data.netSocketNotice.socketRef
14	IrIasQuery.retCode	2	data.netSocketNotice.condition
15	IrIasQuery.overflow	0	NetSocketNoticeEventType.eType
16	IrIasQuery.result	2	NetSocketNoticeEventType.penDown
20	IrIasQuery.callBack	3	NetSocketNoticeEventType.tapCount
		4	NetSocketNoticeEventType.screenX
1	keyBitPower	6	NetSocketNoticeEventType.screenY
2	keyBitPageUp	8	NetSocketNoticeEventType.data
4	keyBitPageDown	0	NetSocketNoticeMailboxType.message
8	keyBitHard1	4	NetSocketNoticeMailboxType.reserved
16	keyBitHard2	6	NetSocketNoticeMailboxType.socketRef
32	keyBitHard3	8	NetSocketNoticeMailboxType.condition
64	keyBitHard4	0	notice.wake.taskID
128	keyBitCradle	4	notice.wake.socketRefP
(hex) 100	keyBitAntenna	8	notice.wake.conditionP
(hex) 200	keyBitContrast	0	notice.callback.callbackP
-1	keyBitsAll	4	notice.callback.userDataP
255	slowestKeyDelayRate	0	notice.mailbox.mailboxID
255	slowestKeyPeriodRate	4	notice.mailbox.message
0	nfCommaPeriod	8	notice.mailbox.wAck
1	nfPeriodComma	0	notice.event.eType
2	nfSpaceComma	0	notice.notify.notifyType
3	nfApostrophePeriod	0	NetSocketNoticeType.condition
4	nfApostropheComma	4	NetSocketNoticeType.type
0	netFtrNumVersion	5	NetSocketNoticeType.notice
1	netFtrCommandBlocks	2	netSocketNoticeUDPReceive
(hex) FFFF	netConfigIndexCurSettings	4	netSocketNoticeTCPReceive
8	netDrvvrTypeLen	8	netSocketNoticeTCPTransmit
16	netDrvvrHWNameLen	16	netSocketNoticeTCPRemoteClosed
10	netIFNameLen	32	netSocketNoticeTCPClosed
14	netIFMaxHWAddrLen	64	netSocketNoticeConnectInbound
16	netMaxIPAddrStrLen	128	netSocketNoticeConnectOutbound
1	netWlAppEventFlagCTPOnly	0	NetSocketAddrINType.family
1	netSocketOptIPOptions	2	NetSocketAddrINType.port
1	netSocketOptTCPNoDelay	4	NetSocketAddrINType.addr
2	netSocketOptTCPMaxSeg	0	netIPAddrLocal
1	netSocketOptSockDebug	0	NetSocketAddrType.family
2	netSocketOptSockAcceptConn	2	NetSocketAddrType.data
4	netSocketOptSockReuseAddr	0	NetSocketAddrRawType.family
8	netSocketOptSockKeepAlive	0	BitmapTypeV3
16	netSocketOptSockDontRoute	2	NetSocketAddrRawType.ifInstance
32	netSocketOptSockBroadcast	4	NetSocketAddrRawType.ifCreator
64	netSocketOptSockUseLoopback	0	NetIOVecType.bufP
128	netSocketOptSockLinger	4	NetIOVecType.bufLen
(hex) 100	netSocketOptSockOOBInLine	16	netIOVecMaxLen
4097	netSocketOptSockSndBufSize	0	NetIOParamType.addrP
4098	netSocketOptSockRcvBufSize	4	NetIOParamType.addrLen
4099	netSocketOptSockSndLowWater	6	NetIOParamType.iov
4100	netSocketOptSockRcvLowWater	10	NetIOParamType.iovLen
4101	netSocketOptSockSndTimeout	12	NetIOParamType.accessRights
4102	netSocketOptSockRcvTimeout	16	NetIOParamType.accessRightsLen
4104	netSocketOptSockSocketType	1	netIOFlagOutOfBand
(hex) 2000	netSocketOptSockNonBlocking	2	netIOFlagPeek
8194	netSocketOptSockMultiPktAddr	4	netIOFlagDontRoute
8195	netSocketOptSockNotice	255	netDNSMaxDomainName
0	netSocketOptLevelIP	63	netDNSMaxDomainLabel
6	netSocketOptLevelTCP	1	netDNSMaxAliases
(hex) FFFF	netSocketOptLevelSocket	0	BitmapTypeV2
		4	netDNSMaxAddresses
0	NetSocketLingerType.onOff	0	NetHostInfoType.nameP
2	NetSocketLingerType.time	4	NetHostInfoType.nameAliasesP
		8	NetHostInfoType.addrType
0	netSocketAddrRaw	10	NetHostInfoType.addrLen
2	netSocketAddrINET		
1	netSocketTypeStream		
2	netSocketTypeDatagram		
3	netSocketTypeRaw		
4	netSocketTypeReliableMsg		
8	netSocketTypeLicensee		
1	netSocketProtoIPICMP		
6	netSocketProtoIPTCP		
17	netSocketProtoIPUDP		
255	netSocketProtoIPRAW		
0	netSocketDirInput		
1	netSocketDirOutput		
2	netSocketDirBoth		
1	netIFMediaUp		
2	netIFMediaDown		
0	SysNotifyNetLibIFMediaTag.eType		
1	SysNotifyNetLibIFMediaTag.ifCreator		
5	SysNotifyNetLibIFMediaTag.ifInstance		
1	netSocketNoticeNotify		

12	NetHostInfoType.addrListP	72	param.icmpStats.icmpOutSrcQuenchs
0	NetHostInfoBufType.hostInfo	76	param.icmpStats.icmpOutRedirects
16	NetHostInfoBufType.name	80	param.icmpStats.icmpOutEchos
(hex) 110	NetHostInfoBufType.aliasList	84	param.icmpStats.icmpOutEchoReps
280	NetHostInfoBufType.aliases	88	param.icmpStats.icmpOutTimestamps
536	NetHostInfoBufType.addressList	92	param.icmpStats.icmpOutTimestampReps
552	NetHostInfoBufType.address	96	param.icmpStats.icmpOutAddrMasks
		100	param.icmpStats.icmpOutAddrMaskReps
15	netServMaxName	0	param.ipStats.ipInReceives
15	netProtoMaxName	4	param.ipStats.ipInHdrErrors
1	netServMaxAliases	8	param.ipStats.ipInAddrErrors
0	NetServInfoType.nameP	12	param.ipStats.ipForwDatagrams
0	BitmapTypeV1	16	param.ipStats.ipInUnknownProtos
4	NetServInfoType.nameAliasesP	20	param.ipStats.ipInDiscards
8	NetServInfoType.port	24	param.ipStats.ipInDelivers
10	NetServInfoType.protoP	28	param.ipStats.ipOutRequests
0	NetServInfoBufType.servInfo	32	param.ipStats.ipOutDiscards
14	NetServInfoBufType.name	36	param.ipStats.ipOutNoRoutes
30	NetServInfoBufType.aliasList	40	param.ipStats.ipReasmReqds
38	NetServInfoBufType.aliases	44	param.ipStats.ipReasmOKs
53	NetServInfoBufType.protoName	48	param.ipStats.ipReasmFails
69	NetServInfoBufType.reserved	52	param.ipStats.ipFragOKs
		56	param.ipStats.ipFragFails
		60	param.ipStats.ipFragCreates
		64	param.ipStats.ipRoutingDiscards
		68	param.ipStats.ipDefaultTTL
		72	param.ipStats.ipReasmTimeout
32	netConfigNameSize	0	param.interfaceStats.index
0	NetConfigNameType.name	2	param.interfaceStats.inOctets
2	netTracingMsgs	6	param.interfaceStats.inUcastPkts
4	netTracingPktIP	10	param.interfaceStats.inNUcastPkts
0	BitmapTypeV0	14	param.interfaceStats.inDiscards
8	netTracingFuncs	18	param.interfaceStats.inErrors
16	netTracingAppMsgs	22	param.interfaceStats.inUnknownProtos
32	netTracingPktData40	26	param.interfaceStats.outOctets
64	netTracingPktData	30	param.interfaceStats.outUcastPkts
128	netTracingPktIFHi	34	param.interfaceStats.outNUcastPkts
(hex) 100	netTracingPktIFMid	38	param.interfaceStats.outDiscards
(hex) 200	netTracingPktIFLow	42	param.interfaceStats.outErrors
4	netTracingPkts	0	param.interfaceInfo.index
0	netMasterInterfaceInfo	2	param.interfaceInfo.creator
1	netMasterInterfaceStats	6	param.interfaceInfo.instance
2	netMasterIPStats	8	param.interfaceInfo.netIFP
3	netMasterICMPStats	12	param.interfaceInfo.drvrName
4	netMasterUDPStats	20	param.interfaceInfo.hwName
5	netMasterTCPStats	36	param.interfaceInfo.localNetHdrLen
6	netMasterTraceEventGet	37	param.interfaceInfo.localNetTrailerLen
0	param.traceEventGet.index	38	param.interfaceInfo.localNetMaxFrame
2	param.traceEventGet.textP	40	param.interfaceInfo.ifName
0	param.tcpStats.tcpRtoAlgorithm	50	param.interfaceInfo.driverUp
4	param.tcpStats.tcpRtoMin	51	param.interfaceInfo.ifUp
8	param.tcpStats.tcpRtoMax	52	param.interfaceInfo.hwAddrLen
12	param.tcpStats.tcpMaxConn	54	param.interfaceInfo.hwAddr
16	param.tcpStats.tcpActiveOpens	68	param.interfaceInfo.mtu
20	param.tcpStats.tcpPassiveOpens	70	param.interfaceInfo.speed
24	param.tcpStats.tcpAttemptFails	74	param.interfaceInfo.lastStateChange
28	param.tcpStats.tcpEstabResets	78	param.interfaceInfo.ipAddr
32	param.tcpStats.tcpCurrEstab	82	param.interfaceInfo.subnetMask
36	param.tcpStats.tcpInSegs	86	param.interfaceInfo.broadcast
40	param.tcpStats.tcpOutSegs	0	NetMasterPBType.param
44	param.tcpStats.tcpRetransSegs	0	netSettingResetAll
48	param.tcpStats.tcpInErrs	1	netSettingPrimaryDNS
52	param.tcpStats.tcpOutRsts	2	netSettingSecondaryDNS
0	param.udpStats.udpInDatagrams	3	netSettingDefaultRouter
4	param.udpStats.udpNoPorts	4	netSettingDefaultIFCreator
8	param.udpStats.udpInErrors	5	netSettingDefaultIFInstance
12	param.udpStats.udpOutDatagrams	6	netSettingHostName
0	param.icmpStats.icmpInMsgs	7	netSettingDomainName
4	param.icmpStats.icmpInErrors	8	netSettingHostTbl
8	param.icmpStats.icmpInDestUnreaches	9	netSettingCloseWaitTime
12	param.icmpStats.icmpInTimeExcds	10	netSettingInitialTCPResendTime
16	param.icmpStats.icmpInParmProbs	(hex) 1000	netSettingTraceBits
20	param.icmpStats.icmpInSrcQuenchs	4097	netSettingTraceSize
24	param.icmpStats.icmpInRedirects	4098	netSettingTraceStart
28	param.icmpStats.icmpInEchos	4099	netSettingTraceRoll
32	param.icmpStats.icmpInEchoReps	4100	netSettingRTPrimaryDNS
36	param.icmpStats.icmpInTimestamps	4101	netSettingRTSecondaryDNS
40	param.icmpStats.icmpInTimestampReps	4102	netSettingConfigTable
44	param.icmpStats.icmpInAddrMasks	0	netIFSettingResetAll
48	param.icmpStats.icmpInAddrMaskReps	1	netIFSettingUp
52	param.icmpStats.icmpOutMsgs	2	netIFSettingName
56	param.icmpStats.icmpOutErrors	3	netIFSettingReqIPAddr
60	param.icmpStats.icmpOutDestUnreaches	4	netIFSettingSubnetMask
64	param.icmpStats.icmpOutTimeExcds	5	netIFSettingBroadcast
68	param.icmpStats.icmpOutParmProbs	6	netIFSettingUsername
		7	netIFSettingPassword
		8	netIFSettingDialbackUsername

9	netIFSettingDialbackPassword	(hex) A823	netLibTrapIFUp
10	netIFSettingAuthUsername	(hex) A824	netLibTrapIFDown
11	netIFSettingAuthPassword	(hex) A825	netLibTrapIFMediaUp
12	netIFSettingServiceName	(hex) A826	netLibTrapScriptExecuteV32
13	netIFSettingLoginScript	(hex) A827	netLibTrapGetHostByAddr
14	netIFSettingConnectLog	(hex) A828	netLibTrapGetServByName
15	netIFSettingInactivityTimeout	(hex) A829	netLibTrapSocketAddr
16	netIFSettingEstablishmentTimeout	(hex) A82A	netLibTrapFinishCloseWait
17	netIFSettingDynamicIP	(hex) A82B	netLibTrapGetMailExchangeByName
18	netIFSettingVJCompEnable	(hex) A82C	netLibTrapPrefsAppend
19	netIFSettingVJCompSlots	(hex) A82D	netLibTrapIFMediaDown
20	netIFSettingMTU	(hex) A82E	netLibTrapOpenCount
21	netIFSettingAsyncCtlMap	(hex) A82F	netLibTrapTracePrintF
22	netIFSettingPortNum	(hex) A830	netLibTrapTracePutS
23	netIFSettingBaudRate	(hex) A831	netLibTrapOpenIfCloseWait
24	netIFSettingFlowControl	(hex) A832	netLibTrapHandlePowerOff
25	netIFSettingStopBits	(hex) A833	netLibTrapConnectionRefresh
26	netIFSettingParityOn	(hex) A834	netLibTrapBitMove
27	netIFSettingParityEven	(hex) A835	netLibTrapBitPutFixed
28	netIFSettingUseModem	(hex) A836	netLibTrapBitGetFixed
29	netIFSettingPulseDial	(hex) A837	netLibTrapBitPutUIntV
30	netIFSettingModemInit	(hex) A838	netLibTrapBitGetUIntV
31	netIFSettingModemPhone	(hex) A839	netLibTrapBitPutIntV
32	netIFSettingRedialCount	(hex) A83A	netLibTrapBitGetIntV
33	netIFSettingPowerUp	(hex) A83B	netLibOpenConfig
34	netIFSettingWireless	(hex) A83C	netLibConfigMakeActive
35	netIFSettingDNSQuery	(hex) A83D	netLibConfigList
36	netIFSettingQuitOnTxFail	(hex) A83E	netLibConfigIndexFromName
37	netIFSettingQueueSize	(hex) A83F	netLibConfigDelete
38	netIFSettingTxInQueue	(hex) A840	netLibConfigSaveAs
39	netIFSettingTxSent	(hex) A841	netLibConfigRename
40	netIFSettingTxDiscard	(hex) A842	netLibConfigAliasSet
41	netIFSettingRssi	(hex) A843	netLibConfigAliasGet
42	netIFSettingRssiAsPercent	(hex) A844	netLibTrapScriptExecute
43	netIFSettingRadioState	(hex) A845	netLibTrapLast
44	netIFSettingBase	8	bitsInByte
45	netIFSettingRadioID	36	bitVarIntMaxBits
46	netIFSettingBattery	5	bitVarIntMaxBytes
47	netIFSettingNetworkLoad		
48	netIFSettingConnectionName	0	SysNotifyParamType.notifyType
(hex) 1000	netIFSettingTraceBits	4	SysNotifyParamType.broadcaster
4097	netIFSettingGlobalsPtr	8	SysNotifyParamType.notifyDetailsP
4098	netIFSettingActualIPAddr	12	SysNotifyParamType.userDataP
4099	netIFSettingServerIPAddr	16	SysNotifyParamType.handled
4100	netIFSettingBringDownOnPowerDown	17	SysNotifyParamType.reserved2
4101	netIFSettingRawMode	0	sysNotifyNormalPriority
4102	netIFSettingLocRawInfo	-1	sysNotifyNoDatabaseID
4103	netIFSettingDriverVersion	1	sysNotifyVersionNum
4104	netIFSettingFirmwareVersion	30	sysNotifyDefaultQueueSize
4105	netIFSettingFirmwareDate		
4106	netIFSetting80211Device	0	SysNotifyAppLaunchOrQuitTag.version
4107	netIFSetting80211ESSID	4	SysNotifyAppLaunchOrQuitTag.dbID
4108	netIFSetting80211AccessPointBSSID	8	SysNotifyAppLaunchOrQuitTag.cardNo
4109	netIFSetting80211AssociationStatus		
4110	netIFSetting80211MKKCallSign	0	SysNotifyVirtualCharHandlingTag.version
4111	netIFSetting80211CountryText	4	SysNotifyVirtualCharHandlingTag.keyDown
(hex) 8000	netIFSettingCustom		
0	netRadioStateOffNotConnected	0	SysNotifyPenStrokeTag.version
1	netRadioStateOnNotConnected	4	SysNotifyPenStrokeTag.startPt
2	netRadioStateOnConnected	8	SysNotifyPenStrokeTag.endPt
3	netRadioStateOffConnected		
32	netFDSetsize		
(hex) A805	netLibTrapAddrINToA	0	SysNotifyDisplayChangeDetailsTag.oldDepth
(hex) A806	netLibTrapAddrAToIN	4	SysNotifyDisplayChangeDetailsTag.newDepth
(hex) A807	netLibTrapSocketOpen		
(hex) A808	netLibTrapSocketClose	0	SysNotifyLocaleChangedTag.oldLocale
(hex) A809	netLibTrapSocketOptionSet	4	SysNotifyLocaleChangedTag.newLocale
(hex) A80A	netLibTrapSocketOptionGet		
(hex) A80B	netLibTrapSocketBind	0	sysSleepPowerButton
(hex) A80C	netLibTrapSocketConnect	1	sysSleepAutoOff
(hex) A80D	netLibTrapSocketListen	2	sysSleepResumed
(hex) A80E	netLibTrapSocketAccept	3	sysSleepUnknown
(hex) A80F	netLibTrapSocketShutdown		
(hex) A810	netLibTrapSendPB	0	SleepEventParamTag.reason
(hex) A811	netLibTrapSend	2	SleepEventParamTag.deferSleep
(hex) A812	netLibTrapReceivePB		
(hex) A813	netLibTrapReceive	0	SysNotifyDBInfoTag.dbID
(hex) A814	netLibTrapDmReceive	4	SysNotifyDBInfoTag.cardNo
(hex) A815	netLibTrapSelect	6	SysNotifyDBInfoTag.attributes
(hex) A816	netLibTrapPrefsGet	8	SysNotifyDBInfoTag.dbName
(hex) A817	netLibTrapPrefsSet	40	SysNotifyDBInfoTag.creator
(hex) A818	netLibTrapDrvrvWake	44	SysNotifyDBInfoTag.type
(hex) A819	netLibTrapInterfacePtr		
(hex) A81A	netLibTrapMaster	0	SysNotifyDBDeletedTag.oldDBID
(hex) A81B	netLibTrapGetHostByName	4	SysNotifyDBDeletedTag.cardNo
(hex) A81C	netLibTrapSettingGet	6	SysNotifyDBDeletedTag.attributes
(hex) A81D	netLibTrapSettingSet	8	SysNotifyDBDeletedTag.dbName
(hex) A81E	netLibTrapIFAttach	40	SysNotifyDBDeletedTag.creator
(hex) A81F	netLibTrapIFDetach	44	SysNotifyDBDeletedTag.type
(hex) A820	netLibTrapIFGet		
(hex) A821	netLibTrapIFSettingGet	0	SysNotifyDBCreatedTag.dbName
(hex) A822	netLibTrapIFSettingSet	32	SysNotifyDBCreatedTag.creator

36 SysNotifyDBCcreatedTag.type	25 lCorsican
40 SysNotifyDBCcreatedTag.newDBID	26 lCzech
44 SysNotifyDBCcreatedTag.cardNo	27 lWelsh
46 SysNotifyDBCcreatedTag.resDB	28 lDanish
47 SysNotifyDBCcreatedTag.padding	29 lBhutani
0 SysNotifyDBChangedTag.dbName	30 lGreek
32 SysNotifyDBChangedTag.dbID	31 lEsperanto
36 SysNotifyDBChangedTag.creator	32 lEstonian
40 SysNotifyDBChangedTag.type	33 lBasque
44 SysNotifyDBChangedTag.crDate	34 lPersian
48 SysNotifyDBChangedTag.modDate	35 lFinnish
52 SysNotifyDBChangedTag.bckUpDate	36 lFiji
56 SysNotifyDBChangedTag.modNum	37 lFaroese
60 SysNotifyDBChangedTag.appInfoID	38 lFrisian
64 SysNotifyDBChangedTag.sortInfoID	39 lIrish
68 SysNotifyDBChangedTag.attributes	40 lScotsGaelic
70 SysNotifyDBChangedTag.cardNo	41 lGalician
72 SysNotifyDBChangedTag.version	42 lGuarani
74 SysNotifyDBChangedTag.fields	43 lGujarati
76 SysNotifyDBChangedTag.oldName	44 lHausa
108 SysNotifyDBChangedTag.oldCreator	45 lHindi
112 SysNotifyDBChangedTag.oldType	46 lCroatian
116 SysNotifyDBChangedTag.oldAttributes	47 lHungarian
118 SysNotifyDBChangedTag.padding	48 lArmenian
1 DBChangedFieldSetName	49 lInterlingua
2 DBChangedFieldSetCreator	50 lInterlingue
4 DBChangedFieldSetType	51 lInupiak
8 DBChangedFieldSetCrDate	52 lIndonesian
16 DBChangedFieldSetModDate	53 lIcelandic
32 DBChangedFieldSetBckUpDate	54 lHebrew
64 DBChangedFieldSetModNum	55 lYiddish
128 DBChangedFieldSetAppInfo	56 lJavanese
(hex) 100 DBChangedFieldSetSortInfo	57 lGeorgian
(hex) 200 DBChangedFieldSetAttributes	58 lKazakh
(hex) 400 DBChangedFieldSetVersion	59 lGreenlandic
0 SysNotifyDBDirtyTag.dbName	60 lCambodian
32 SysNotifyDBDirtyTag.creator	61 lKannada
36 SysNotifyDBDirtyTag.type	62 lKorean
1000 omOverlayRscID	63 lKashmiri
1 omFtrDefaultLocale	64 lKurdish
0 omInit	65 lKirghiz
1 omOpenOverlayDatabase	66 lLatin
2 omLocaleToOverlayDBName	67 lLingala
3 omOverlayDBNameToLocale	68 lLaothian
4 omGetCurrentLocale	69 lLithuanian
5 omGetIndexedLocale	70 lLatvian
6 omGetSystemLocale	71 lMalagasy
7 omSetSystemLocale	72 lMaori
8 omGetRoutineAddress	73 lMacedonian
9 omGetNextSystemLocale	74 lMalayalam
9 omMaxSelector	75 lMongolian
0 OmSearchStateType.searchState	76 lMoldavian
32 OmSearchStateType.systemDBRef	77 lMarathi
36 OmSearchStateType.systemDBCard	78 lMalay
38 OmSearchStateType.systemDBName	79 lMaltese
70 OmSearchStateType.systemDBNameLen	80 lBurmese
72 OmSearchStateType.curLocale	81 lNauru
76 OmSearchStateType.didNoOverlaySystem	82 lNepali
77 OmSearchStateType.foundSystem	83 lNorwegian
78 OmSearchStateType.reserved	84 lOccitan
40 maxEncodingNameLength	85 lAfan
0 lEnglish	86 lOriya
1 lFrench	87 lPunjabi
2 lGerman	88 lPolish
3 lItalian	89 lPashto
4 lSpanish	90 lPortuguese
5 lUnused	91 lQuechua
6 lJapanese	92 lRhaetoRomance
7 lDutch	93 lKurundi
8 lAfar	94 lRomanian
9 lAbkhazian	95 lRussian
10 lAfrikaans	96 lKinyarwanda
11 lAmharic	97 lSanskrit
12 lArabic	98 lSindhi
13 lAssamese	99 lSangho
14 lAymara	100 lSerboCroatian
15 lAzerbaijani	101 lSinghalese
16 lBashkir	102 lSlovak
17 lByelorussian	103 lSlovenian
18 lBulgarian	104 lSamoan
19 lBihari	105 lShona
20 lBislama	106 lSomali
21 lBengali	107 lAlbanian
22 lTibetan	108 lSerbian
23 lBreton	109 lSiswati
24 lCatalan	110 lSesotho
	111 lSudanese
	112 lSwedish
	113 lSwahili
	114 lTamil
	115 lTelugu
	116 lTajik

117	lThai	72	cColumbia
118	lTigrinya	73	cCostaRica
119	lTurkmen	74	cCuba
120	lTagalog	75	cCapeVerde
121	lSetswana	76	cChristmasIsland
122	lTonga	77	cCyprus
123	lTurkish	78	cCzechRepublic
124	lTsonga	79	cDjibouti
125	lTatar	80	cDominica
126	lTwi	81	cDominicanRepublic
127	lUkrainian	82	cAlgeria
128	lUrdu	83	cEcuador
129	lUzbek	84	cEstonia
130	lVietnamese	85	cEgypt
131	lVolapuk	86	cWesternSahara
132	lWolof	87	cEritrea
133	lXhosa	88	cEthiopia
134	lYoruba	89	cFiji
135	lChinese	90	cFalklandIslands
136	lZulu	91	cMicronesia
0	cAustralia	92	cFaeroeIslands
1	cAustria	93	cMetropolitanFrance
2	cBelgium	94	cGabon
3	cBrazil	95	cGrenada
4	cCanada	96	cGeorgia
5	cDenmark	97	cFrenchGuiana
6	cFinland	98	cGhana
7	cFrance	99	cGibraltar
8	cGermany	100	cGreenland
9	cHongKong	101	cGambia
10	cIceland	102	cGuinea
11	cIreland	103	cGuadeloupe
12	cItaly	104	cEquatorialGuinea
13	cJapan	105	cGreece
14	cLuxembourg	106	cSouthGeorgiaAndTheSouthSandwichIslands
15	cMexico	107	cGuatemala
16	cNetherlands	108	cGuam
17	cNewZealand	109	cGuineaBisseu
18	cNorway	110	cGuyana
19	cSpain	111	cHeardAndMcDonaldIslands
20	cSweden	112	cHonduras
21	cSwitzerland	113	cCroatia
22	cUnitedKingdom	114	cHaiti
23	cUnitedStates	115	cHungary
24	cIndia	116	cIsrael
25	cIndonesia	117	cBritishIndianOceanTerritory
26	cRepublicOfKorea	118	cIraq
27	cMalaysia	119	cIran
28	cChina	120	cJamaica
29	cPhilippines	121	cJordan
30	cSingapore	122	cKenya
31	cThailand	123	cKyrgyzstan
32	cTaiwan	124	cCambodia
33	cAndorra	125	cKiribati
34	cUnitedArabEmirates	126	cComoros
35	cAfghanistan	127	cStKittsAndNevis
36	cAntiguaAndBarbuda	128	cDemocraticPeoplesRepublicOfKorea
37	cAnguilla	129	cKuwait
38	cAlbania	130	cCaymanIslands
39	cArmenia	131	cKazakhstan
40	cNetherlandsAntilles	132	cLaos
41	cAngola	133	cLebanon
42	cAntarctica	134	cStLucia
43	cArgentina	135	cLiechtenstein
44	cAmericanSamoa	136	cSriLanka
45	cAruba	137	cLiberia
46	cAzerbaijan	138	cLesotho
47	cBosniaAndHerzegovina	139	cLithuania
48	cBarbados	140	cLatvia
49	cBangladesh	141	cLibya
50	cBurkinaFaso	142	cMorocco
51	cBulgaria	143	cMonaco
52	cBahrain	144	cMoldova
53	cBurundi	145	cMadagascar
54	cBenin	146	cMarshallIslands
55	cBermuda	147	cMacedonia
56	cBruneiDarussalam	148	cMali
57	cBolivia	149	cMyanmar
58	cBahamas	150	cMongolia
59	cBhutan	151	cMacau
60	cBouvetIsland	152	cNorthernMarianaIslands
61	cBotswana	153	cMartinique
62	cBelarus	154	cMauritania
63	cBelize	155	cMontserrat
64	cCocosIslands	156	cMalta
65	cDemocraticRepublicOfTheCongo	157	cMauritius
66	cCentralAfricanRepublic	158	cMaldives
67	cCongo	159	cMalawi
68	cIvoryCoast	160	cMozambique
69	cCookIslands	161	cNamibia
70	cChile	162	cNewCaledonia
71	cCameroon	163	cNiger



164	cNorfolkIsland	8	kAttnFlagsAlwaysCustomEffect
165	cNigeria	(hex) FFFF	kAttnFlagsEverything
166	cNicaragua	(hex) 10000.	kAttnFlagsNoSound
167	cNepal	(hex) 20000.	kAttnFlagsNoLED
168	cNauru	(hex) 40000.	kAttnFlagsNoVibrate
169	cNiue	(hex) 80000.	kAttnFlagsNoCustomEffect
170	cOman	(hex) FFFF0000.	kAttnFlagsNothing
171	cPanama	0	kAttnFtrCapabilities
172	cPeru	1	kAttnFlagsUserWantsSound
173	cFrenchPolynesia	2	kAttnFlagsUserWantsLED
174	cPapuaNewGuinea	4	kAttnFlagsUserWantsVibrate
175	cPakistan	8	kAttnFlagsUserWantsCustomEffect
176	cPoland	(hex) FFFF	kAttnFlagsUserSettingsMask
177	cStPierreAndMiquelon	(hex) 10000.	kAttnFlagsHasSound
178	cPitcairn	(hex) 20000.	kAttnFlagsHasLED
179	cPuertoRico	(hex) 40000.	kAttnFlagsHasVibrate
180	cPortugal	(hex) 80000.	kAttnFlagsHasCustomEffect
181	cPalau	(hex) FFFF0000.	kAttnFlagsCapabilitiesMask
182	cParaguay	0	kAttnLevelInsistent
183	cQatar	1	kAttnLevelSubtle
184	cReunion	1	kAttnCommandDrawDetail
185	cRomania	2	kAttnCommandDrawList
186	cRussianFederation	3	kAttnCommandPlaySound
187	cRwanda	4	kAttnCommandCustomEffect
188	cSaudiArabia	5	kAttnCommandGoThere
189	cSolomonIslands	6	kAttnCommandGotIt
190	cSeychelles	7	kAttnCommandSnooze
191	cSudan	8	kAttnCommandIterate
192	cStHelena		
193	cSlovenia	0	AttnCommandArgsIterateTag.iterationData
194	cSvalbardAndJanMayenIslands		
195	cSlovakia	0	AttnCommandArgsGotItTag.dismissedByUser
196	cSierraLeone		
197	cSanMarino	0	AttnCommandArgsDrawListTag.bounds
198	cSenegal	8	AttnCommandArgsDrawListTag.firstTime
199	cSomalia	9	AttnCommandArgsDrawListTag.flags
200	cSuriname	13	AttnCommandArgsDrawListTag.selected
201	cSaoTomeAndPrincipe		
202	cElSalvador	0	AttnCommandArgsDrawDetailTag.bounds
203	cSyranArabRepublic	8	AttnCommandArgsDrawDetailTag.firstTime
204	cSwaziland	9	AttnCommandArgsDrawDetailTag.flags
205	cTurksAndCaicosIslands		
206	cChad	0	AttnLaunchCodeArgsType.command
207	cFrenchSouthernTerritories	2	AttnLaunchCodeArgsType.userData
208	cTogo	6	AttnLaunchCodeArgsType.commandArgsP
209	cTajikistan		
210	cTokelau	0	AttnNotifyDetailsType.flags
211	cTurkmenistan		
212	cTunisia	-1	noPreferenceFound
213	cTonga	2	preferenceDataVer2
214	cEastTimor	3	preferenceDataVer3
215	cTurkey	4	preferenceDataVer4
216	cTrinidadAndTobago	5	preferenceDataVer5
217	cTuvalu	6	preferenceDataVer6
218	cTanzania	8	preferenceDataVer8
219	cUkraine	9	preferenceDataVer9
220	cUganda	10	preferenceDataVer10
221	cUnitedStatesMinorOutlyingIslands	11	preferenceDataVer11
222	cUruguay	11	preferenceDataVerLatest
223	cUzbekistan	2	defaultAutoOffDuration
224	cHolySee	120	defaultAutoOffDurationSecs
225	cStVincentAndTheGrenadines	255	peggedAutoOffDuration
226	cVenezuela	(hex) FFFF	peggedAutoOffDurationSecs
227	cBritishVirginIslands	0	defaultAutoLockType
228	cUSVirginIslands	0	defaultAutoLockTime
229	cVietNam	0	defaultAutoLockTimeFlag
230	cVanuatu	0	defaultSysSoundLevel
231	cWallisAndFutunaIslands	0	defaultGameSoundLevel
232	cSamoa	0	defaultAlarmSoundLevel
233	cYemen	64	defaultSysSoundVolume
234	cMayotte	64	defaultGameSoundVolume
235	cYugoslavia	64	defaultAlarmSoundVolume
236	cSouthAfrica	0	unitsEnglish
237	cZambia	1	unitsMetric
238	cZimbabwe	0	slOn
32	pwdLength	1	slOff
64	pwdEncryptionKeyLength	0	never
0	kAttnIndicatorLeft	1	uponPowerOff
0	kAttnIndicatorTop	2	atPresetTime
16	kAttnIndicatorWidth	3	afterPresetDelay
15	kAttnIndicatorHeight	0	alOff
15	kAttnListMaxIconWidth	1	alEventsOnly
17	kAttnListTextOffset	2	alEventsAndRandom
1	kAttnFlagsSoundBit	3	alEventsAndMoreRandom
2	kAttnFlagsLEDBit	0	prefVersion
4	kAttnFlagsVibrateBit	1	prefCountry
8	kAttnFlagsCustomEffectBit	2	prefDateFormat
(hex) FFFF	kAttnFlagsAllBits	3	prefLongDateFormat
0	kAttnFlagsUseUserSettings	4	prefWeekStartDay
1	kAttnFlagsAlwaysSound	5	prefTimeFormat
2	kAttnFlagsAlwaysLED	6	prefNumberFormat
4	kAttnFlagsAlwaysVibrate	7	prefAutoOffDuration

8	prefSysSoundLevelV20	44	SystemPreferencesType.calcCharAppCreator
9	prefGameSoundLevelV20	48	SystemPreferencesType.hardCradleCharAppCreator
10	prefAlarmSoundLevelV20	52	SystemPreferencesType.launcherCharAppCreator
11	prefHidePrivateRecordsV33	56	SystemPreferencesType.hardCradle2CharAppCreator
12	prefDeviceLocked	60	SystemPreferencesType.animationLevel
13	prefLocalSyncRequiresPassword	61	SystemPreferencesType.maskPrivateRecords
14	prefRemoteSyncRequiresPassword	62	SystemPreferencesType.sysSoundVolume
15	prefSysBatteryKind	64	SystemPreferencesType.gameSoundVolume
16	prefAllowEasterEggs	66	SystemPreferencesType.alarmSoundVolume
17	prefMinutesWestOfGMT	68	SystemPreferencesType.beamReceive
18	prefDaylightSavings	69	SystemPreferencesType.calibrateDigitizerAtReset
19	prefRonamaticChar	70	SystemPreferencesType.systemKeyboardID
20	prefHard1CharAppCreator	72	SystemPreferencesType.defSerialPlugIn
21	prefHard2CharAppCreator	76	SystemPreferencesType.stayOnWhenPluggedIn
22	prefHard3CharAppCreator	77	SystemPreferencesType.stayLitWhenPluggedIn
23	prefHard4CharAppCreator	78	SystemPreferencesType.antennaCharAppCreator
24	prefCalcCharAppCreator	82	SystemPreferencesType.measurementSystem
25	prefHardCradleCharAppCreator	83	SystemPreferencesType.reserved3
26	prefLauncherAppCreator	84	SystemPreferencesType.autoOffDurationSecs
27	prefSysPrefFlags	86	SystemPreferencesType.timeZone
28	prefHardCradle2CharAppCreator	88	SystemPreferencesType.daylightSavingAdjustment
29	prefAnimationLevel	90	SystemPreferencesType.timeZoneCountry
30	prefSysSoundVolume	91	SystemPreferencesType.autoLockType
31	prefGameSoundVolume	92	SystemPreferencesType.autoLockTime
32	prefAlarmSoundVolume	96	SystemPreferencesType.autoLockTimeFlag
33	prefBeamReceive	97	SystemPreferencesType.language
34	prefCalibrateDigitizerAtReset	98	SystemPreferencesType.attentionFlags
35	prefSystemKeyboardID	102	SystemPreferencesType.defaultAppCreator
36	prefDefSerialPlugIn	106	SystemPreferencesType.defFepPlugInCreator
37	prefStayOnWhenPluggedIn	110	SystemPreferencesType.colorThemeID
38	prefStayLitWhenPluggedIn		
39	prefAntennaCharAppCreator		
40	prefMeasurementSystem	0	ButtonDefaultAppType.keyCode
41	prefShowPrivateRecords	2	ButtonDefaultAppType.creator
42	prefAutoOffDurationSecs		
43	prefTimeZone	0	ButtonDefaultListType.numButtons
44	prefDaylightSavingAdjustment	2	ButtonDefaultListType.button
45	prefAutoLockType		
46	prefAutoLockTime	(hex) 8000	scptLaunchCmdDoNothing
47	prefAutoLockTimeFlag	(hex) 8001	scptLaunchCmdListCmds
48	prefLanguage	(hex) 8002	scptLaunchCmdExecuteCmd
49	prefLocale	0	pluginNetLibDoNothing
50	prefTimeZoneCountry	1	pluginNetLibReadBytes
51	prefAttentionFlags	2	pluginNetLibWriteBytes
52	prefDefaultAppCreator	3	pluginNetLibGetUserName
53	prefDefFepPlugInCreator	4	pluginNetLibGetUserPwd
54	prefColorThemeID	5	pluginNetLibCheckCancelStatus
		6	pluginNetLibPromptUser
		7	pluginNetLibConnLog
		8	pluginNetLibCallUIProc
		9	pluginNetLibGetSerLibRefNum
0	SystemPreferencesTypeV10.version	15	pluginMaxCmdNameLen
2	SystemPreferencesTypeV10.country	15	pluginMaxModuleNameLen
3	SystemPreferencesTypeV10.dateFormat	10	pluginMaxNumOfCmds
4	SystemPreferencesTypeV10.longDateFormat	63	pluginMaxLenTxtStringArg
5	SystemPreferencesTypeV10.weekStartDay		
6	SystemPreferencesTypeV10.timeFormat	0	PluginCmdType.commandName
7	SystemPreferencesTypeV10.numberFormat	16	PluginCmdType.hasTxtStringArg
8	SystemPreferencesTypeV10.autoOffDuration	17	PluginCmdType.reserved
9	SystemPreferencesTypeV10.sysSoundLevel		
10	SystemPreferencesTypeV10.alarmSoundLevel	0	PluginInfoType.pluginName
11	SystemPreferencesTypeV10.hideSecretRecords	16	PluginInfoType.numOfCommands
12	SystemPreferencesTypeV10.deviceLocked	18	PluginInfoType.command
13	SystemPreferencesTypeV10.reserved1		
14	SystemPreferencesTypeV10.sysPrefFlags		
16	SystemPreferencesTypeV10.sysBatteryKind	0	PluginCallbackProcType.selectorProcP
17	SystemPreferencesTypeV10.reserved2		
		0	PluginExecCmdType.commandName
0	SystemPreferencesType.version	16	PluginExecCmdType.txtStringArg
2	SystemPreferencesType.country	80	PluginExecCmdType.procP
3	SystemPreferencesType.dateFormat	84	PluginExecCmdType.handle
4	SystemPreferencesType.longDateFormat		
5	SystemPreferencesType.weekStartDay		
6	SystemPreferencesType.timeFormat	0	kDrvrCreator
7	SystemPreferencesType.numberFormat	0	kDrvrResID
8	SystemPreferencesType.autoOffDuration	3	kDrvrVersion3
9	SystemPreferencesType.sysSoundLevelV20	4	kDrvrVersion4
10	SystemPreferencesType.gameSoundLevelV20	4	kDrvrVersion
11	SystemPreferencesType.alarmSoundLevelV20	64	kMaxPortDescStrLen
12	SystemPreferencesType.hideSecretRecords	1000	kPortDescStrID
13	SystemPreferencesType.deviceLocked	1	portPhysicalPort
		2	portBkgndModeSupported
		4	portRS232Capable
		8	portIRDACapable
		16	portCradlePort
		32	portExternalPort
		64	portModemPort
		(hex) 100	portConsolePort
		128	portCncMgrVisible
		(hex) 1000	portPrivateUse
		(hex) 200	portUSBCapable
		0	drvIRQNone
14	SystemPreferencesType.localSyncRequiresPassword	1	drvIRQ1
15	SystemPreferencesType.remoteSyncRequiresPassword	2	drvIRQ2
16	SystemPreferencesType.sysPrefFlags	4	drvIRQ3
18	SystemPreferencesType.sysBatteryKind		
19	SystemPreferencesType.reserved1		
20	SystemPreferencesType.minutesWestOfGMT		
24	SystemPreferencesType.daylightSavings		
25	SystemPreferencesType.reserved2		
26	SystemPreferencesType.ronamaticChar		
28	SystemPreferencesType.hard1CharAppCreator		
32	SystemPreferencesType.hard2CharAppCreator		
36	SystemPreferencesType.hard3CharAppCreator		
40	SystemPreferencesType.hard4CharAppCreator		

8	drvrIRQ4	5	sndAlarm
16	drvrIRQ5	6	sndConfirmation
32	drvrIRQ6	7	sndClick
64	drvrIRQOther		
0	DrvrInfoType.drvrID	0	SndMidiRecHdrType.signature
4	DrvrInfoType.drvrVersion	4	SndMidiRecHdrType.bDataOffset
8	DrvrInfoType.maxBaudRate	5	SndMidiRecHdrType.reserved
12	DrvrInfoType.handshakeThreshold	0	SndMidiRecType.hdr
16	DrvrInfoType.portFlags	6	SndMidiRecType.name
20	DrvrInfoType.portDesc		
24	DrvrInfoType.irqType	0	SndMidiListItemType.name
25	DrvrInfoType.multipleEnumerations	32	SndMidiListItemType.uniqueRecID
26	DrvrInfoType.dbCreator	36	SndMidiListItemType.dbID
		40	SndMidiListItemType.cardNo
0	drvrEntryGetUartFeatures		
1	drvrEntryGetDrvrFuncs	1	sndSmfCmdPlay
2	drvrEntryGetUartFtrsNEntries	2	sndSmfCmdDuration
1	drvrStatusCtsOn		
2	drvrStatusRtsOn	0	SndCallbackInfoType.funcP
4	drvrStatusDsrOn	4	SndCallbackInfoType.dwUserData
8	drvrStatusTxFifoFull		
16	drvrStatusTxFifoEmpty	0	SndSmfCallbacksType.completion
32	drvrStatusBreakAsserted	8	SndSmfCallbacksType.blocking
64	drvrStatusDataReady	16	SndSmfCallbacksType.reserved
0	DrvrRcvQType.rcvQ	-1	sndSmfPlayAllMilliSec
4	DrvrRcvQType.qWriteByte		
8	DrvrRcvQType.qWriteBlock	0	SndSmfOptionsType.dwStartMilliSec
12	DrvrRcvQType.qGetSize	4	SndSmfOptionsType.dwEndMilliSec
16	DrvrRcvQType.qGetSpace	8	SndSmfOptionsType.amplitude
20	DrvrRcvQType.qSignalCheck	10	SndSmfOptionsType.interruptible
		11	SndSmfOptionsType.reserved1
0	SrmRcvQType.qStart	12	SndSmfOptionsType.reserved
4	SrmRcvQType.qEnd		
8	SrmRcvQType.qSize	0	SndSmfChanRangeType.bFirstChan
12	SrmRcvQType.qData	1	SndSmfChanRangeType.bLastChan
16	SrmRcvQType.qPort		
0	slkSocketDebugger	0	sndFtrIDVersion
1	slkSocketConsole	100	sndMgrVersionNum
2	slkSocketRemoteUI	0	sndInput
3	slkSocketDLP	1	sndOutput
4	slkSocketFirstDynamic	0	sndMono
0	slkPktTypeSystem	1	sndStereo
1	slkPktTypeUnused1	-1	sndSystemVolume
2	slkPktTypePAD	-2	sndGameVolume
3	slkPktTypeLoopBackTest	-3	sndAlarmVolume
		1	sndInt8
0	SlkPktHeaderType.signature1	17	sndUInt8
		2	sndInt16Big
2	SlkPktHeaderType.signature2	18	sndInt16Little
3	SlkPktHeaderType.dest	4	sndInt32Big
4	SlkPktHeaderType.src	20	sndInt32Little
5	SlkPktHeaderType.type	36	sndFloatBig
6	SlkPktHeaderType.bodySize	52	sndFloatLittle
8	SlkPktHeaderType.transId	2	sndInt16
9	SlkPktHeaderType.checksum	18	sndInt16Opposite
		4	sndInt32
(hex) BEEF	slkPktHeaderSignature1	20	sndInt32Opposite
237	slkPktHeaderSignature2	36	sndFloat
190	slkPktHeaderSigFirst	52	sndFloatOpposite
239	slkPktHeaderSigSecond	0	sndFlagSync
237	slkPktHeaderSigThird	1	sndFlagAsync
		0	sndFlagNormal
0	SlkPktFooterType.crc16	0	sndPanCenter
		-1024	sndPanFullLeft
0	SlkWriteDataType.size	(hex) 400	sndPanFullRight
2	SlkWriteDataType.dataP	12	maxStrIToALen
		0	SetAtLeast
0	SlkSocketListenType.listenerP	1	SetExactly
4	SlkSocketListenType.headerBufferP	2	SetAtMost
8	SlkSocketListenType.bodyBufferP	3	SetDefault
12	SlkSocketListenType.bodyBufferSize	4	ResetTimer
64	sndMaxAmp	0	PenBtnInfoType.boundsR
64	sndDefaultAmp	8	PenBtnInfoType.asciiCode
32	sndMidiNameLength	10	PenBtnInfoType.keyCode
1	sndCmdFreqDurationAmp	12	PenBtnInfoType.modifiers
2	sndCmdNoteOn		
3	sndCmdFrgOn	0	PenBtnListType.numButtons
4	sndCmdQuiet	2	PenBtnListType.buttons
0	SndCommandType.cmd	0	alphaGraffitiSilkScreenArea
1	SndCommandType.reserved	1	numericGraffitiSilkScreenArea
2	SndCommandType.param1		
6	SndCommandType.param2	0	SilkScreenAreaType.bounds
8	SndCommandType.param3	8	SilkScreenAreaType.areaType
		12	SilkScreenAreaType.index
1	sndInfo	(hex) 100	sysPktMaxMemChunk
2	sndWarning	(hex) 110	sysPktMaxBodySize
4	sndStartUp	1000	sysPktInitialTimeout

0 SysPktBodyType.command	1 SysPktCommCmdType._filler
1 SysPktBodyType._filler	2 SysPktCommCmdType.set
2 SysPktBodyType.data	3 SysPktCommCmdType.padding
	4 SysPktCommCmdType.baudRate
	8 SysPktCommCmdType.flags
3 sysPktMaxBodyChunks	
0 sysPktStateCmd	0 SysPktCommRspType.command
128 sysPktStateRsp	1 SysPktCommRspType._filler
1 sysPktReadMemCmd	2 SysPktCommRspType.baudRate
129 sysPktReadMemRsp	6 SysPktCommRspType.flags
0 SysPktReadMemCmdType.command	16 sysPktGetTrapBreaksCmd
1 SysPktReadMemCmdType._filler	144 sysPktGetTrapBreaksRsp
2 SysPktReadMemCmdType.address	17 sysPktSetTrapBreaksCmd
6 SysPktReadMemCmdType.numBytes	145 sysPktSetTrapBreaksRsp
	18 sysPktGremlinsCmd
0 SysPktReadMemRspType.command	0 SysPktGremlinsCmdType.command
1 SysPktReadMemRspType._filler	1 SysPktGremlinsCmdType._filler
	2 SysPktGremlinsCmdType.action
2 sysPktWriteMemCmd	4 SysPktGremlinsCmdType.data
130 sysPktWriteMemRsp	
0 SysPktWriteMemCmdType.command	1 sysPktGremlinsIdle
1 SysPktWriteMemCmdType._filler	2 sysPktGremlinsEvent
2 SysPktWriteMemCmdType.address	19 sysPktFindCmd
6 SysPktWriteMemCmdType.numBytes	147 sysPktFindRsp
0 SysPktWriteMemRspType.command	0 SysPktFindCmdType.command
1 SysPktWriteMemRspType._filler	1 SysPktFindCmdType._filler
	2 SysPktFindCmdType.firstAddr
3 sysPktSingleStepCmd	6 SysPktFindCmdType.lastAddr
4 sysPktGetRtnNameCmd	10 SysPktFindCmdType.numBytes
132 sysPktGetRtnNameRsp	12 SysPktFindCmdType.caseInsensitive
5 sysPktReadRegsCmd	13 SysPktFindCmdType.padding
133 sysPktReadRegsRsp	
6 sysPktWriteRegsCmd	0 SysPktFindRspType.command
134 sysPktWriteRegsRsp	1 SysPktFindRspType._filler
7 sysPktContinueCmd	2 SysPktFindRspType.addr
10 sysPktRPCCmd	6 SysPktFindRspType.found
138 sysPktRPCRsp	
	7 SysPktFindRspType.padding
0 SysPktRPCParamInfo.byRef	20 sysPktGetTrapConditionsCmd
1 SysPktRPCParamInfo.size	148 sysPktGetTrapConditionsRsp
2 SysPktRPCParamInfo.data	21 sysPktSetTrapConditionsCmd
	149 sysPktSetTrapConditionsRsp
0 SysPktRPCType.command	22 sysPktChecksumCmd
1 SysPktRPCType._filler	150 sysPktChecksumRsp
2 SysPktRPCType.trapWord	
4 SysPktRPCType.resultD0	0 SysPktChecksumType.command
8 SysPktRPCType.resultA0	1 SysPktChecksumType._filler
12 SysPktRPCType.numParams	2 SysPktChecksumType.firstAddr
14 SysPktRPCType.param	6 SysPktChecksumType.numBytes
	8 SysPktChecksumType.seed
11 sysPktGetBreakpointsCmd	10 SysPktChecksumType.checksum
139 sysPktGetBreakpointsRsp	
12 sysPktSetBreakpointsCmd	23 sysPktExecFlashCmd
140 sysPktSetBreakpointsRsp	151 sysPktExecFlashRsp
12 sysPktRemoteUIUpdCmd	127 sysPktRemoteMsgCmd
0 SysPktRemoteUIUpdCmdType.command	0 SysPktRemoteMsgCmdType.command
1 SysPktRemoteUIUpdCmdType._filler	1 SysPktRemoteMsgCmdType._filler
2 SysPktRemoteUIUpdCmdType.rowBytes	
4 SysPktRemoteUIUpdCmdType.fromY	(hex) 400 GremlinIsOn
6 SysPktRemoteUIUpdCmdType.fromX	32767 sysRandomMax
8 SysPktRemoteUIUpdCmdType.toY	0 translitOpStandardBase
10 SysPktRemoteUIUpdCmdType.toX	0 translitOpUpperCase
12 SysPktRemoteUIUpdCmdType.height	1 translitOpLowerCase
14 SysPktRemoteUIUpdCmdType.width	2 translitOpReserved2
16 SysPktRemoteUIUpdCmdType.pixels	3 translitOpReserved3
	1000 translitOpCustomBase
13 sysPktRemoteEvtCmd	(hex) 8000 translitOpPreprocess
	32 kTxtConvertStateSize
0 SysPktRemoteEvtCmdType.command	
1 SysPktRemoteEvtCmdType._filler	0 TxtConvertStateType.ioSrcState
2 SysPktRemoteEvtCmdType.penDown	32 TxtConvertStateType.ioDstState
3 SysPktRemoteEvtCmdType.padding1	
4 SysPktRemoteEvtCmdType.penX	128 byteAttrFirst
6 SysPktRemoteEvtCmdType.penY	64 byteAttrLast
8 SysPktRemoteEvtCmdType.keyPress	32 byteAttrMiddle
9 SysPktRemoteEvtCmdType.padding2	1 byteAttrSingle
10 SysPktRemoteEvtCmdType.keyModifiers	3 maxCharBytes
12 SysPktRemoteEvtCmdType.keyAscii	0 tsmFtrNumFlags
14 SysPktRemoteEvtCmdType.keyCode	1 tsmFtrFlagsHasFep
	0 tsmGetFepMode
13 sysPktDbgBreakToggleCmd	1 tsmSetFepMode
141 sysPktDbgBreakToggleRsp	2 tsmHandleEvent
14 sysPktFlashCmd	3 tsmInit
142 sysPktFlashRsp	4 tsmDrawMode
15 sysPktCommCmd	5 tsmGetSystemFep
143 sysPktCommRsp	6 tsmSetSystemFep
	7 tsmGetCurrentFep
0 SysPktCommCmdType.command	

8	tsmSetCurrentFep	1	FieldAttrTag.numeric.shift
9	tsmGetSystemFepCreator	0	FieldAttrTag.numeric
10	tsmSetSystemFepCreator		
11	tsmGetCurrentFepCreator	1	FieldAttrTag.reserved.mask
12	tsmSetCurrentFepCreator	1	FieldAttrTag.reserved.size
13	tsmFepHandleEvent	0	FieldAttrTag.reserved.shift
14	tsmFepMapEvent	0	FieldAttrTag.reserved
15	tsmFepTerminate		
16	tsmFepReset	0	buttonCtl
17	tsmFepCommitAction	1	pushButtonCtl
18	tsmFepOptionsList	2	checkboxCtl
18	tsmMaxSelector	3	popupTriggerCtl
0	tsmFepModeDefault	4	selectorTriggerCtl
1	tsmFepModeOff	5	repeatingButtonCtl
128	tsmFepModeCustom	6	sliderCtl
32767	maxFieldTextLen	7	feedbackSliderCtl
11	maxFieldLines	0	noButtonFrame
0	leftAlign	1	standardButtonFrame
1	centerAlign	2	boldButtonFrame
2	rightAlign	3	rectangleButtonFrame
100	undoBufferSize	-1	noListSelection
0	undoNone	0	sclUpArrow
1	undoTyping	1	sclDownArrow
2	undoBackspace	2	sclUpPage
3	undoDelete	3	sclDownPage
4	undoPaste	4	sclCar
5	undoCut	1	tableDefaultColumnSpacing
6	undoInput	7	tableNoteIndicatorWidth
		11	tableNoteIndicatorHeight
1	FieldAttrTag.usable.mask	255	tableMaxTextItemSize
1	FieldAttrTag.usable.size	(hex) FFFF	tblUnusableRow
15	FieldAttrTag.usable.shift	0	checkboxTableItem
0	FieldAttrTag.usable	1	customTableItem
		2	dateTableItem
1	FieldAttrTag.visible.mask	3	labelTableItem
1	FieldAttrTag.visible.size	4	numericTableItem
14	FieldAttrTag.visible.shift	5	popupTriggerTableItem
0	FieldAttrTag.visible	6	textTableItem
		7	textWithNoteTableItem
1	FieldAttrTag.editable.mask	8	timeTableItem
1	FieldAttrTag.editable.size	9	narrowTextTableItem
13	FieldAttrTag.editable.shift	10	tallCustomTableItem
0	FieldAttrTag.editable	(hex) FFFF	noFocus
		(hex) FFFF	frmInvalidObjectId
1	FieldAttrTag.singleLine.mask	255	frmNoSelectedControl
1	FieldAttrTag.singleLine.size	(hex) 8000	frmRedrawUpdateCode
12	FieldAttrTag.singleLine.shift	1974	frmResponseCreate
0	FieldAttrTag.singleLine	(hex) BEEF	frmResponseQuit
		0	informationAlert
1	FieldAttrTag.hasFocus.mask	1	confirmationAlert
1	FieldAttrTag.hasFocus.size	2	warningAlert
11	FieldAttrTag.hasFocus.shift	0	frmFieldObj
0	FieldAttrTag.hasFocus	1	frmControlObj
		2	frmListObj
1	FieldAttrTag.dynamicSize.mask	3	frmTableObj
1	FieldAttrTag.dynamicSize.size	4	frmBitmapObj
10	FieldAttrTag.dynamicSize.shift	5	frmLineObj
0	FieldAttrTag.dynamicSize	6	frmFrameObj
		7	frmRectangleObj
1	FieldAttrTag.insPtVisible.mask	8	frmLabelObj
1	FieldAttrTag.insPtVisible.size	9	frmTitleObj
9	FieldAttrTag.insPtVisible.shift	10	frmPopupObj
0	FieldAttrTag.insPtVisible	11	frmGraffitiStateObj
		12	frmGadgetObj
1	FieldAttrTag.dirty.mask	13	frmScrollBarObj
1	FieldAttrTag.dirty.size	0	formGadgetDrawCmd
		1	formGadgetEraseCmd
8	FieldAttrTag.dirty.shift	2	formGadgetHandleEventCmd
0	FieldAttrTag.dirty	3	formGadgetDeleteCmd
3	FieldAttrTag.underlined.mask	1	FormGadgetAttrTag.usable.mask
2	FieldAttrTag.underlined.size	1	FormGadgetAttrTag.usable.size
6	FieldAttrTag.underlined.shift	15	FormGadgetAttrTag.usable.shift
0	FieldAttrTag.underlined	0	FormGadgetAttrTag.usable
3	FieldAttrTag.justification.mask	1	FormGadgetAttrTag.extended.mask
2	FieldAttrTag.justification.size	1	FormGadgetAttrTag.extended.size
4	FieldAttrTag.justification.shift	14	FormGadgetAttrTag.extended.shift
0	FieldAttrTag.justification	0	FormGadgetAttrTag.extended
1	FieldAttrTag.autoShift.mask	1	FormGadgetAttrTag.visible.mask
1	FieldAttrTag.autoShift.size	1	FormGadgetAttrTag.visible.size
3	FieldAttrTag.autoShift.shift	13	FormGadgetAttrTag.visible.shift
0	FieldAttrTag.autoShift	0	FormGadgetAttrTag.visible
1	FieldAttrTag.hasScrollBar.mask	8191	FormGadgetAttrTag.reserved.mask
1	FieldAttrTag.hasScrollBar.size	13	FormGadgetAttrTag.reserved.size
2	FieldAttrTag.hasScrollBar.shift	0	FormGadgetAttrTag.reserved.shift
0	FieldAttrTag.hasScrollBar	0	FormGadgetAttrTag.reserved
1	FieldAttrTag.numeric.mask	0	FormGadgetTypeInCallback.id
1	FieldAttrTag.numeric.size	2	FormGadgetTypeInCallback.attr

4	FormGadgetTypeInCallback.rect	1	kbdCapsKey
12	FormGadgetTypeInCallback.data	255	kbdNoKey
16	FormGadgetTypeInCallback.handler	0	kbdAlpha
		1	kbdNumbersAndPunc
0	FormActiveStateType.data	2	kbdAccent
(hex) 2710	categoryHideEditCategory	255	kbdDefault
10001	categoryDefaultEditCategoryString	1	KeyboardShiftFlag
		2	KeyboardCapslockFlag
0	AppInfoTag.renamedCategories	0	menuCmdBarResultNone
2	AppInfoTag.categoryLabels	1	menuCmdBarResultChar
258	AppInfoTag.categoryUniqIDs	2	menuCmdBarResultMenuItem
274	AppInfoTag.lastUniqID	3	menuCmdBarResultNotify
275	AppInfoTag.padding	20	menuCmdBarMaxTextLength
		0	menuCmdBarOnRight
		255	menuCmdBarOnLeft
		-1	noMenuSelection
3	numClipboardForamts	-1	noMenuItemSelection
3	numClipboardFormats	-2	separatorItemSelection
1000	cbdMaxTextLength	0	menuButtonCause
0	clipboardText	1	menuCommandCause
1	clipboardInk	45	MenuSeparatorChar
2	clipboardBitmap	0	showPrivateRecords
0	selectDayByDay	1	maskPrivateRecords
1	selectDayByWeek	2	hidePrivateRecords
2	selectDayByMonth	128	progressMaxMessage
		31	progressMaxTitle
0	DaySelectorType.bounds	7	progressMaxButtonText
8	DaySelectorType.visible		
9	DaySelectorType.reserved1	0	PrgCallbackData.stage
10	DaySelectorType.visibleMonth	2	PrgCallbackData.textP
12	DaySelectorType.visibleYear	6	PrgCallbackData.textLen
14	DaySelectorType.selected	8	PrgCallbackData.message
28	DaySelectorType.selectDayBy	12	PrgCallbackData.error
29	DaySelectorType.reserved2	14	PrgCallbackData.bitmapId
		1	PrgCallbackData.canceled.mask
0	fatalReset	1	PrgCallbackData.canceled.size
1	fatalEnterDebugger	15	PrgCallbackData.canceled.shift
(hex) FFFF	fatalDoNothing	16	PrgCallbackData.canceled
9	maxFinds	1	PrgCallbackData.showDetails.mask
16	maxFindStrLen	1	PrgCallbackData.showDetails.size
		14	PrgCallbackData.showDetails.shift
0	FindMatchType.appCardNo	16	PrgCallbackData.showDetails
2	FindMatchType.appDbID	1	PrgCallbackData.textChanged.mask
6	FindMatchType.foundInCaller	1	PrgCallbackData.textChanged.size
7	FindMatchType.reserved	13	PrgCallbackData.textChanged.shift
8	FindMatchType.dbCardNo	16	PrgCallbackData.textChanged
10	FindMatchType.dbID	1	PrgCallbackData.timedOut.mask
14	FindMatchType.recordNum	1	PrgCallbackData.timedOut.size
16	FindMatchType.matchPos	12	PrgCallbackData.timedOut.shift
18	FindMatchType.matchFieldNum	16	PrgCallbackData.timedOut
20	FindMatchType.matchCustom	18	PrgCallbackData.timeout
		22	PrgCallbackData.barMaxValue
0	FindParamsType.dbAccessMode	26	PrgCallbackData.barCurValue
2	FindParamsType.recordNum	30	PrgCallbackData.barMessage
4	FindParamsType.more	34	PrgCallbackData.barFlags
5	FindParamsType.strAsTyped	1	PrgCallbackData.delay.mask
22	FindParamsType.strToFind	1	PrgCallbackData.delay.size
39	FindParamsType.reserved1	15	PrgCallbackData.delay.shift
40	FindParamsType.noAccessAllowed1	36	PrgCallbackData.delay
42	FindParamsType.lineNumber	38	PrgCallbackData.userDataP
44	FindParamsType.continuation		
45	FindParamsType.noAccessAllowed2	0	ProgressType.opaque1
46	FindParamsType.noAccessAllowed3	4	ProgressType.opaque2
50	FindParamsType.noAccessAllowed4	1	ProgressType.opaque3.mask
52	FindParamsType.noAccessAllowed5	1	ProgressType.opaque3.size
56	FindParamsType.noAccessAllowed6		
58	FindParamsType.noAccessAllowed7	15	ProgressType.opaque3.shift
59	FindParamsType.noAccessAllowed8	8	ProgressType.opaque3
60	FindParamsType.noAccessAllowed9		
92	FindParamsType.noAccessAllowed10		
		1	ProgressType.cancel.mask
0	GoToParamsType.searchStrLen	1	ProgressType.cancel.size
2	GoToParamsType.dbCardNo	14	ProgressType.cancel.shift
4	GoToParamsType.dbID	8	ProgressType.cancel
8	GoToParamsType.recordNum		
10	GoToParamsType.matchPos	7	ProgressType.opaque4.mask
12	GoToParamsType.matchFieldNum	3	ProgressType.opaque4.size
14	GoToParamsType.matchCustom	11	ProgressType.opaque4.shift
		8	ProgressType.opaque4
255	referenceDefault		
1	glfCapsLock	10	ProgressType.error
2	glfNumLock	12	ProgressType.stage
0	gsiShiftNone	14	ProgressType.opaque5
1	gsiNumLock	143	ProgressType.opaque6
2	gsiCapsLock	144	ProgressType.opaque7
3	gsiShiftPunctuation	146	ProgressType.opaque8
4	gsiShiftExtended	154	ProgressType.opaque9
5	gsiShiftUpper	158	ProgressType.opaque10
6	gsiShiftLower	162	ProgressType.opaque11
10	kbdReturnKey	166	ProgressType.opaque12
9	kbdTabKey	170	ProgressType.opaque13
8	kbdBackspaceKey	174	ProgressType.opaque14
2	kbdShiftKey	178	ProgressType.opaque15

179	ProgressType.opaque16	13268	secHideRecordsAlert
180	ProgressType.opaque17	13269	secMaskRecordsAlert
184	ProgressType.opaque18	0	secHideMaskRecordsOK
188	ProgressType.opaque19	1	secHideMaskRecordsCancel
220	ProgressType.opaque20	13300	secEnterPasswordAlert
(hex) 770	daySelectorMinYear	0	secEnterPasswordOK
2031	daySelectorMaxYear	1	secEnterPasswordCancel
0	HMSTime.hours	10030	BarCutBitmap
1	HMSTime.minutes	10031	BarCopyBitmap
2	HMSTime.seconds	(hex) 2730	BarPasteBitmap
3	HMSTime.reserved	10033	BarUndoBitmap
0	UIObjectFrame	10034	BarBeamBitmap
1	UIObjectFill	10035	BarSecureBitmap
2	UIObjectForeground	10036	BarDeleteBitmap
3	UIObjectSelectedFill	10037	BarInfoBitmap
4	UIObjectSelectedForeground	10050	SecLockBitmap
5	UIMenuFrame	6	SecLockWidth
6	UIMenuFill	8	SecLockHeight
7	UIMenuForeground	(hex) 2710	sysEditMenuID
8	UIMenuSelectedFill	(hex) 2710	sysEditMenuUndoCmd
9	UIMenuSelectedForeground	10001	sysEditMenuCutCmd
10	UIFieldBackground	10002	sysEditMenuCopyCmd
11	UIFieldText	10003	sysEditMenuPasteCmd
12	UIFieldTextLines	10004	sysEditMenuSelectAllCmd
13	UIFieldCaret	10005	sysEditMenuSeparator
14	UIFieldTextHighlightBackground	10006	sysEditMenuKeyboardCmd
15	UIFieldTextHighlightForeground	10007	sysEditMenuGraffitiCmd
16	UIFieldFepRawText	10020	sysNetworkProgress01Bitmap
17	UIFieldFepRawBackground	10021	sysNetworkProgress02Bitmap
18	UIFieldFepConvertedText	10022	sysNetworkProgress03Bitmap
19	UIFieldFepConvertedBackground	10023	sysNetworkProgress04Bitmap
20	UIFieldFepUnderline	10024	sysNetworkProgress05Bitmap
21	UIFormFrame	10025	sysNetworkProgress06Bitmap
22	UIFormFill	10100	sysEditMenuJapAddWord
23	UIDialogFrame	10101	sysEditMenuJapLookupWord
24	UIDialogFill	10200	noteMenuID
25	UIAlertFrame	(hex) 2710	noteUndoCmd
26	UIAlertFill	10001	noteCutCmd
27	UIOK	10002	noteCopyCmd
28	UICaution	10003	notePasteCmd
29	UIWarning	10004	noteSelectAllCmd
30	UILastColorTableEntry	10005	noteSeparator
0	UIPickColorStartPalette	10006	noteKeyboardCmd
1	UIPickColorStartRGB	10006	noteGraffitiCmd
(hex) 2710	defaultAppIconBitmap	10200	noteFontCmd
10001	defaultAppSmallIconBitmap	10201	noteTopOfPageCmd
(hex) 2710	systemVersionID	10202	noteBottomOfPageCmd
1	appVersionID	10203	notePhoneLookupCmd
1000	appVersionAlternateID	10300	newNoteMenuID
1000	ainID	10300	newNoteFontCmd
10001	oemVersionID	10301	newNotePhoneLookupCmd
10001	maxCategoryWidthID	10900	NoteView
(hex) 2710	SelectACategoryAlert	10950	NewNoteView
10002	LowBatteryAlert	10901	NoteField
10003	VeryLowBatteryAlert	10902	NoteDoneButton
10004	UndoAlert	10903	NoteSmallFontButton
1	UndoCancelButton	10904	NoteLargeFontButton
10005	MergeCategoryAlert	10905	NoteDeleteButton
0	MergeCategoryYes	10906	NoteUpButton
1	MergeCategoryNo	10907	NoteDownButton
10006	privateRecordInfoAlert	10908	NoteScrollBar
10007	ClipboardLimitAlert	1	NoteFontGroup
10012	CategoryExistsAlert	(hex) 1000	noteViewMaxLength
10013	DeviceFullAlert	11000	aboutDialog
10014	categoryAllUsedAlert	11001	aboutNameLabel
10015	RemoveCategoryAlert	11002	aboutVersionLabel
0	RemoveCategoryYes	11100	categoryNewNameDialog
1	RemoveCategoryNo	11103	categoryNewNameField
(hex) 2720	DemoUnitAlert	(hex) 2B60	categoryNewNameOKButton
10017	NoDataToBeamAlert	(hex) 2710	CategoriesEditForm
10017	NoDataToSendAlert	10002	CategoriesEditList
10018	LowCradleChargedBatteryAlert	10003	CategoriesEditOKButton
10019	VeryLowCradleChargedBatteryAlert	10004	CategoriesEditNewButton
10020	CategoryTooLongAlert	10005	CategoriesEditRenameButton
10024	InfoOKAlert	10006	CategoriesEditDeleteButton
10025	InfoOKCancelAlert	(hex) 2BC0	graffitiReferenceDialog
10026	InfoCancelAlert	11202	graffitiReferenceDoneButton
10027	PrivacyWarningAlert	11203	graffitiReferenceUpButton
10028	ConfirmationOKAlert	11204	graffitiReferenceDownButton
10029	ConfirmationOKCancelAlert	11205	graffitiReferenceFirstBitmap
10030	ConfirmationCancelAlert	10004	categoryAllStrID
10031	WarningOKAlert	10005	categoryEditStrID
(hex) 2730	WarningOKCancelAlert	10006	menuCommandStrID
10033	WarningCancelAlert	10007	launcherBatteryStrID
10100	sysFatalAlert	10008	systemNameStrID
13250	secInvalidPasswordAlert	10009	phoneLookupTitleStrID
13251	secGotoInvalidRecordAlert	10010	phoneLookupAddStrID
13261	secShowPrivatePermanentPassEntryAlert	10011	phoneLookupFormatStrID
13265	secShowMaskedPrivatePermanentPassEntryAlert	(hex) 4E40	m68kTrapInstr
		15	m68kTrapVectorMask
		0	M68KExcTableType.initStack

4	M68KExcTableType.initPC	(id)	mdem	sysFileCMailDemo
8	M68KExcTableType.busErr	(id)	pref	sysFileCFirstApp
12	M68KExcTableType.addressErr	(id)	setp	sysFileCAltFirstApp
16	M68KExcTableType.illegalInstr	(id)	pref	sysFileCDefaultApp
20	M68KExcTableType.divideByZero	(id)	date	sysFileCDefaultButton1App
24	M68KExcTableType.chk	(id)	addr	sysFileCDefaultButton2App
28	M68KExcTableType.trap	(id)	todo	sysFileCDefaultButton3App
32	M68KExcTableType.privilege	(id)	memo	sysFileCDefaultButton4App
36	M68KExcTableType.trace	(id)	calc	sysFileCDefaultCalcButtonApp
40	M68KExcTableType.aTrap	(id)	sync	sysFileCDefaultCradleApp
44	M68KExcTableType.fTrap	(id)	sync	sysFileCDefaultModemApp
48	M68KExcTableType.reserved12	(id)	lnch	sysFileCDefaultAntennaButtonApp
		(id)	0000	sysFileCNullApp
52	M68KExcTableType.coproc	(id)	????	sysFileCSimulator
56	M68KExcTableType.formatErr	(id)	digi	sysFileCDigitizer
60	M68KExcTableType.uninitializedInt	(id)	dtm	sysFileCDateTime
64	M68KExcTableType.reserved	(id)	gnrl	sysFileCGeneral
96	M68KExcTableType.spuriousInt	(id)	frmt	sysFileCFormats
100	M68KExcTableType.autoVec1	(id)	shct	sysFileCShortCuts
104	M68KExcTableType.autoVec2	(id)	btn	sysFileCButtons
108	M68KExcTableType.autoVec3	(id)	ownr	sysFileCOwner
112	M68KExcTableType.autoVec4	(id)	modm	sysFileCModemPanel
116	M68KExcTableType.autoVec5	(id)	dial	sysFileCDialPanel
120	M68KExcTableType.autoVec6	(id)	netw	sysFileCNetworkPanel
124	M68KExcTableType.autoVec7	(id)	wclp	sysFileCWirelessPanel
128	M68KExcTableType.trapN	(id)	udic	sysFileCUserDict
192	M68KExcTableType.unassigned	(id)	hpad	sysFileCPADHtal
		(id)	htcp	sysFileCTCPHtal
0	M68KRegsType.d	(id)	hrel	sysFileCRELHtal
32	M68KRegsType.a	(id)	mine	sysFileCMineHunt
60	M68KRegsType.usp	(id)	puzl	sysFileCPuzzle15
64	M68KRegsType.ssp	(id)	olbi	sysFileCOpenLibInfo
68	M68KRegsType.pc	(id)	flsh	sysFileCHwrFlashMgr
72	M68KRegsType.sr	(id)	phop	sysFileCPhonePanel
(hex) 8000	m68kSrTraceMask	(id)	mmfx	sysFileDRAMFixOriginal
15	m68kSrTraceBit	(id)	dmfx	sysFileDRAMFix
(hex) 2000	m68kSrSupervisorMask	(id)	libr	sysFileTLibrary
(hex) 700	m68kSrInterruptMask	(id)	libx	sysFileTLibraryExtension
8	m68kSrInterruptOffset	(id)	net1	sysFileCNet
16	m68kSrExtendMask	(id)	netp	sysFileCRmpLib
8	m68kSrNegativeMask	(id)	inet	sysFileCINetLib
4	m68kSrZeroMask	(id)	secl	sysFileCSecLib
2	m68kSrOverflowMask	(id)	webl	sysFileCWebLib
1	m68kSrCarryMask	(id)	irda	sysFileCIRLib
0	CPU_68K	(id)	blth	sysFileCBTLib
1	CPU_x86	(id)	bttx	sysFileCBtTransLib
0	false	(id)	locl	sysFileCLocalLib
1	true	(id)	lz77	sysFileCLz77Lib
0	sysDbgBreakpointTrapNum	(id)	smsl	sysFileCSmsLib
8	sysDbgTrapNum	(id)	btex	sysFileCBtExgLib
15	sysDispatchTrapNum	(id)	pdil	sysFileCpdiLib
(id) psys	sysFileCSystem	(id)	tmgr	sysFileCTelMgrLib
(id) poem	sysFileCOEMSystem	(id)	spht	sysFileCTelTaskSerial
(id) pdvc	sysFileCPalmDevice	(id)	ttsk	sysFileTTelTaskSerial
(id) graf	sysFileCGraffiti	(id)	patd	sysFileCBaseATDriver
(id) ptch	sysFileCSystemPatch	(id)	patd	sysFileTBaseATDriver
(id) calc	sysFileCCalculator	(id)	stgd	sysFileCStandardGsm
(id) secr	sysFileCSecurity	(id)	pdrv	sysFileTPhoneDriver
(id) pref	sysFileCPreferences	(id)	smgr	sysFileCSerialMgr
(id) addr	sysFileCAddress	(id)	swrp	sysFileCSerialWrapper
(id) todo	sysFileCToDo	(id)	iwrp	sysFileCIRSerialWrapper
(id) date	sysFileCDatebook	(id)	tsml	sysFileCTextServices
(id) memo	sysFileCMemo	(id)	sdrv	sysFileTUartPlugIn
(id) sync	sysFileCSync	(id)	vdrv	sysFileTVirtPlugIn
(id) memr	sysFileCMemory	(id)	u328	sysFileCUart328
(id) mail	sysFileCMail	(id)	u8EZ	sysFileCUart328EZ
(id) exps	sysFileCExpense	(id)	u650	sysFileCUart650
(id) lnch	sysFileCLAuncher	(id)	ircm	sysFileCVirtIrComm
(id) clpr	sysFileCCLipper	(id)	rpcm	sysFileCVirtRfComm
(id) dial	sysFileCDial	(id)	btcp	sysFileCBtConnectPanelHelper
(id) setp	sysFileCSetup	(id)	pusb	sysFileCPDIUSBd12
(id) actv	sysFileCActivate	(id)	usbd	sysPortUSBDesktop
(id) gafd	sysFileCGenericActivate	(id)	usbc	sysPortUSBConsole
(id) fins	sysFileCFlashInstaller	(id)	usbp	sysPortUSBPeripheral
(id) rfdg	sysFileCRFdiag	(id)	econ	sysFileCExternalConnector
(id) msgs	sysFileCMessaging	(id)	expn	sysFileCExpansionMgr
(id) gsmf	sysFileCModemFlashTool	(id)	vfsm	sysFileCVFSMgr
(id) dict	sysFileCJEDict	(id)	fatf	sysFileCFATFS
(id) srvr	sysFileHotSyncServer	(id)	sdsd	sysFileCSdSpiCard
(id) hssu	sysFileHotSyncServerUpdate	(id)	pnps	sysFileCSlotDriverPnps
(id) cinf	sysFileCCardInfo	(id)	sndm	sysFileCSoundMgr
(id) fone	sysFileCPhone	(id)	mdia	sysFileCMultimedia
(id) smsm	sysFileCSmsMessenger	(id)	rsrc	sysFileTSystem
(id) nett	sysFileCNetTrace	(id)	ptch	sysFileTSystemPatch
(id) ping	sysFileCPing	(id)	pupd	sysFileTProductUpdate
(id) lpkr	sysFileCLanguagePicker	(id)	krnl	sysFileTKernel
(id) mfxl	sysFileCMfgExtension	(id)	boot	sysFileTBoot
(id) mfgf	sysFileCMfgFunctional	(id)	shal	sysFileTSmallHal
(id) mfgc	sysFileCMfgCalibration	(id)	bhal	sysFileTBigHal
(id) gdem	sysFileCGraffitiDemo	(id)	spls	sysFileTSplash
		(id)	uish	sysFileTUIAppShell
		(id)	ovly	sysFileTOverlay



(id) extn sysFileTExtension	(id) crdi sysNotifyCardInsertedEvent
(id) appl sysFileTApplication	(id) crdo sysNotifyCardRemovedEvent
(id) panl sysFileTPanel	(id) volm sysNotifyVolumeMountedEvent
(id) sprf sysFileTSavedPreferences	(id) volu sysNotifyVolumeUnmountedEvent
(id) pref sysFileTPreferences	(id) hlpr sysNotifyHelperEvent
(id) smfr sysFileTMidi	(id) pose sysNotifyPOSEMountEvent
(id) pqa sysFileTpqa	(id) locc sysNotifyLocaleChangedEvent
(id) locm sysFileTLocaleModule	(id) retk sysNotifyRetryEnqueueKey
(id) actp sysFileTActivationPlugin	(id) attn sysNotifyGotUsersAttention
(id) dict sysFileTUserDictionary	(id) dbs- sysNotifyDBDeletedEvent
(id) lean sysFileTLearningData	(id) dbcr sysNotifyDBCreatedEvent
(id) macr sysFileTGraffitiMacros	(id) dbmn sysNotifyDBChangedEvent
(id) htal sysFileTHtalLib	(id) dbdr sysNotifyDBDirtyEvent
(id) exgl sysFileTExgLib	(id) unlk sysNotifyDeviceUnlocked
(id) libs sysFileTSlotDriver	(id) fone sysNotifyPhoneEvent
(id) libf sysFileTFileSystem	(id) neti sysNotifyNetLibIFMediaEvent
(id) strm sysFileTFileStream	(id) -pdb sysNotifyDeleteProtectedEvent
(id) temp sysFileTTemp	(id) irda sysNotifyIrDASniffEvent
(id) nppi sysFileTNetworkPanelPlugin	(id) hpps sysNotifyProcessPenStrokeEvent
(id) scpt sysFileTScriptPlugin	(id) hvch sysNotifyVirtualCharHandlingEvent
(id) sdio sysFileTStdIO	(id) hede sysNotifyEventDequeuedEvent
(id) ???? sysFileTSimulator	(id) hidl sysNotifyIdleTimeEvent
(id) boot sysResTBootCode	(id) hapl sysNotifyAppLaunchingEvent
(id) pref sysResTAppPrefs	(id) hapq sysNotifyAppQuittingEvent
(id) xprf sysResTExtPrefs	(id) hipe sysNotifyInsPtEnableEvent
(id) code sysResTAppCode	(id) hkbd sysNotifyKeyboardDialogEvent
(id) pupd sysResTProductUpdateCode	(id) ovly omOverlayRscType
(id) data sysResTAppGData	(id) ovly omFtrCreator
(id) extn sysResTExtensionCode	(id) attn kAttnFtrCreator
(id) exte sysResTExtensionOEMCode	(id) code kDrvrCODEType
(id) feat sysResTFeatures	(id) PMrc sndMidiRecSignature
(id) libr sysResTLibrary	(id) scrn silkscreenRectScreen
(id) silk sysResTSilkscreen	(id) graf silkscreenRectGraffiti
(id) tmpl sysResTGrfTemplate	(id) tsml tsmFtrCreator
(id) dict sysResTGrfDictionary	(id) tSTR strRsc
(id) dflt sysResTDefaultDB	(id) tAIN ainRsc
(id) cpdb sysResTCompressedDB	(id) tAIB iconType
(id) tSTL sysResTErrStrings	(id) Tbmp bitmapRsc
(id) hsbd sysResTButtonDefaults	(id) Tbsb bsBitmapRsc
(id) wave sysResTSound	(id) Talt alertRscType
(id) psys sysResTSysPref	(id) tkbd kbdRscType
(id) flsh sysResTFlashMgr	(id) MBAR MenuRscType
(id) flid sysResTHwrFlashIdent	(id) NFNT fontRscType
(id) flcd sysResTHwrFlashCode	(id) nfnt fontExtRscType
(id) fntm sysResTFontMap	(id) tver verRsc
(id) poem sysFtrTOEMSys	(id) tAIS appInfoStringsRsc
(id) keyb sysFtrTKeyboard	(id) fnti fontIndexType
(id) psys sysFtrCreator	(id) MIDI midiRsc
(id) snum sysROMTokenSnum	(id) tcIt colorTableRsc
(id) hsiu sysNotifyHSISerialPortInUseEvent	(id) tint constantRscType
(id) hspr sysNotifyHSIPeripheralRespondedEvent	(id) tFRM formRscType
(id) hspn sysNotifyHSIPeripheralNotRespondingEvent	(id) tSTL strListRscType
(id) ncon sysNotifyHSIInoConnectionEvent	(id) wrdl wrdListRscType
(id) usbd sysNotifyHSIUSBCradleEvent	(id) taic defaultCategoryRscType
(id) rs2c sysNotifyHSIRS232CradleEvent	(id) tbin binaryGeneralRscType
(id) usbp sysNotifyHSIUSBPeripheralEvent	
(id) rs2p sysNotifyHSIRS232PeripheralEvent	511 errMaxMsgLength
(id) debug sysNotifyHSIDebugEvent	0 errNone
(id) ppp_ serFncPPPSession	(hex) 100 memErrorClass
(id) slip serFncSLIPSession	(hex) 200 dmErrorClass
(id) psys serFncDebugger	(hex) 300 serErrorClass
(id) sync serFncHotSync	(hex) 400 slkErrorClass
(id) psys serFncConsole	(hex) 500 sysErrorClass
(id) tmgr serFncTelephony	(hex) 600 fplErrorClass
(id) cmgr kCncFtrCncMgrCreator	(hex) 680 flpErrorClass
(id) pose kPalmOSEmulatorFeatureCreator	(hex) 700 evtErrorClass
(id) irda irFtrCreator	(hex) 800 sndErrorClass
(id) netl netCreator	(hex) 900 almErrorClass
(id) netl netFtrCreator	(hex) A00 timErrorClass
(id) libr netLibType	(hex) B00 penErrorClass
(id) rsrc netPrefsType	(hex) C00 ftrErrorClass
(id) neti netIFFFileType	(hex) D00 cmpErrorClass
(id) loop netIFCreatorLoop	(hex) E00 dlkErrorClass
(id) slip netIFCreatorSLIP	(hex) F00 padErrorClass
(id) ppp_ netIFCreatorPPP	(hex) 1000 grfErrorClass
(id) ram_ netIFCreatorRAM	(hex) 1100 mdmErrorClass
(id) psys sysNotifyBroadcasterCode	(hex) 1200 netErrorClass
(id) hots sysNotifySyncStartEvent	(hex) 1300 htalErrorClass
(id) sync sysNotifySyncFinishEvent	(hex) 1400 inetErrorClass
(id) tena sysNotifyAntennaRaisedEvent	(hex) 1500 exgErrorClass
(id) rstf sysNotifyResetFinishedEvent	(hex) 1600 fileErrorClass
(id) bozo sysNotifyForgotPasswordEvent	(hex) 1700 rftuErrorClass
(id) time sysNotifyTimeChangeEvent	(hex) 1800 txtErrorClass
(id) slpq sysNotifySleepRequestEvent	(hex) 1900 tsmErrorClass
(id) slp! sysNotifySleepNotifyEvent	(hex) 1A00 webErrorClass
(id) worm sysNotifyEarlyWakeupEvent	(hex) 1B00 secErrorClass
(id) lazy sysNotifyLateWakeupEvent	(hex) 1C00 emuErrorClass
(id) scrd sysNotifyDisplayChangeEvent	(hex) 1D00 flshErrorClass
(id) cbar sysNotifyMenuCmdBarOpenEvent	(hex) 1E00 pwrErrorClass
(id) cncp cncNotifyProfileEvent	(hex) 1F00 cncErrorClass
(id) ecna sysExternalConnectorAttachEvent	(hex) 2000 actvErrorClass
(id) ecnd sysExternalConnectorDetachEvent	(hex) 2100 radioErrorClass

(hex) 2200	dispErrorClass	1297	sysNotifyErrDuplicateEntry
(hex) 2300	bltErrorClass	1299	sysNotifyErrBroadcastBusy
(hex) 2400	winErrorClass	1300	sysNotifyErrBroadcastCancelled
(hex) 2500	omErrorClass	1301	sysErrMbId
(hex) 2600	menuErrorClass	1302	sysErrMbNone
(hex) 2700	lz77ErrorClass	1303	sysErrMbBusy
(hex) 2800	smsErrorClass	1304	sysErrMbFull
(hex) 2900	expErrorClass	1305	sysErrMbDepth
(hex) 2A00	vfsErrorClass	1306	sysErrMbEnv
(hex) 2B00	lmErrorClass	1307	sysNotifyErrQueueFull
(hex) 2C00	intlErrorClass	1308	sysNotifyErrQueueEmpty
(hex) 2D00	pdiErrorClass	1309	sysNotifyErrNoStackSpace
(hex) 2E00	attnErrorClass	1310	sysErrNotInitialized
(hex) 2F00	telErrorClass	1311	sysErrNotAsleep
(hex) 3000	hwrErrorClass	(hex) 520	sysErrNotAsleepN
(hex) 3100	blthErrorClass	(hex) 1E00	pwrErrNone
(hex) 3200	udaErrorClass	7681	pwrErrBacklight
(hex) 3800	cpmErrorClass	7682	pwrErrRadio
(hex) 3900	sslErrorClass	7683	pwrErrBeam
(hex) 7000	oemErrorClass	7684	pwrErrGeneric
(hex) 7F00	errInfoClass	19	sysFtrNumErrorCheckLevel
(hex) 8000	appErrorClass	769	serErrBadParam
2305	almErrMemory	770	serErrBadPort
2306	almErrFull	771	serErrNoMem
4353	mdmErrNoTone	772	serErrBadConnID
4354	mdmErrNoDCD	773	serErrTimeOut
4355	mdmErrBusy	774	serErrLineErr
4356	mdmErrUserCan	775	serErrAlreadyOpen
4357	mdmErrCmdError	776	serErrStillOpen
4358	mdmErrNoModem	777	serErrNotOpen
4359	mdmErrMemory	778	serErrNotSupported
4360	mdmErrPrefs	779	serErrNoDevicesAvail
4361	mdmErrDial	780	serErrConfigurationFailed
4362	mdmErrNoPhoneNum	1	serLineErrorParity
(hex) 2710	sysResIDErrStrings	2	serLineErrorHWOverrun
10002	sysResIDSndError	4	serLineErrorFraming
9217	winErrPalette	8	serLineErrorBreak
257	memErrChunkLocked	16	serLineErrorHShake
258	memErrNotEnoughSpace	32	serLineErrorSWOverrun
259	memErrInvalidParam	64	serLineErrorCarrierLost
260	memErrChunkNotLocked	9	sysSerialClearErr
261	memErrCardNotPresent	7937	kCncErrAddProfileFailed
262	memErrNoCardHeader	7938	kCncErrProfileListFull
263	memErrInvalidStoreHeader	7939	kCncErrGetProfileFailed
264	memErrRAMOnlyCard	7940	kCncErrDBAccessFailed
265	memErrWriteProtect	7941	kCncErrGetProfileListFailed
266	memErrNoRAMOnCard	7942	kCncErrProfileReadOnly
267	memErrNoStore	7943	kCncErrProfileNotFound
268	memErrROMOnlyCard	7944	kCncErrProfileParamNotFound
513	dmErrMemError	7945	kCncErrProfileParamReadOnly
514	dmErrIndexOutOfRange	7946	kCncErrProfileParamNameHasChange
515	dmErrInvalidParam	7947	kCncErrProfileGetParamFailed
516	dmErrReadOnly	7948	kCncErrProfileSetParamFailed
517	dmErrDatabaseOpen	7949	kCncErrProfileBadParamSize
518	dmErrCantOpen	7950	kCncErrProfileBadSystemFlagBitnum
519	dmErrCantFind	7937	cncErrAddProfileFailed
520	dmErrRecordInWrongCard	7938	cncErrProfileListFull
521	dmErrCorruptDatabase	7939	cncErrGetProfileFailed
522	dmErrRecordDeleted	7940	cncErrConDBNotFound
523	dmErrRecordArchived	7941	cncErrGetProfileListFailed
524	dmErrNotRecordDB	7942	cncErrProfileReadOnly
525	dmErrNotResourceDB	7943	cncErrProfileNotFound
526	dmErrROMBased	11009	lmErrUnknownLocale
527	dmErrRecordBusy	11010	lmErrBadLocaleIndex
(hex) 210	dmErrResourceNotFound	11011	lmErrBadLocaleSettingChoice
529	dmErrNoOpenDatabase	11012	lmErrSettingDataOverflow
530	dmErrInvalidCategory	5377	exgMemError
531	dmErrNotValidRecord	5378	exgErrStackInit
532	dmErrWriteOutOfBounds	5379	exgErrUserCancel
533	dmErrSeekFailed	5380	exgErrNoReceiver
534	dmErrAlreadyOpenForWrites	5381	exgErrNoKnownTarget
535	dmErrOpenedByAnotherTask	5382	exgErrTargetMissing
536	dmErrUniqueIDNotFound	5383	exgErrNotAllowed
537	dmErrAlreadyExists	5384	exgErrBadData
538	dmErrInvalidDatabaseName	5385	exgErrAppError
539	dmErrDatabaseProtected	5386	exgErrUnknown
540	dmErrDatabaseNotProtected	5387	exgErrDeviceFull
1281	sysErrTimeout	5388	exgErrDisconnected
1282	sysErrParamErr	5389	exgErrNotFound
1283	sysErrNoFreeResource	5390	exgErrBadParam
1284	sysErrNoFreeRAM	5391	exgErrNotSupported
1285	sysErrNotAllowed	(hex) 1510	exgErrDeviceBusy
1286	sysErrSemInUse	5393	exgErrBadLibrary
1287	sysErrInvalidID	5394	exgErrNotEnoughPower
1288	sysErrOutOfOwnerIDs	3073	ftrErrInvalidParam
1289	sysErrNoFreeLibSlots	3074	ftrErrNoSuchFeature
1290	sysErrLibNotFound	3075	ftrErrAlreadyExists
1291	sysErrDelayWakened	3076	ftrErrROMBased
1292	sysErrRomIncompatible	3077	ftrErrInternalErr
1293	sysErrBufTooSmall	5633	fileErrMemError
1294	sysErrPrefNotFound	5634	fileErrInvalidParam
(hex) 510	sysNotifyErrEntryNotFound	5635	fileErrCorruptFile

5636	fileErrNotFound	4630	netErrWrongSocketType
5637	fileErrTypeCreatorMismatch	4631	netErrSocketNotListening
5638	fileErrReplaceError	4632	netErrUnknownSetting
5639	fileErrCreateError	4633	netErrInvalidSettingSize
5640	fileErrOpenError	4634	netErrPrefNotFound
5641	fileErrInUse	4635	netErrInvalidInterface
5642	fileErrReadOnly	4636	netErrInterfaceNotFound
5643	fileErrInvalidDescriptor	4637	netErrTooManyInterfaces
5644	fileErrCloseError	4638	netErrBufWrongSize
5645	fileErrOutOfBounds	4639	netErrUserCancel
5646	fileErrPermissionDenied	(hex) 1220	netErrBadScript
5647	fileErrIOError	4641	netErrNoSocket
(hex) 1610	fileErrEOF	4642	netErrSocketRcvBufFull
5649	fileErrNotStream	4643	netErrNoPendingConnect
3	fileOpGetLastError	4644	netErrUnexpectedCmd
4	fileOpClearError	4645	netErrNoTCB
5	fileOpGetIOErrorStatus	4646	netErrNilRemoteWindowSize
1665	flpErrOutOfRange	4647	netErrNoTimerProc
4097	grfErrBadParam	4648	netErrSocketInputShutdown
4098	grfErrPointBufferFull	4649	netErrCmdBlockNotCheckedOut
4099	grfErrNoGlyphTable	4650	netErrCmdNotDone
4100	grfErrNoDictionary	4651	netErrUnknownProtocol
4101	grfErrNoMapping	4652	netErrUnknownService
4102	grfErrMacroNotFound	4653	netErrUnreachableDest
4103	grfErrDepthTooDeep	4654	netErrReadOnlySetting
4104	grfErrMacroPtrTooSmall	4655	netErrWouldBlock
4105	grfErrNoMacros	(hex) 1230	netErrAlreadyInProgress
4225	grfErrMacroIncomplete	4657	netErrPPPTimeout
4226	grfErrBranchNotFound	4658	netErrPPPBroughtDown
(hex) 1010	grfErrGenericHWRErrBase	4659	netErrAuthFailure
(hex) 1010	grfErrNoHWRInstalled	4660	netErrPPPAddressRefused
(hex) 300	hostSelectorErrNo	4661	netErrDNSNameTooLong
771	hostSelectorFError	4662	netErrDNSBadName
(hex) 1C00	hostErrorClass	4663	netErrDNSBadArgs
0	hostErrNone	4664	netErrDNSLabelTooLong
(hex) 1C00	hostErrBase	4665	netErrDNSAllocationFailure
7169	hostErrUnknownGestaltSelector	4666	netErrDNSTimeout
7170	hostErrDiskError	4667	netErrDNSUnreachable
7171	hostErrOutOfMemory	4668	netErrDNSFormat
7172	hostErrMemReadOutOfRange	4669	netErrDNSServerFailure
7173	hostErrMemWriteOutOfRange	4670	netErrDNSNonexistantName
7174	hostErrMemInvalidPtr	4671	netErrDNSNIY
7175	hostErrInvalidParameter	(hex) 1240	netErrDNSRefused
7176	hostErrTimeout	4673	netErrDNSImpossible
7177	hostErrInvalidDeviceType	4674	netErrDNSNoRRS
7178	hostErrInvalidRAMSize	4675	netErrDNSAborted
7179	hostErrFileNotFound	4676	netErrDNSBadProtocol
7180	hostErrRPCcall	4677	netErrDNSTruncated
7181	hostErrSessionRunning	4678	netErrDNSNoRecursion
7182	hostErrSessionNotRunning	4679	netErrDNSIrrelevant
7183	hostErrNoSignalWaiters	4680	netErrDNSNotInLocalCache
(hex) 1C10	hostErrSessionNotPaused	4681	netErrDNSNoPort
7185	hostErrPermissions	4682	netErrIPCantFragment
7186	hostErrFileNameTooLong	4683	netErrIPNoRoute
7187	hostErrNotADirectory	4684	netErrIPNoSrc
7188	hostErrTooManyFiles	4685	netErrIPNoDst
7189	hostErrFileTooBig	4686	netErrIPktOverflow
7190	hostErrReadOnlyFS	4687	netErrTooManyTCPConnections
7191	hostErrIsDirectory	(hex) 1250	netErrNoDNSServers
7192	hostErrExists	4689	netErrInterfaceDown
7193	hostErrOpNotAvailable	4690	netErrNoChannel
7194	hostErrDirNotEmpty	4691	netErrDieState
7195	hostErrDiskFull	4692	netErrReturnedInMail
7196	hostErrUnknownError	4693	netErrReturnedNoTransfer
7197	hostErrProfilingNotReady	4694	netErrReturnedIllegal
11265	intlErrInvalidSelector	4695	netErrReturnedCongest
2	netWlAppEventFlagDisplayErrs	4696	netErrReturnedError
4103	netSocketOptSockErrorStatus	4697	netErrReturnedBusy
8193	netSocketOptSockRequireErrClear	4698	netErrGMANState
1	netSocketNoticeErr	4699	netErrQuitOnTxFail
1	netTracingErrors	4700	netErrFlexListFull
4609	netErrAlreadyOpen	4701	netErrSenderMAN
4610	netErrNotOpen	4702	netErrIllegalType
4611	netErrStillOpen	4703	netErrIllegalState
4612	netErrParamErr	(hex) 1260	netErrIllegalFlags
4613	netErrNoMoreSockets	4705	netErrIllegalSendlist
4614	netErrOutOfResources	4706	netErrIllegalMPAKLength
4615	netErrOutOfMemory	4707	netErrIllegalAddressee
4616	netErrSocketNotOpen	4708	netErrIllegalPacketClass
4617	netErrSocketBusy	4709	netErrBufferLength
4618	netErrMessageTooBig	4710	netErrNiCdLowBattery
4619	netErrSocketNotConnected	4711	netErrRFinterfaceFatal
4620	netErrNoInterfaces	4712	netErrIllegalLogout
4621	netErrBufTooSmall	4713	netErrAAARadioLoad
4622	netErrUnimplemented	4714	netErrAntennaDown
4623	netErrPortInUse	4715	netErrNiCdCharging
(hex) 1210	netErrQuietTimeNotElapsed	4716	netErrAntennaWentDown
4625	netErrInternal	4717	netErrNotActivated
4626	netErrTimeout	4718	netErrRadioTemp
4627	netErrSocketAlreadyConnected	4719	netErrNiCdChargeError
4628	netErrSocketClosedByRemote	(hex) 1270	netErrNiCdSag
4629	netErrOutOfCmdBlocks	4721	netErrNiCdChargeSuspend

4723	netErrConfigNotFound	1	chrStartOfHeading
4724	netErrConfigCantDelete	2	chrStartOfText
4725	netErrConfigTooMany	3	chrEndOfText
4726	netErrConfigBadName	4	chrEndOfTransmission
4727	netErrConfigNotAlias	5	chrEnquiry
4728	netErrConfigCantPointToAlias	6	chrAcknowledge
4729	netErrConfigEmpty	7	chrBell
4730	netErrAlreadyOpenWithOtherConfig	8	chrBackspace
4731	netErrConfigAliasErr	9	chrHorizontalTabulation
4732	netErrNoMultiPktAddr	10	chrLineFeed
4733	netErrOutOfPackets	11	chrVerticalTabulation
4734	netErrMultiPktAddrReset	12	chrFormFeed
4735	netErrStaleMultiPktAddr	13	chrCarriageReturn
(hex) 1280	netErrScptPluginMissing	14	chrShiftOut
4737	netErrScptPluginLaunchFail	15	chrShiftIn
4738	netErrScptPluginCmdFail	16	chrDataLinkEscape
4739	netErrScptPluginInvalidCmd	17	chrDeviceControlOne
4740	netErrTelMissingComponent	18	chrDeviceControlTwo
4741	netErrTelErrorNotHandled	19	chrDeviceControlThree
4742	netErrDeviceNotReady	20	chrDeviceControlFour
4743	netErrDeviceInitFail	21	chrNegativeAcknowledge
4744	netErrInterfaceIncompatible	22	chrSynchronousIdle
4690	netErrMobitexStart	23	chrEndOfTransmissionBlock
4721	netErrMobitexEnd	24	chrCancel
0	omPtrShowErrorsFlag	25	chrEndOfMedium
9473	omErrBaseRequiresOverlay	26	chrSubstitute
9474	omErrUnknownLocale	27	chrEscape
9475	omErrBadOverlayDBName	28	chrFileSeparator
9476	omErrInvalidLocaleIndex	29	chrGroupSeparator
9477	omErrInvalidLocale	30	chrRecordSeparator
9478	omErrInvalidSystemOverlay	31	chrUnitSeparator
9479	omErrNoNextSystemLocale	32	chrSpace
2817	penErrBadParam	33	chrExclamationMark
2818	penErrIgnorePoint	34	chrQuotationMark
11777	attnErrMemory	35	chrNumberSign
128	drvrrStatusLineErr	36	chrDollarSign
1025	slkErrChecksum	37	chrPercentSign
1026	slkErrFormat	38	chrAmpersand
1027	slkErrBuffer	39	chrApostrophe
1028	slkErrTimeOut	40	chrLeftParenthesis
1029	slkErrHandle	41	chrRightParenthesis
1030	slkErrBodyLimit	42	chrAsterisk
1031	slkErrTransId	43	chrPlusSign
1032	slkErrResponse	44	chrComma
1033	slkErrNoDefaultProc	45	chrHyphenMinus
1034	slkErrWrongPacketType	46	chrFullStop
1035	slkErrBadParam	47	chrSolidus
1036	slkErrAlreadyOpen	48	chrDigitZero
1037	slkErrOutOfSockets	49	chrDigitOne
1038	slkErrSocketNotOpen	50	chrDigitTwo
1039	slkErrWrongDestSocket	51	chrDigitThree
(hex) 410	slkErrWrongPktType	52	chrDigitFour
1041	slkErrBusy	53	chrDigitFive
1042	slkErrNotOpen	54	chrDigitSix
3	sndError	55	chrDigitSeven
2049	sndErrBadParam	56	chrDigitEight
2050	sndErrBadChannel	57	chrDigitNine
2051	sndErrMemory	58	chrColon
2052	sndErrOpen	59	chrSemicolon
2053	sndErrQFull	60	chrLessThanSign
2054	sndErrQEmpty	61	chrEqualsSign
2055	sndErrFormat	62	chrGreaterThanSign
2056	sndErrBadStream	63	chrQuestionMark
2057	sndErrInterrupted	64	chrCommercialAt
2058	sndErrNotImpl	65	chrCapital_A
2059	sndErrInvalidStream	66	chrCapital_B
1793	evtErrParamErr	67	chrCapital_C
1794	evtErrQueueFull	68	chrCapital_D
1795	evtErrQueueEmpty	69	chrCapital_E
6145	txtErrUknownTranslitOp	70	chrCapital_F
6146	txtErrTranslitOverrun	71	chrCapital_G
6147	txtErrTranslitOverflow	72	chrCapital_H
6148	txtErrConvertOverflow	73	chrCapital_I
6149	txtErrConvertUnderflow	74	chrCapital_J
6150	txtErrUnknownEncoding	75	chrCapital_K
6151	txtErrNoCharMapping	76	chrCapital_L
6152	txtErrTranslitUnderflow	77	chrCapital_M
2561	timErrMemory	78	chrCapital_N
3	errorAlert	79	chrCapital_O
9729	menuErrNoMenu	80	chrCapital_P
9730	menuErrNotFound	81	chrCapital_Q
9731	menuErrSameId	82	chrCapital_R
9732	menuErrTooManyItems	83	chrCapital_S
9733	menuErrOutOfMemory	84	chrCapital_T
10021	ErrOKAlert	85	chrCapital_U
10022	ErrOKCancelAlert	86	chrCapital_V
10023	ErrCancelAlert	87	chrCapital_W
10034	StrippedBaseLaunchErrAlert	88	chrCapital_X
10035	GenericLaunchErrAlert	89	chrCapital_Y
11003	aboutErrorStr	90	chrCapital_Z
0	chrNull	91	chrLeftSquareBracket
		93	chrRightSquareBracket

94	chrCircumflexAccent		300	vchrIrGotData
95	chrLowLine		301	vchrResetAutoOff
96	chrGraveAccent	(hex)	200	vchrHardKeyMin
97	chrSmall_A		767	vchrHardKeyMax
98	chrSmall_B		516	vchrHard1
99	chrSmall_C		517	vchrHard2
100	chrSmall_D		518	vchrHard3
101	chrSmall_E		519	vchrHard4
102	chrSmall_F		520	vchrHardPower
103	chrSmall_G		521	vchrHardCradle
104	chrSmall_H		522	vchrHardCradle2
105	chrSmall_I		523	vchrHardContrast
106	chrSmall_J		524	vchrHardAntenna
107	chrSmall_K		525	vchrHardBrightness
108	chrSmall_L		527	vchrHardEarbud
109	chrSmall_M		532	vchrHard5
110	chrSmall_N		533	vchrHard6
111	chrSmall_O		534	vchrHard7
112	chrSmall_P		535	vchrHard8
113	chrSmall_Q		536	vchrHard9
114	chrSmall_R		537	vchrHard10
115	chrSmall_S	(hex)	300	vchrThumperMin
116	chrSmall_T		1023	vchrThumperMax
117	chrSmall_U	(hex)	500	vchrPalmMin
118	chrSmall_V		1535	vchrPalmMax
119	chrSmall_W		5325	vchrCessnaMin
120	chrSmall_X		5325	vchrCessnaMax
121	chrSmall_Y	(hex)	14D0	vchrAcerMin
122	chrSmall_Z	(hex)	14D0	vchrAcerMax
123	chrLeftCurlyBracket	(hex)	1500	vchrCFlashMin
124	chrVerticalLine		5391	vchrCFlashMax
125	chrRightCurlyBracket	(hex)	1550	vchrPhoenixMin
126	chrTilde		5487	vchrPhoenixMax
127	chrDelete	(hex)	15A0	vchrSPTMin
9	chrTab		5551	vchrSPTMax
11	vchrPageUp	(hex)	1600	vchrSlinkyMin
12	vchrPageDown		5887	vchrSlinkyMax
20	chrOtaSecure	(hex)	1700	vchrSonyMin
21	chrOta		6143	vchrSonyMax
22	chrCommandStroke	(hex)	1800	vchrAlphaSmartMin
23	chrShortcutStroke	(hex)	1800	vchrAlphaSmartMax
24	chrEllipsis		0	nullChr
25	chrNumericSpace		8	backspaceChr
26	chrCardIcon		9	tabChr
28	chrLeftArrow		10	linefeedChr
29	chrRightArrow		11	pageUpChr
30	chrUpArrow		11	chrPageUp
31	chrDownArrow		12	pageDownChr
257	vchrLowBattery		12	chrPageDown
258	vchrEnterDebugger		13	crChr
259	vchrNextField		13	returnChr
260	vchrStartConsole		20	otaSecureChr
261	vchrMenu		21	otaChr
262	vchrCommand		27	escapeChr
263	vchrConfirm		28	leftArrowChr
264	vchrLaunch		29	rightArrowChr
265	vchrKeyboard		30	upArrowChr
266	vchrFind		31	downArrowChr
267	vchrCalc		32	spaceChr
268	vchrPrevField		34	quoteChr
269	vchrAlarm		44	commaChr
270	vchrRonamatic		46	periodChr
271	vchrGraffitiReference		58	colonChr
(hex) 110	vchrKeyboardAlpha		257	lowBatteryChr
273	vchrKeyboardNumeric		258	enterDebuggerChr
274	vchrLock		259	nextFieldChr
275	vchrBacklight		260	startConsoleChr
276	vchrAutoOff		261	menuChr
277	vchrExgTest		262	commandChr
278	vchrSendData		263	confirmChr
279	vchrIrReceive		264	launchChr
280	vchrTsm1		265	keyboardChr
281	vchrTsm2		266	findChr
282	vchrTsm3		267	calcChr
283	vchrTsm4		268	prevFieldChr
284	vchrRadioCoverageOK		269	alarmChr
285	vchrRadioCoverageFail		270	ronamaticChr
286	vchrPowerOff		271	graffitiReferenceChr
287	vchrResumeSleep	(hex)	110	keyboardAlphaChr
(hex) 120	vchrLateWakeup		273	keyboardNumericChr
289	vchrTsmMode		274	lockChr
290	vchrBrightness		275	backlightChr
291	vchrContrast		276	autoOffChr
292	vchrExpCardInserted		277	exgTestChr
293	vchrExpCardRemoved		278	sendDataChr
511	vchrExgIntData		279	irReceiveChr
294	vchrAttnStateChanged		284	radioCoverageOKChr
295	vchrAttnUnsnooze		285	radioCoverageFailChr
296	vchrAttnIndicatorTapped		286	powerOffChr
297	vchrAttnAllowClose		287	resumeSleepChr
298	vchrAttnReopen	(hex)	120	lateWakeupChr
299	vchrCardCloseMenu		290	brightnessChr

291	contrastChr	11	charEncodingXAutoJp
516	hard1Chr	33	charEncodingISO8859_7
517	hard2Chr	34	charEncodingCP1253
518	hard3Chr	35	charEncodingCP869
519	hard4Chr	36	charEncodingCP737
520	hardPowerChr	37	charEncodingMacXGr
521	hardCradleChr	38	charEncodingCP1251
522	hardCradle2Chr	39	charEncodingISO8859_5
523	hardContrastChr	40	charEncodingKoi8R
524	hardAntennaChr	41	charEncodingKoi8
525	hardBrightnessChr	42	charEncodingCP855
527	hardEarbudChr	43	charEncodingCP866
3	symbolLeftArrow	44	charEncodingMacCyr
4	symbolRightArrow	45	charEncodingMacUkraine
5	symbolUpArrow	46	charEncodingCP1254
6	symbolDownArrow	47	charEncodingISO8859_9
7	symbolSmallDownArrow	48	charEncodingCP857
8	symbolSmallUpArrow	49	charEncodingMacTurc
9	symbolMemo	50	charEncodingCP853
10	symbolHelp	51	charEncodingISO8859_6
11	symbolNote	52	charEncodingAsmo708
12	symbolNoteSelected	53	charEncodingCP1256
13	symbolCapsLock	54	charEncodingCP864
14	symbolNumLock	55	charEncodingAsmo708Plus
15	symbolShiftUpper	56	charEncodingAsmo708Fr
16	symbolShiftPunc	57	charEncodingMacAra
17	symbolShiftExt	58	charEncodingGB2312
18	symbolShiftNone	59	charEncodingHZ
19	symbolNoTime	60	charEncodingBig5
20	symbolAlarm	61	charEncodingViscii
21	symbolRepeat	62	charEncodingViqr
22	symbolCheckMark	63	charEncodingVncii
23	symbolDiamondChr	65	charEncodingVietnet
24	symbolClubChr	66	charEncodingCP1258
25	symbolHeartChr	67	charEncodingKsc5601
26	symbolSpadeChr	68	charEncodingCP949
1	symbol7ScrollUp	69	charEncodingISO2022Kr
2	symbol7ScrollDown	70	charEncodingISO8859_8I
3	symbol7ScrollUpDisabled	71	charEncodingISO8859_8
4	symbol7ScrollDownDisabled	72	charEncodingCP1255
0	symbolCheckboxOff	73	charEncodingCP1255V
1	symbolCheckboxOn	74	charEncodingTis620
2	symbol11LeftArrow	64	charEncodingCP874
3	symbol11RightArrow	1	charEncodingOnlySingleByte
4	symbol11Help	2	charEncodingHasDoubleByte
5	symbol11LeftArrowDisabled	4	charEncodingHasLigatures
6	symbol11RightArrowDisabled	8	charEncodingRightToLeft
3	symbolFont	(hex) 200	charAttr_XA
4	symbol11Font	(hex) 100	charAttr_XS
5	symbol7Font	128	charAttr_BB
3	srnUSBIsochronous	64	charAttr_CN
511	exgIntDataChr	32	charAttr_DI
58	valueDelimiterChr	16	charAttr_LO
46	groupDelimiterChr	8	charAttr_PU
61	paramaterNameDelimiterChr	4	charAttr_SP
13	endOfLineChr	2	charAttr_UP
0	charEncodingUnknown	1	charAttr_XD
77	charEncodingMax	574	charAttrPrint
3	charEncodingPalmLatin	324	charAttrSpace
7	charEncodingCP1252	562	charAttrAlNum
2	charEncodingISO8859_1	530	charAttrAlpha
1	charEncodingAscii	192	charAttrCntrl
5	charEncodingPalmSJIS	570	charAttrGraph
8	charEncodingCP932	12	charAttrDelim
4	charEncodingShiftJIS	(hex) A381	sysTrapWinGetPixel
9	charEncodingUCS2	(hex) A1D7	sysTrapTblRowSelectable
6	charEncodingUTF8	(hex) A1D8	sysTrapTblSetLoadDataProcedure
24	charEncodingUTF7	(hex) A1D9	sysTrapTblSetSaveDataProcedure
75	charEncodingUTF16	(hex) A1DA	sysTrapTblGetBounds
76	charEncodingUTF16BE	(hex) A1DB	sysTrapTblSetRowHeight
77	charEncodingUTF16LE	(hex) A1DC	sysTrapTblGetColumnWidth
12	charEncodingCP850	(hex) A1DD	sysTrapTblGetRowID
13	charEncodingCP437	(hex) A1DE	sysTrapTblSetRowID
14	charEncodingCP865	(hex) A1DF	sysTrapTblMarkRowInvalid
15	charEncodingCP860	(hex) A1E0	sysTrapTblMarkTableInvalid
16	charEncodingCP861	(hex) A382	sysTrapWinPaintPixel
17	charEncodingCP863	(hex) A1E1	sysTrapTblGetSelection
18	charEncodingCP775	(hex) A1E2	sysTrapTblInsertRow
19	charEncodingMacIslande	(hex) A1E3	sysTrapTblRemoveRow
20	charEncodingMacintosh	(hex) A1E4	sysTrapTblRowInvalid
21	charEncodingCP1257	(hex) A1E5	sysTrapTblRedrawTable
22	charEncodingISO8859_3	(hex) A1E6	sysTrapTblRowUsable
23	charEncodingISO8859_4	(hex) A1E7	sysTrapTblReleaseFocus
26	charEncodingISO8859_2	(hex) A1E8	sysTrapTblEditing
27	charEncodingCP1250	(hex) A1E9	sysTrapTblGetCurrentField
28	charEncodingCP852	(hex) A1EA	sysTrapTblSetColumnUsable
29	charEncodingXKamenicky	(hex) A383	sysTrapWinDrawPixel
30	charEncodingMacXCroate	(hex) A1EB	sysTrapTblGetRowHeight
31	charEncodingMacXLat2	(hex) A1EC	sysTrapTblSetColumnWidth
32	charEncodingMacXRomania	(hex) A1ED	sysTrapTblGrabFocus
25	charEncodingEucJp	(hex) A1EE	sysTrapTblSetItemPtr
10	charEncodingISO2022Jp		

(hex) A1EF	sysTrapTblFindRowIndex	(hex) A243	sysTrapHwrSetCPUDutyCycle
(hex) A1F0	sysTrapTblGetLastUsableRow	(hex) A244	sysTrapHwrDisplayInit
(hex) A1F1	sysTrapTblGetColumnSpacing	(hex) A38C	sysTrapWinDrawPolygon
(hex) A1F2	sysTrapTblFindRowData	(hex) A245	sysTrapHwrDisplaySleep
(hex) A1F3	sysTrapTblGetRowData	(hex) A246	sysTrapHwrTimerInit
(hex) A1F4	sysTrapTblSetRowData	(hex) A247	sysTrapHwrCursorV33
(hex) A384	sysTrapWinErasePixel	(hex) A248	sysTrapHwrBatteryLevel
(hex) A1F5	sysTrapTblSetColumnSpacing	(hex) A249	sysTrapHwrDelay
(hex) A1F6	sysTrapWinCreateWindow	(hex) A24A	sysTrapHwrEnableDataWrites
(hex) A1F7	sysTrapWinCreateOffscreenWindow	(hex) A24B	sysTrapHwrDisableDataWrites
(hex) A1F8	sysTrapWinDeleteWindow	(hex) A24C	sysTrapHwrLCDBaseAddrV33
(hex) A1F9	sysTrapWinInitializeWindow	(hex) A24D	sysTrapHwrDisplayDrawBootScreen
(hex) A1FA	sysTrapWinAddWindow	(hex) A24E	sysTrapHwrTimerSleep
(hex) A1FB	sysTrapWinRemoveWindow	(hex) A38D	sysTrapWinErasePolygon
(hex) A1FC	sysTrapWinSetActiveWindow	(hex) A24F	sysTrapHwrTimerWake
(hex) A1FD	sysTrapWinSetDrawWindow	(hex) A250	sysTrapHwrDisplayWake
(hex) A1FE	sysTrapWinGetDrawWindow	(hex) A251	sysTrapHwrIRQ1Handler
(hex) A385	sysTrapWinInvertPixel	(hex) A252	sysTrapHwrIRQ2Handler
(hex) A1FF	sysTrapWinGetActiveWindow	(hex) A253	sysTrapHwrIRQ3Handler
(hex) A200	sysTrapWinGetDisplayWindow	(hex) A254	sysTrapHwrIRQ4Handler
(hex) A201	sysTrapWinGetFirstWindow	(hex) A255	sysTrapHwrIRQ5Handler
(hex) A202	sysTrapWinEnableWindow	(hex) A256	sysTrapHwrIRQ6Handler
(hex) A203	sysTrapWinDisableWindow	(hex) A257	sysTrapHwrDockSignals
(hex) A204	sysTrapWinGetWindowFrameRect	(hex) A258	sysTrapHwrPluggedIn
(hex) A205	sysTrapWinDrawWindowFrame	(hex) A38E	sysTrapWinInvertPolygon
(hex) A206	sysTrapWinEraseWindow	(hex) A259	sysTrapCrcl6CalcBlock
(hex) A207	sysTrapWinSaveBits	(hex) A25A	sysTrapSelectDayV10
(hex) A208	sysTrapWinRestoreBits	(hex) A25B	sysTrapSelectTimeV33
(hex) A386	sysTrapWinPaintPixels	(hex) A25C	sysTrapDayDrawDaySelector
(hex) A209	sysTrapWinCopyRectangle	(hex) A25D	sysTrapDayHandleEvent
(hex) A20A	sysTrapWinScrollRectangle	(hex) A25E	sysTrapDayDrawDays
(hex) A20B	sysTrapWinGetDisplayExtent	(hex) A25F	sysTrapDayOfWeek
(hex) A20C	sysTrapWinGetWindowExtent	(hex) A260	sysTrapDaysInMonth
(hex) A20D	sysTrapWinDisplayToWindowPt	(hex) A261	sysTrapDayOfMonth
(hex) A20E	sysTrapWinWindowToDisplayPt	(hex) A262	sysTrapDateDaysToDate
(hex) A20F	sysTrapWinGetClip	(hex) A38F	sysTrapWinFillPolygon
(hex) A210	sysTrapWinSetClip	(hex) A263	sysTrapDateToDays
(hex) A211	sysTrapWinResetClip	(hex) A264	sysTrapDateAdjust
(hex) A212	sysTrapWinClipRectangle	(hex) A265	sysTrapDateSecondsToDate
(hex) A387	sysTrapWinPaintLines	(hex) A266	sysTrapDateToAscii
(hex) A213	sysTrapWinDrawLine	(hex) A267	sysTrapDateToDOWDMFormat
(hex) A214	sysTrapWinDrawGrayLine	(hex) A268	sysTrapTimeToAscii
(hex) A215	sysTrapWinEraseLine	(hex) A269	sysTrapFind
(hex) A216	sysTrapWinInvertLine	(hex) A26A	sysTrapFindStrInStr
(hex) A217	sysTrapWinFillLine	(hex) A26B	sysTrapFindSaveMatch
(hex) A218	sysTrapWinDrawRectangle	(hex) A26C	sysTrapFindGetLineBounds
(hex) A219	sysTrapWinEraseRectangle	(hex) A390	sysTrapWinPaintArc
(hex) A21A	sysTrapWinInvertRectangle	(hex) A26D	sysTrapFindDrawHeader
(hex) A21B	sysTrapWinDrawRectangleFrame	(hex) A26E	sysTrapPenOpen
(hex) A21C	sysTrapWinDrawGrayRectangleFrame	(hex) A26F	sysTrapPenClose
(hex) A388	sysTrapWinPaintLine	(hex) A270	sysTrapPenGetRawPen
(hex) A21D	sysTrapWinEraseRectangleFrame	(hex) A271	sysTrapPenCalibrate
(hex) A21E	sysTrapWinInvertRectangleFrame	(hex) A272	sysTrapPenRawToScreen
(hex) A21F	sysTrapWinGetFramesRectangle	(hex) A273	sysTrapPenScreenToRaw
(hex) A220	sysTrapWinDrawChars	(hex) A274	sysTrapPenResetCalibration
(hex) A221	sysTrapWinEraseChars	(hex) A275	sysTrapPenSleep
(hex) A222	sysTrapWinInvertChars	(hex) A276	sysTrapPenWake
(hex) A223	sysTrapWinGetPattern	(hex) A391	sysTrapWinDrawArc
(hex) A224	sysTrapWinSetPattern	(hex) A277	sysTrapResLoadForm
(hex) A225	sysTrapWinSetUnderlineMode	(hex) A278	sysTrapResLoadMenu
(hex) A226	sysTrapWinDrawBitmap	(hex) A279	sysTrapFtrInit
(hex) A389	sysTrapWinPaintRectangle	(hex) A27A	sysTrapFtrUnregister
(hex) A227	sysTrapWinModal	(hex) A27B	sysTrapFtrGet
(hex) A228	sysTrapWinGetDrawWindowBounds	(hex) A27C	sysTrapFtrSet
(hex) A229	sysTrapWinFillRectangle	(hex) A27D	sysTrapFtrGetByIndex
(hex) A22A	sysTrapWinDrawInvertedChars	(hex) A27E	sysTrapGrfInit
(hex) A22B	sysTrapPrefOpenPreferencesDBV10	(hex) A27F	sysTrapGrfFree
(hex) A22C	sysTrapPrefGetPreferences	(hex) A280	sysTrapGrfGetState
(hex) A22D	sysTrapPrefSetPreferences	(hex) A392	sysTrapWinEraseArc
(hex) A22E	sysTrapPrefGetAppPreferencesV10	(hex) A281	sysTrapGrfSetState
(hex) A22F	sysTrapPrefSetAppPreferencesV10	(hex) A282	sysTrapGrfFlushPoints
(hex) A230	sysTrapSndInit	(hex) A283	sysTrapGrfAddPoint
(hex) A38A	sysTrapWinPaintRectangleFrame	(hex) A284	sysTrapGrfInitState
(hex) A231	sysTrapSndSetDefaultVolume	(hex) A285	sysTrapGrfCleanState
(hex) A232	sysTrapSndGetDefaultVolume	(hex) A286	sysTrapGrfMatch
(hex) A233	sysTrapSndDoCmd	(hex) A287	sysTrapGrfGetMacro
(hex) A234	sysTrapSndPlaySystemSound	(hex) A288	sysTrapGrfFilterPoints
(hex) A235	sysTrapAlmInit	(hex) A289	sysTrapGrfGetNumPoints
(hex) A236	sysTrapAlmCancelAll	(hex) A28A	sysTrapGrfGetPoint
(hex) A237	sysTrapAlmAlarmCallback	(hex) A393	sysTrapWinInvertArc
(hex) A238	sysTrapAlmSetAlarm	(hex) A28B	sysTrapGrfFindBranch
(hex) A239	sysTrapAlmGetAlarm	(hex) A28C	sysTrapGrfMatchGlyph
(hex) A23A	sysTrapAlmDisplayAlarm	(hex) A28D	sysTrapGrfGetGlyphMapping
(hex) A38B	sysTrapWinPaintPolygon	(hex) A28E	sysTrapGrfGetMacroName
(hex) A23B	sysTrapAlmEnableNotification	(hex) A28F	sysTrapGrfDeleteMacro
(hex) A23C	sysTrapHwrGetRAMMapping	(hex) A290	sysTrapGrfAddMacro
(hex) A23D	sysTrapHwrMemWritable	(hex) A291	sysTrapGrfGetAndExpandMacro
(hex) A23E	sysTrapHwrMemReadable	(hex) A292	sysTrapGrfProcessStroke
(hex) A23F	sysTrapHwrDoze	(hex) A293	sysTrapGrfFieldChange
(hex) A240	sysTrapHwrSleep	(hex) A294	sysTrapGetCharSortValue
(hex) A241	sysTrapHwrWake	(hex) A394	sysTrapWinFillArc
(hex) A242	sysTrapHwrSetSystemClock	(hex) A295	sysTrapGetCharAttr

(hex) A296	sysTrapGetCharCaselessValue	(hex) A2E9	sysTrapSysTicksPerSecond
(hex) A297	sysTrapPwdExists	(hex) A2EA	sysTrapHwrBacklightV33
(hex) A298	sysTrapPwdVerify	(hex) A2EB	sysTrapDmDatabaseProtect
(hex) A299	sysTrapPwdSet	(hex) A2EC	sysTrapTblSetBounds
(hex) A29A	sysTrapPwdRemove	(hex) A2ED	sysTrapStrNCompare
(hex) A29B	sysTrapGsiInitialize	(hex) A2EE	sysTrapStrNCaselessCompare
(hex) A29C	sysTrapGsiSetLocation	(hex) A29D	sysTrapWinPalette
(hex) A29D	sysTrapGsiEnable	(hex) A2EF	sysTrapPhoneNumberLookup
(hex) A29E	sysTrapGsiEnabled	(hex) A2F0	sysTrapFrmSetMenu
(hex) A000	sysTrapBase	(hex) A2F1	sysTrapEncDigestMD5
(hex) A395	sysTrapWinPushDrawState	(hex) A2F2	sysTrapDmFindSortPosition
(hex) A29F	sysTrapGsiSetShiftState	(hex) A2F3	sysTrapSysBinarySearch
(hex) A2A0	sysTrapKeyInit	(hex) A2F4	sysTrapSysErrString
(hex) A2A1	sysTrapKeyHandleInterrupt	(hex) A2F5	sysTrapSysStringByIndex
(hex) A2A2	sysTrapKeyCurrentState	(hex) A2F6	sysTrapEvtAddUniqueEventToQueue
(hex) A2A3	sysTrapKeyResetDoubleClick	(hex) A2F7	sysTrapStrLocalizeNumber
(hex) A2A4	sysTrapKeyRates	(hex) A2F8	sysTrapStrDelocalizeNumber
(hex) A2A5	sysTrapKeySleep	(hex) A39E	sysTrapWinRGBToIndex
(hex) A2A6	sysTrapKeyWake	(hex) A2F9	sysTrapLocGetNumberSeparators
(hex) A2A7	sysTrapDlkControl	(hex) A2FA	sysTrapMenuSetActiveMenuRscID
(hex) A2A8	sysTrapDlkStartServer	(hex) A2FB	sysTrapLstScrollList
(hex) A396	sysTrapWinPopDrawState	(hex) A2FC	sysTrapCategoryInitialize
(hex) A2A9	sysTrapDlkGetSyncInfo	(hex) A2FD	sysTrapEncDigestMD4
(hex) A2AA	sysTrapDlkSetLogEntry	(hex) A2FE	sysTrapEncDES
(hex) A2AB	sysTrapIntlDispatch	(hex) A2FF	sysTrapLstGetVisibleItems
(hex) A2AC	sysTrapSysLibLoad	(hex) A300	sysTrapWinSetBounds
(hex) A2AD	sysTrapSndPlaySmf	(hex) A301	sysTrapCategorySetName
(hex) A2AE	sysTrapSndCreateMidiList	(hex) A302	sysTrapFldSetInsertionPoint
(hex) A2AF	sysTrapAbtShowAbout	(hex) A000	sysTrapMemInit
(hex) A2B0	sysTrapMdmDial	(hex) A39F	sysTrapWinIndexToRGB
(hex) A2B1	sysTrapMdmHangUp	(hex) A303	sysTrapFrmSetObjectBounds
(hex) A2B2	sysTrapDmSearchRecord	(hex) A304	sysTrapWinSetColors
(hex) A397	sysTrapWinSetDrawMode	(hex) A305	sysTrapFlpDispatch
(hex) A2B3	sysTrapSysInsertionSort	(hex) A306	sysTrapFlpEmDispatch
(hex) A2B4	sysTrapDmInsertionSort	(hex) A307	sysTrapExgInit
(hex) A2B5	sysTrapLstSetTopItem	(hex) A308	sysTrapExgConnect
(hex) A2B6	sysTrapSclSetScrollBar	(hex) A309	sysTrapExgPut
(hex) A2B7	sysTrapSclDrawScrollBar	(hex) A30A	sysTrapExgGet
(hex) A2B8	sysTrapSclHandleEvent	(hex) A30B	sysTrapExgAccept
(hex) A2B9	sysTrapSysMailboxCreate	(hex) A30C	sysTrapExgDisconnect
(hex) A2BA	sysTrapSysMailboxDelete	(hex) A3A0	sysTrapWinScreenLock
(hex) A2BB	sysTrapSysMailboxFlush	(hex) A30D	sysTrapExgSend
(hex) A2BC	sysTrapSysMailboxSend	(hex) A30E	sysTrapExgReceive
(hex) A398	sysTrapWinSetForeColor	(hex) A30F	sysTrapExgRegisterData
(hex) A2BD	sysTrapSysMailboxWait	(hex) A310	sysTrapExgNotifyReceiveV35
(hex) A2BE	sysTrapSysTaskWait	(hex) A311	sysTrapSysReserved30Trap2
(hex) A2BF	sysTrapSysTaskWake	(hex) A312	sysTrapPrgStartDialogV31
(hex) A2C0	sysTrapSysTaskWaitClr	(hex) A313	sysTrapPrgStopDialog
(hex) A2C1	sysTrapSysTaskSuspend	(hex) A314	sysTrapPrgUpdateDialog
(hex) A2C2	sysTrapSysTaskResume	(hex) A315	sysTrapPrgHandleEvent
(hex) A2C3	sysTrapCategoryCreateList	(hex) A316	sysTrapImcReadFieldNoSemicolon
(hex) A2C4	sysTrapCategoryFreeList	(hex) A3A1	sysTrapWinScreenUnlock
(hex) A2C5	sysTrapCategoryEeditV20	(hex) A317	sysTrapImcReadFieldQuotablePrintable
(hex) A2C6	sysTrapCategorySelect	(hex) A318	sysTrapImcReadPropertyParameter
(hex) A399	sysTrapWinSetBackColor	(hex) A319	sysTrapImcSkipAllPropertyParameters
(hex) A2C7	sysTrapDmDeleteCategory	(hex) A31A	sysTrapImcReadWhiteSpace
(hex) A2C8	sysTrapSysEvGroupCreate	(hex) A31B	sysTrapImcWriteQuotedPrintable
(hex) A2C9	sysTrapSysEvGroupSignal	(hex) A31C	sysTrapImcWriteNoSemicolon
(hex) A2CA	sysTrapSysEvGroupRead	(hex) A31D	sysTrapImcStringIsAscii
(hex) A2CB	sysTrapSysEvGroupWait	(hex) A31E	sysTrapTblGetItemFont
(hex) A2CC	sysTrapEvtEventAvail	(hex) A31F	sysTrapTblSetItemFont
(hex) A2CD	sysTrapEvtSysEventAvail	(hex) A320	sysTrapFontSelect
(hex) A2CE	sysTrapStrNCopy	(hex) A3A2	sysTrapWinGetBitmap
(hex) A2CF	sysTrapKeySetMask	(hex) A321	sysTrapFntDefineFont
(hex) A2D0	sysTrapSelectDay	(hex) A322	sysTrapCategoryEdit
(hex) A39A	sysTrapWinSetTextColor	(hex) A323	sysTrapSysGetOSVersionString
(hex) A2D1	sysTrapPrefGetPreference	(hex) A324	sysTrapSysBatteryInfo
(hex) A2D2	sysTrapPrefSetPreference	(hex) A325	sysTrapSysUIBusy
(hex) A2D3	sysTrapPrefGetAppPreferences	(hex) A326	sysTrapWinValidateHandle
(hex) A2D4	sysTrapPrefSetAppPreferences	(hex) A327	sysTrapFrmValidatePtr
(hex) A2D5	sysTrapFrmPointInTitle	(hex) A328	sysTrapCtlValidatePointer
(hex) A2D6	sysTrapStrNcat	(hex) A329	sysTrapWinMoveWindowAddr
(hex) A2D7	sysTrapMemCmp	(hex) A32A	sysTrapFrmAddSpaceForObject
(hex) A2D8	sysTrapTblSetColumnEditIndicator	(hex) A3A3	sysTrapUIColorInit
(hex) A2D9	sysTrapFntWordWrap	(hex) A32B	sysTrapFrmNewForm
(hex) A2DA	sysTrapFldGetScrollValues	(hex) A32C	sysTrapCtlNewControl
(hex) A39B	sysTrapWinGetPatternType	(hex) A32D	sysTrapFldNewField
(hex) A2DB	sysTrapSysCreateDataBaseList	(hex) A32E	sysTrapLstNewList
(hex) A2DC	sysTrapSysCreatePanelList	(hex) A32F	sysTrapFrmNewLabel
(hex) A2DD	sysTrapDlkDispatchRequest	(hex) A330	sysTrapFrmNewBitmap
(hex) A2DE	sysTrapStrPrintf	(hex) A331	sysTrapFrmNewGadget
(hex) A2DF	sysTrapStrVPrintf	(hex) A332	sysTrapFileOpen
(hex) A2E0	sysTrapPrefOpenPreferenceDB	(hex) A333	sysTrapFileClose
(hex) A2E1	sysTrapSysGraffitiReferenceDialog	(hex) A334	sysTrapFileDelete
(hex) A2E2	sysTrapSysKeyboardDialog	(hex) A3A4	sysTrapUIColorGetTableEntryIndex
(hex) A2E3	sysTrapFntWordWrapReverseNLines	(hex) A335	sysTrapFileReadLow
(hex) A2E4	sysTrapFntGetScrollValues	(hex) A336	sysTrapFileWrite
(hex) A39C	sysTrapWinSetPatternType	(hex) A337	sysTrapFileSeek
(hex) A2E5	sysTrapTblSetRowStaticHeight	(hex) A338	sysTrapFileTell
(hex) A2E6	sysTrapTblHasScrollBar	(hex) A339	sysTrapFileTruncate
(hex) A2E7	sysTrapSclGetScrollBar	(hex) A33A	sysTrapFileControl
(hex) A2E8	sysTrapFldGetNumberOfBlankLines	(hex) A33B	sysTrapFrmActiveState



```

(hex) A33C sysTrapSysGetAppInfo
(hex) A33D sysTrapSysGetStackInfo
(hex) A33E sysTrapWinScreenMode
(hex) A3A5 sysTrapUIColorGetTableEntryRGB
(hex) A33F sysTrapHwrLCDGetDepthV33
(hex) A340 sysTrapHwrGetROMToken
(hex) A341 sysTrapDbgControl
(hex) A342 sysTrapExgDBRead
(hex) A343 sysTrapExgDBWrite
(hex) A344 sysTrapHostControl
(hex) A345 sysTrapFrmRemoveObject
(hex) A346 sysTrapSysReserved30Trap1
(hex) A347 sysTrapExpansionDispatch
(hex) A348 sysTrapFileSystemServiceDispatch
(hex) A3A6 sysTrapUIColorSetTableEntry
(hex) A349 sysTrapOEMDispatch
(hex) A34A sysTrapHwrLCDContrastV33
(hex) A34B sysTrapSysLCDContrast
(hex) A34C sysTrapUIColorContrastAdjust
(hex) A34D sysTrapHwrDockStatus
(hex) A34E sysTrapFntWidthToOffset
(hex) A34F sysTrapSelectOneTime
(hex) A350 sysTrapWinDrawChar
(hex) A351 sysTrapWinDrawTruncChars
(hex) A352 sysTrapSysNotifyInit
(hex) A3A7 sysTrapUIColorPushTable
(hex) A353 sysTrapSysNotifyRegister
(hex) A354 sysTrapSysNotifyUnregister
(hex) A355 sysTrapSysNotifyBroadcast
(hex) A356 sysTrapSysNotifyBroadcastDeferred
(hex) A357 sysTrapSysNotifyDatabaseAdded
(hex) A358 sysTrapSysNotifyDatabaseRemoved
(hex) A359 sysTrapSysWantEvent
(hex) A35A sysTrapFtrPtrNew
(hex) A35B sysTrapFtrPtrFree
(hex) A35C sysTrapFtrPtrResize
(hex) A3A8 sysTrapUIColorPopTable
(hex) A35D sysTrapSysReserved31Trap1
(hex) A35E sysTrapHwrNVVPrefSet
(hex) A35F sysTrapHwrNVVPrefGet
(hex) A360 sysTrapFlashInit
(hex) A361 sysTrapFlashCompress
(hex) A362 sysTrapFlashErase
(hex) A363 sysTrapFlashProgram
(hex) A364 sysTrapAlmTimeChange
(hex) A365 sysTrapErrAlertCustom
(hex) A366 sysTrapPrgStartDialog
(hex) A001 sysTrapMemInitHeapTable
(hex) A3A9 sysTrapCtlNewGraphicControl
(hex) A367 sysTrapSerialDispatch
(hex) A368 sysTrapHwrBattery
(hex) A369 sysTrapDmGetDatabaseLockState
(hex) A36A sysTrapCncGetProfileList
(hex) A36B sysTrapCncGetProfileInfo
(hex) A36C sysTrapCncAddProfile
(hex) A36D sysTrapCncDeleteProfile
(hex) A36E sysTrapSndPlaySmfResource
(hex) A36F sysTrapMemPtrDataStorage
(hex) A370 sysTrapClipboardAppendItem
(hex) A3AA sysTrapTblGetItemPtr
(hex) A371 sysTrapWiCmdV32
(hex) A372 sysTrapHwrDisplayAttributes
(hex) A373 sysTrapHwrDisplayDoze
(hex) A374 sysTrapHwrDisplayPalette
(hex) A375 sysTrapBltFindIndexes
(hex) A376 sysTrapBmpGetBits
(hex) A377 sysTrapBltCopyRectangle
(hex) A378 sysTrapBltDrawChars
(hex) A379 sysTrapBltLineRoutine
(hex) A37A sysTrapBltRectangleRoutine
(hex) A3AB sysTrapUIBrightnessAdjust
(hex) A37B sysTrapScrCompress
(hex) A37C sysTrapScrDecompress
(hex) A37D sysTrapSysLCDBrightness
(hex) A37E sysTrapWinPaintChar
(hex) A37F sysTrapWinPaintChars
(hex) A380 sysTrapWinPaintBitmap
(hex) A3AC sysTrapUIPickColor
(hex) A3AD sysTrapEvtSetAutoOffTimer
(hex) A3AE sysTrapTsmDispatch
(hex) A3AF sysTrapOmDispatch
(hex) A3B0 sysTrapDmOpenDBNoOverlay
(hex) A3B1 sysTrapDmOpenDBWithLocale
(hex) A3B2 sysTrapResLoadConstant
(hex) A3B3 sysTrapHwrPreDebugInit
(hex) A3B4 sysTrapHwrResetNMI
(hex) A3B5 sysTrapHwrResetPMM
(hex) A3B6 sysTrapKeyBootKeys
(hex) A3B7 sysTrapDbgSerDrvOpen
(hex) A3B8 sysTrapDbgSerDrvClose
(hex) A3B9 sysTrapDbgSerDrvControl
(hex) A3BA sysTrapDbgSerDrvStatus
(hex) A3BB sysTrapDbgSerDrvWriteChar
(hex) A3BC sysTrapDbgSerDrvReadChar
(hex) A3BD sysTrapHwrPostDebugInit
(hex) A3BE sysTrapHwrIdentifyFeatures
(hex) A3BF sysTrapHwrModelSpecificInit
(hex) A3C0 sysTrapHwrModelInitStage2
(hex) A3C1 sysTrapHwrInterruptsInit
(hex) A3C2 sysTrapHwrSoundOn
(hex) A3C3 sysTrapHwrSoundOff
(hex) A3C4 sysTrapSysKernelClockTick
(hex) A3C5 sysTrapMenuEraseMenu
(hex) A3C6 sysTrapSelectTime
(hex) A3C7 sysTrapMenuCmdBarAddButton
(hex) A3C8 sysTrapMenuCmdBarGetButtonData
(hex) A3C9 sysTrapMenuCmdBarDisplay
(hex) A3CA sysTrapHwrGetSilkscreenID
(hex) A002 sysTrapMemStoreInit
(hex) A3CB sysTrapEvtGetSilkscreenAreaList
(hex) A3CC sysTrapSysFatalAlertInit
(hex) A3CD sysTrapDateTemplateToAscii
(hex) A3CE sysTrapSecVerifyPW
(hex) A3CF sysTrapSecSelectViewStatus
(hex) A3D0 sysTrapTblSetColumnMasked
(hex) A3D1 sysTrapTblSetRowMasked
(hex) A3D2 sysTrapTblRowMasked
(hex) A3D3 sysTrapFrmCustomResponseAlert
(hex) A3D4 sysTrapFrmNewGsi
(hex) A3D5 sysTrapMenuShowItem
(hex) A3D6 sysTrapMenuHideItem
(hex) A3D7 sysTrapMenuAddItem
(hex) A3D8 sysTrapFrmSetGadgetHandler
(hex) A3D9 sysTrapCtlSetGraphics
(hex) A3DA sysTrapCtlGetSliderValues
(hex) A3DB sysTrapCtlSetSliderValues
(hex) A3DC sysTrapCtlNewSliderControl
(hex) A3DD sysTrapBmpCreate
(hex) A3DE sysTrapBmpDelete
(hex) A3DF sysTrapBmpCompress
(hex) A3E0 sysTrapBmpGetColortable
(hex) A3E1 sysTrapBmpSize
(hex) A3E2 sysTrapBmpBitsSize
(hex) A3E3 sysTrapBmpColortableSize
(hex) A3E4 sysTrapWinCreateBitmapWindow
(hex) A3E5 sysTrapEvtSetNullEventTick
(hex) A3E6 sysTrapExgDoDialog
(hex) A3E7 sysTrapSysUICleanup
(hex) A3E8 sysTrapWinSetForeColorRGB
(hex) A3E9 sysTrapWinSetBackColorRGB
(hex) A3EA sysTrapWinSetTextForeColorRGB
(hex) A3EB sysTrapWinGetPixelRGB
(hex) A3EC sysTrapSysReserved40Trap1
(hex) A3ED sysTrapSysReserved40Trap2
(hex) A3EE sysTrapSysReserved40Trap3
(hex) A3EF sysTrapSysReserved40Trap4
(hex) A3F0 sysTrapCncMgrDispatch
(hex) A3F1 sysTrapSysNotifyBroadcastFromInterrupt
(hex) A3F2 sysTrapEvtWakeUpWithoutNilEvent
(hex) A3F3 sysTrapStrCompareAscii
(hex) A3F4 sysTrapAccessorDispatch
(hex) A3F5 sysTrapBltGetPixel
(hex) A3F6 sysTrapBltPaintPixel
(hex) A3F7 sysTrapScrScreenInit
(hex) A3F8 sysTrapScrUpdateScreenBitmap
(hex) A3F9 sysTrapScrPalette
(hex) A3FA sysTrapScrGetColortable
(hex) A3FB sysTrapScrGetGrayPat
(hex) A3FC sysTrapScrScreenLock
(hex) A3FD sysTrapScrScreenUnlock
(hex) A3FE sysTrapFntPrvGetFontList
(hex) A3FF sysTrapExgRegisterDatatype
(hex) A400 sysTrapExgNotifyReceive
(hex) A401 sysTrapExgNotifyGoto
(hex) A402 sysTrapExgRequest
(hex) A403 sysTrapExgSetDefaultApplication
(hex) A404 sysTrapExgGetDefaultApplication
(hex) A405 sysTrapExgGetTargetApplication
(hex) A406 sysTrapExgGetRegisteredApplications
(hex) A407 sysTrapExgGetRegisteredTypes
(hex) A408 sysTrapExgNotifyPreview
(hex) A409 sysTrapExgControl
(hex) A40A sysTrapLmDispatch
(hex) A40B sysTrapMemGetRomNVParams
(hex) A40C sysTrapFntWCharWidth
(hex) A40D sysTrapDmFindDatabaseWithTypeCreator
(hex) A40E sysTrapSelectTimeZone
(hex) A40F sysTrapTimeZoneToAscii
(hex) A410 sysTrapStrNCompareAscii
(hex) A411 sysTrapTimTimeZoneToUTC
(hex) A412 sysTrapTimUTCToTimeZone
(hex) A413 sysTrapPhoneNumberLookupCustom
(hex) A414 sysTrapHwrDebugSelect

```

(hex) A415	sysTrapBltRoundedRectangle	(hex) A00D	sysTrapMemHeapFlags
(hex) A416	sysTrapBltRoundedRectangleFill	(hex) A00E	sysTrapMemHeapCompact
(hex) A417	sysTrapWinPrvInitCanvas	(hex) A00F	sysTrapMemHeapInit
(hex) A418	sysTrapHwrCalcDynamicHeapSize	(hex) A010	sysTrapMemHeapFreeByOwnerID
(hex) A419	sysTrapHwrDebuggerEnter	(hex) A011	sysTrapMemChunkNew
(hex) A41A	sysTrapHwrDebuggerExit	(hex) A012	sysTrapMemChunkFree
(hex) A41B	sysTrapLstGetTopItem	(hex) A013	sysTrapMemPtrNew
(hex) A41C	sysTrapHwrModelInitStage3	(hex) A014	sysTrapMemPtrRecoverHandle
(hex) A41D	sysTrapAttnIndicatorAllow	(hex) A015	sysTrapMemPtrFlags
(hex) A41E	sysTrapAttnIndicatorAllowed	(hex) A016	sysTrapMemPtrSize
(hex) A41F	sysTrapAttnIndicatorEnable	(hex) A017	sysTrapMemPtrOwner
(hex) A420	sysTrapAttnIndicatorEnabled	(hex) A018	sysTrapMemPtrHeapID
(hex) A421	sysTrapAttnIndicatorSetBlinkPattern	(hex) A019	sysTrapMemPtrCardNo
(hex) A422	sysTrapAttnIndicatorGetBlinkPattern	(hex) A01A	sysTrapMemPtrToLocalID
(hex) A423	sysTrapAttnIndicatorTicksTillNextBlink	(hex) A01B	sysTrapMemPtrSetOwner
(hex) A424	sysTrapAttnIndicatorCheckBlink	(hex) A01C	sysTrapMemPtrResize
(hex) A425	sysTrapAttnInitialize	(hex) A01D	sysTrapMemPtrResetLock
(hex) A426	sysTrapAttnGetAttention	(hex) A01E	sysTrapMemHandleNew
(hex) A427	sysTrapAttnUpdate	(hex) A01F	sysTrapMemHandleLockCount
(hex) A428	sysTrapAttnForgetIt	(hex) A020	sysTrapMemHandleToLocalID
(hex) A429	sysTrapAttnGetCounts	(hex) A021	sysTrapMemHandleLock
(hex) A42A	sysTrapAttnListOpen	(hex) A022	sysTrapMemHandleUnlock
(hex) A42B	sysTrapAttnHandleEvent	(hex) A023	sysTrapMemLocalIDToGlobal
(hex) A42C	sysTrapAttnEffectOfEvent	(hex) A024	sysTrapMemLocalIDKInd
(hex) A42D	sysTrapAttnIterate	(hex) A025	sysTrapMemLocalIDToPtr
(hex) A003	sysTrapMemCardFormat	(hex) A026	sysTrapMemMove
(hex) A42E	sysTrapAttnDoSpecialEffects	(hex) A027	sysTrapMemSet
(hex) A42F	sysTrapAttnDoEmergencySpecialEffects	(hex) A028	sysTrapMemStoreSearch
(hex) A430	sysTrapAttnAllowClose	(hex) A029	sysTrapSysReserved10Trap1
(hex) A431	sysTrapAttnReopen	(hex) A02A	sysTrapMemKernelInit
(hex) A432	sysTrapAttnEnableNotification	(hex) A02B	sysTrapMemHandleFree
(hex) A433	sysTrapHwrLEDAtributes	(hex) A02C	sysTrapMemHandleFlags
(hex) A434	sysTrapHwrVibrateAttributes	(hex) A02D	sysTrapMemHandleSize
(hex) A435	sysTrapSecGetPwdHint	(hex) A02E	sysTrapMemHandleOwner
(hex) A436	sysTrapSecSetPwdHint	(hex) A02F	sysTrapMemHandleHeapID
(hex) A437	sysTrapHwrFlashWrite	(hex) A030	sysTrapMemHandleDataStorage
(hex) A438	sysTrapKeyboardStatusNew	(hex) A031	sysTrapMemHandleCardNo
(hex) A439	sysTrapKeyboardStatusFree	(hex) A032	sysTrapMemHandleSetOwner
(hex) A43A	sysTrapKbdSetLayout	(hex) A033	sysTrapMemHandleResize
(hex) A43B	sysTrapKbdGetLayout	(hex) A034	sysTrapMemHandleResetLock
(hex) A43C	sysTrapKbdSetPosition	(hex) A035	sysTrapMemPtrUnlock
(hex) A43D	sysTrapKbdGetPosition	(hex) A036	sysTrapMemLocalIDToLockedPtr
(hex) A43E	sysTrapKbdSetShiftState	(hex) A037	sysTrapMemSetDebugMode
(hex) A43F	sysTrapKbdGetShiftState	(hex) A038	sysTrapMemHeapScramble
(hex) A440	sysTrapKbdDraw	(hex) A039	sysTrapMemHeapCheck
(hex) A441	sysTrapKbdErase	(hex) A03A	sysTrapMemNumCards
(hex) A442	sysTrapKbdHandleEvent	(hex) A03B	sysTrapMemDebugMode
(hex) A443	sysTrapOEMDispatch2	(hex) A03C	sysTrapMemSemaphoreReserve
(hex) A444	sysTrapHwrCustom	(hex) A03D	sysTrapMemSemaphoreRelease
(hex) A445	sysTrapFrmGetActiveField	(hex) A03E	sysTrapMemHeapDynamic
(hex) A446	sysTrapSndPlaySmfIrregardless	(hex) A03F	sysTrapMemNVParams
(hex) A447	sysTrapSndPlaySmfResourceIrregardless	(hex) A040	sysTrapDmInit
(hex) A448	sysTrapSndInterruptSmfIrregardless	(hex) A041	sysTrapDmCreateDatabase
(hex) A449	sysTrapUdaMgrDispatch	(hex) A042	sysTrapDmDeleteDatabase
(hex) A44A	sysTrapPalmPrivate1	(hex) A043	sysTrapDmNumDatabases
(hex) A44B	sysTrapPalmPrivate2	(hex) A044	sysTrapDmGetDatabase
(hex) A44C	sysTrapPalmPrivate3	(hex) A045	sysTrapDmFindDatabase
(hex) A44D	sysTrapPalmPrivate4	(hex) A046	sysTrapDmDatabaseInfo
(hex) A44E	sysTrapBmpGetDimensions	(hex) A047	sysTrapDmSetDatabaseInfo
(hex) A44F	sysTrapBmpGetBitDepth	(hex) A048	sysTrapDmDatabaseSize
(hex) A450	sysTrapBmpGetNextBitmap	(hex) A049	sysTrapDmOpenDatabase
(hex) A451	sysTrapTblGetNumberOfColumns	(hex) A04A	sysTrapDmCloseDatabase
(hex) A452	sysTrapTblGetTopRow	(hex) A04B	sysTrapDmNextOpenDatabase
(hex) A453	sysTrapTblSetSelection	(hex) A04C	sysTrapDmOpenDatabaseInfo
(hex) A454	sysTrapFrmGetObjectIndexFromPtr	(hex) A04D	sysTrapDmResetRecordStates
(hex) A455	sysTrapBmpGetSizes	(hex) A04E	sysTrapDmGetLastErr
(hex) A456	sysTrapWinGetBounds	(hex) A04F	sysTrapDmNumRecords
(hex) A457	sysTrapBltPaintPixels	(hex) A050	sysTrapDmRecordInfo
(hex) A458	sysTrapFldSetMaxVisibleLines	(hex) A051	sysTrapDmSetRecordInfo
(hex) A459	sysTrapScrDefaultPaletteState	(hex) A052	sysTrapDmAttachRecord
(hex) A45A	sysTrapPceNativeCall	(hex) A053	sysTrapDmDetachRecord
(hex) A45B	sysTrapSndStreamCreate	(hex) A054	sysTrapDmMoveRecord
(hex) A45C	sysTrapSndStreamDelete	(hex) A055	sysTrapDmNewRecord
(hex) A45D	sysTrapSndStreamStart	(hex) A056	sysTrapDmRemoveRecord
(hex) A45E	sysTrapSndStreamPause	(hex) A057	sysTrapDmDeleteRecord
(hex) A45F	sysTrapSndStreamStop	(hex) A058	sysTrapDmArchiveRecord
(hex) A460	sysTrapSndStreamSetVolume	(hex) A059	sysTrapDmNewHandle
(hex) A461	sysTrapSndStreamGetVolume	(hex) A05A	sysTrapDmRemoveSecretRecords
(hex) A462	sysTrapSndPlayResource	(hex) A05B	sysTrapDmQueryRecord
(hex) A463	sysTrapSndStreamSetPan	(hex) A05C	sysTrapDmGetRecord
(hex) A464	sysTrapSndStreamGetPan	(hex) A05D	sysTrapDmResizeRecord
(hex) A465	sysTrapMultimediaDispatch	(hex) A05E	sysTrapDmReleaseRecord
(hex) A466	sysTrapLastTrapNumber	(hex) A05F	sysTrapDmGetResource
(hex) A004	sysTrapMemCardInfo	(hex) A060	sysTrapDmGetIResource
(hex) A005	sysTrapMemStoreInfo	(hex) A061	sysTrapDmReleaseResource
(hex) A006	sysTrapMemStoreSetInfo	(hex) A062	sysTrapDmResizeResource
(hex) A007	sysTrapMemNumHeaps	(hex) A063	sysTrapDmNextOpenResDatabase
(hex) A008	sysTrapMemNumRAMHeaps	(hex) A064	sysTrapDmFindResourceType
(hex) A009	sysTrapMemHeapID	(hex) A065	sysTrapDmFindResource
(hex) A00A	sysTrapMemHeapPtr	(hex) A066	sysTrapDmSearchResource
(hex) A00B	sysTrapMemHeapFreeBytes	(hex) A067	sysTrapDmNumResources
(hex) A00C	sysTrapMemHeapSize	(hex) A068	sysTrapDmResourceInfo

(hex) A069	sysTrapDmSetResourceInfo	(hex) A0C5	sysTrapStrCopy
(hex) A06A	sysTrapDmAttachResource	(hex) A0C6	sysTrapStrCat
(hex) A06B	sysTrapDmDetachResource	(hex) A0C7	sysTrapStrLen
(hex) A06C	sysTrapDmNewResource	(hex) A0C8	sysTrapStrCompare
(hex) A06D	sysTrapDmRemoveResource	(hex) A0C9	sysTrapStrIToA
(hex) A06E	sysTrapDmGetResourceIndex	(hex) A0CA	sysTrapStrCaselessCompare
(hex) A06F	sysTrapDmQuickSort	(hex) A0CB	sysTrapStrIToH
(hex) A070	sysTrapDmQueryNextInCategory	(hex) A0CC	sysTrapStrChr
(hex) A071	sysTrapDmNumRecordsInCategory	(hex) A0CD	sysTrapStrStr
(hex) A072	sysTrapDmPositionInCategory	(hex) A0CE	sysTrapStrAToI
(hex) A073	sysTrapDmSeekRecordInCategory	(hex) A0CF	sysTrapStrToLower
(hex) A074	sysTrapDmMoveCategory	(hex) A0D0	sysTrapSerReceiveISP
(hex) A075	sysTrapDmOpenDatabaseByTypeCreator	(hex) A0D1	sysTrapSlkOpen
(hex) A076	sysTrapDmWrite	(hex) A0D2	sysTrapSlkClose
(hex) A077	sysTrapDmStrCopy	(hex) A0D3	sysTrapSlkOpenSocket
(hex) A078	sysTrapDmGetNextDatabaseByTypeCreator	(hex) A0D4	sysTrapSlkCloseSocket
(hex) A079	sysTrapDmWriteCheck	(hex) A0D5	sysTrapSlkSocketRefNum
(hex) A07A	sysTrapDmMoveOpenDBContext	(hex) A0D6	sysTrapSlkSocketSetTimeout
(hex) A07B	sysTrapDmFindRecordByID	(hex) A0D7	sysTrapSlkFlushSocket
(hex) A07C	sysTrapDmGetAppInfoID	(hex) A0D8	sysTrapSlkSetSocketListener
(hex) A07D	sysTrapDmFindSortPositionV10	(hex) A0D9	sysTrapSlkSendPacket
(hex) A07E	sysTrapDmSet	(hex) A0DA	sysTrapSlkReceivePacket
(hex) A07F	sysTrapDmCreateDatabaseFromImage	(hex) A0DB	sysTrapSlkSysPktDefaultResponse
(hex) A080	sysTrapDbgSrcMessage	(hex) A0DC	sysTrapSlkProcessRPC
(hex) A081	sysTrapDbgMessage	(hex) A0DD	sysTrapConPutS
(hex) A082	sysTrapDbgGetMessage	(hex) A0DE	sysTrapConGetS
(hex) A083	sysTrapDbgCommSettings	(hex) A0DF	sysTrapFplInit
(hex) A084	sysTrapErrDisplayFileLineMsg	(hex) A0E0	sysTrapFplFree
(hex) A085	sysTrapErrSetJump	(hex) A0E1	sysTrapFplFToA
(hex) A086	sysTrapErrLongJump	(hex) A0E2	sysTrapFplAToF
(hex) A087	sysTrapErrThrow	(hex) A0E3	sysTrapFplBase10Info
(hex) A088	sysTrapErrExceptionList	(hex) A0E4	sysTrapFplLongToFloat
(hex) A089	sysTrapSysBroadcastActionCode	(hex) A0E5	sysTrapFplFloatToLong
(hex) A08A	sysTrapSysUnimplemented	(hex) A0E6	sysTrapFplFloatToULong
(hex) A08B	sysTrapSysColdBoot	(hex) A0E7	sysTrapFplMul
(hex) A08C	sysTrapSysReset	(hex) A0E8	sysTrapFplAdd
(hex) A08D	sysTrapSysDoze	(hex) A0E9	sysTrapFplSub
(hex) A08E	sysTrapSysAppLaunch	(hex) A0EA	sysTrapFplDiv
(hex) A08F	sysTrapSysAppStartup	(hex) A0EB	sysTrapWinScreenInit
(hex) A090	sysTrapSysAppExit	(hex) A0EC	sysTrapScrCopyRectangle
(hex) A091	sysTrapSysSetA5	(hex) A0ED	sysTrapScrDrawChars
(hex) A092	sysTrapSysSetTrapAddress	(hex) A0EE	sysTrapScrLineRoutine
(hex) A093	sysTrapSysGetTrapAddress	(hex) A0EF	sysTrapScrRectangleRoutine
(hex) A094	sysTrapSysTranslateKernelErr	(hex) A0F0	sysTrapScrScreenInfo
(hex) A095	sysTrapSysSemaphoreCreate	(hex) A0F1	sysTrapScrDrawNotify
(hex) A096	sysTrapSysSemaphoreDelete	(hex) A0F2	sysTrapScrSendUpdateArea
(hex) A097	sysTrapSysSemaphoreWait	(hex) A0F3	sysTrapScrCompressScanLine
(hex) A098	sysTrapSysSemaphoreSignal	(hex) A0F4	sysTrapScrDeCompressScanLine
(hex) A099	sysTrapSysTimerCreate	(hex) A0F5	sysTrapTimGetSeconds
(hex) A09A	sysTrapSysTimerWrite	(hex) A0F6	sysTrapTimSetSeconds
(hex) A09B	sysTrapSysTaskCreate	(hex) A0F7	sysTrapTimGetTicks
(hex) A09C	sysTrapSysTaskDelete	(hex) A0F8	sysTrapTimInit
(hex) A09D	sysTrapSysTaskTrigger	(hex) A0F9	sysTrapTimSetAlarm
(hex) A09E	sysTrapSysTaskID	(hex) A0FA	sysTrapTimGetAlarm
(hex) A09F	sysTrapSysTaskUserInfoPtr	(hex) A0FB	sysTrapTimHandleInterrupt
(hex) A0A0	sysTrapSysTaskDelay	(hex) A0FC	sysTrapTimSecondsToDateTime
(hex) A0A1	sysTrapSysTaskSetTermProc	(hex) A0FD	sysTrapTimDateToSeconds
(hex) A0A2	sysTrapSysUILaunch	(hex) A0FE	sysTrapTimAdjust
(hex) A0A3	sysTrapSysNewOwnerID	(hex) A0FF	sysTrapTimSleep
(hex) A0A4	sysTrapSysSemaphoreSet	(hex) A100	sysTrapTimWake
(hex) A0A5	sysTrapSysDisableInts	(hex) A101	sysTrapCategoryCreateListV10
(hex) A0A6	sysTrapSysRestoreStatus	(hex) A102	sysTrapCategoryFreeListV10
(hex) A0A7	sysTrapSysUIAppSwitch	(hex) A103	sysTrapCategoryFind
(hex) A0A8	sysTrapSysCurAppInfoPV20	(hex) A104	sysTrapCategoryGetName
(hex) A0A9	sysTrapSysHandleEvent	(hex) A105	sysTrapCategoryEidtV10
(hex) A0AA	sysTrapSysInit	(hex) A106	sysTrapCategorySelectV10
(hex) A0AB	sysTrapSysQSort	(hex) A107	sysTrapCategoryGetNext
(hex) A0AC	sysTrapSysCurAppDatabase	(hex) A108	sysTrapCategorySetTriggerLabel
(hex) A0AD	sysTrapSysFatalAlert	(hex) A109	sysTrapCategoryTruncateName
(hex) A0AE	sysTrapSysResSemaphoreCreate	(hex) A10A	sysTrapClipboardAddItem
(hex) A0AF	sysTrapSysResSemaphoreDelete	(hex) A10B	sysTrapClipboardCheckIfItemExist
(hex) A0B0	sysTrapSysResSemaphoreReserve	(hex) A10C	sysTrapClipboardGetItem
(hex) A0B1	sysTrapSysResSemaphoreRelease	(hex) A10D	sysTrapCtlDrawControl
(hex) A0B2	sysTrapSysSleep	(hex) A10E	sysTrapCtlEraseControl
(hex) A0B3	sysTrapSysKeyboardDialogV10	(hex) A10F	sysTrapCtlHideControl
(hex) A0B4	sysTrapSysAppLauncherDialog	(hex) A110	sysTrapCtlShowControl
(hex) A0B5	sysTrapSysSetPerformance	(hex) A111	sysTrapCtlGetValue
(hex) A0B6	sysTrapSysBatteryInfoV20	(hex) A112	sysTrapCtlSetValue
(hex) A0B7	sysTrapSysLibInstall	(hex) A113	sysTrapCtlGetLabel
(hex) A0B8	sysTrapSysLibRemove	(hex) A114	sysTrapCtlSetLabel
(hex) A0B9	sysTrapSysLibTblEntry	(hex) A115	sysTrapCtlHandleEvent
(hex) A0BA	sysTrapSysLibFind	(hex) A116	sysTrapCtlHitControl
(hex) A0BB	sysTrapSysBatteryDialog	(hex) A117	sysTrapCtlSetEnabled
(hex) A0BC	sysTrapSysCopyStringResource	(hex) A118	sysTrapCtlSetUsable
(hex) A0BD	sysTrapSysKernelInfo	(hex) A119	sysTrapCtlEnabled
(hex) A0BE	sysTrapSysLaunchConsole	(hex) A11A	sysTrapEvtInitialize
(hex) A0BF	sysTrapSysTimerDelete	(hex) A11B	sysTrapEvtAddEventToQueue
(hex) A0C0	sysTrapSysSetAutoOffTime	(hex) A11C	sysTrapEvtCopyEvent
(hex) A0C1	sysTrapSysFormPointerArrayToStrings	(hex) A11D	sysTrapEvtGetEvent
(hex) A0C2	sysTrapSysRandom	(hex) A11E	sysTrapEvtGetPen
(hex) A0C3	sysTrapSysTaskSwitching	(hex) A11F	sysTrapEvtSysInit
(hex) A0C4	sysTrapSysTimerRead	(hex) A120	sysTrapEvtGetSysEvent

(hex) A121	sysTrapEvtProcessSoftKeyStroke	(hex) A17D	sysTrapFrmGetFormId
(hex) A122	sysTrapEvtGetPenBtnList	(hex) A17E	sysTrapFrmGetFormPtr
(hex) A123	sysTrapEvtSetPenQueuePtr	(hex) A17F	sysTrapFrmGetNumberOfObjects
(hex) A124	sysTrapEvtPenQueueSize	(hex) A180	sysTrapFrmGetObjectIndex
(hex) A125	sysTrapEvtFlushPenQueue	(hex) A181	sysTrapFrmGetObjectId
(hex) A126	sysTrapEvtEnqueuePenPoint	(hex) A182	sysTrapFrmGetObjectType
(hex) A127	sysTrapEvtDequeuePenStrokeInfo	(hex) A183	sysTrapFrmGetObjectPtr
(hex) A128	sysTrapEvtDequeuePenPoint	(hex) A184	sysTrapFrmHideObject
(hex) A129	sysTrapEvtFlushNextPenStroke	(hex) A185	sysTrapFrmShowObject
(hex) A12A	sysTrapEvtSetKeyQueuePtr	(hex) A186	sysTrapFrmGetObjectPosition
(hex) A12B	sysTrapEvtKeyQueueSize	(hex) A187	sysTrapFrmSetObjectPosition
(hex) A12C	sysTrapEvtFlushKeyQueue	(hex) A188	sysTrapFrmGetControlValue
(hex) A12D	sysTrapEvtDequeueKey	(hex) A189	sysTrapFrmSetControlValue
(hex) A12E	sysTrapEvtDequeueKeyEvent	(hex) A18A	sysTrapFrmGetControlGroupSelection
(hex) A12F	sysTrapEvtWakeUp	(hex) A18B	sysTrapFrmSetControlGroupSelection
(hex) A130	sysTrapEvtResetAutoOffTimer	(hex) A18C	sysTrapFrmCopyLabel
(hex) A131	sysTrapEvtKeyQueueEmpty	(hex) A18D	sysTrapFrmSetLabel
(hex) A132	sysTrapEvtEnableGraffiti	(hex) A18E	sysTrapFrmGetLabel
(hex) A133	sysTrapFldCopy	(hex) A18F	sysTrapFrmSetCategoryLabel
(hex) A134	sysTrapFldCut	(hex) A190	sysTrapFrmSetTitle
(hex) A135	sysTrapFldDrawField	(hex) A191	sysTrapFrmSetTitle
(hex) A136	sysTrapFldEraseField	(hex) A192	sysTrapFrmAlert
(hex) A137	sysTrapFldFreeMemory	(hex) A193	sysTrapFrmDoDialog
(hex) A138	sysTrapFldGetBounds	(hex) A194	sysTrapFrmCustomAlert
(hex) A139	sysTrapFldGetTextPtr	(hex) A195	sysTrapFrmHelp
(hex) A13A	sysTrapFldGetSelection	(hex) A196	sysTrapFrmUpdateScrollers
(hex) A13B	sysTrapFldHandleEvent	(hex) A197	sysTrapFrmGetFirstForm
(hex) A13C	sysTrapFldPaste	(hex) A198	sysTrapFrmVisible
(hex) A13D	sysTrapFldRecalculateField	(hex) A199	sysTrapFrmGetObjectBounds
(hex) A13E	sysTrapFldSetBounds	(hex) A19A	sysTrapFrmCopyTitle
(hex) A13F	sysTrapFldSetText	(hex) A19B	sysTrapFrmGotoForm
(hex) A140	sysTrapFldGetFont	(hex) A19C	sysTrapFrmPopupForm
(hex) A141	sysTrapFldSetFont	(hex) A19D	sysTrapFrmUpdateForm
(hex) A142	sysTrapFldSetSelection	(hex) A19E	sysTrapFrmReturnToForm
(hex) A143	sysTrapFldGrabFocus	(hex) A19F	sysTrapFrmSetEventHandler
(hex) A144	sysTrapFldReleaseFocus	(hex) A1A0	sysTrapFrmDispatchEvent
(hex) A145	sysTrapFldGetInsPtPosition	(hex) A1A1	sysTrapFrmCloseAllForms
(hex) A146	sysTrapFldSetInsPtPosition	(hex) A1A2	sysTrapFrmSaveAllForms
(hex) A147	sysTrapFldSetScrollPosition	(hex) A1A3	sysTrapFrmGetGadgetData
(hex) A148	sysTrapFldGetScrollPosition	(hex) A1A4	sysTrapFrmSetGadgetData
(hex) A149	sysTrapFldGetTextHeight	(hex) A1A5	sysTrapFrmSetCategoryTrigger
(hex) A14A	sysTrapFldGetTextAllocatedSize	(hex) A1A6	sysTrapUIInitialize
(hex) A14B	sysTrapFldGetTextLength	(hex) A1A7	sysTrapUIReset
(hex) A14C	sysTrapFldScrollField	(hex) A1A8	sysTrapInsPtInitialize
(hex) A14D	sysTrapFldScrollable	(hex) A1A9	sysTrapInsPtSetLocation
(hex) A14E	sysTrapFldGetVisibleLines	(hex) A1AA	sysTrapInsPtGetLocation
(hex) A14F	sysTrapFldGetAttributes	(hex) A1AB	sysTrapInsPtEnable
(hex) A150	sysTrapFldSetAttributes	(hex) A1AC	sysTrapInsPtEnabled
(hex) A151	sysTrapFldSendChangeNotification	(hex) A1AD	sysTrapInsPtSetHeight
(hex) A152	sysTrapFldCalcFieldHeight	(hex) A1AE	sysTrapInsPtGetHeight
(hex) A153	sysTrapFldGetTextHandle	(hex) A1AF	sysTrapInsPtCheckBlink
(hex) A154	sysTrapFldCompactText	(hex) A1B0	sysTrapLstSetDrawFunction
(hex) A155	sysTrapFldDirty	(hex) A1B1	sysTrapLstDrawList
(hex) A156	sysTrapFldWordWrap	(hex) A1B2	sysTrapLstEraseList
(hex) A157	sysTrapFldSetTextAllocatedSize	(hex) A1B3	sysTrapLstGetSelection
(hex) A158	sysTrapFldSetTextHandle	(hex) A1B4	sysTrapLstGetSelectionText
(hex) A159	sysTrapFldSetTextPtr	(hex) A1B5	sysTrapLstHandleEvent
(hex) A15A	sysTrapFldGetMaxChars	(hex) A1B6	sysTrapLstSetHeight
(hex) A15B	sysTrapFldSetMaxChars	(hex) A1B7	sysTrapLstSetSelection
(hex) A15C	sysTrapFldSetUsable	(hex) A1B8	sysTrapLstSetListChoices
(hex) A15D	sysTrapFldInsert	(hex) A1B9	sysTrapLstMakeItemVisible
(hex) A15E	sysTrapFldDelete	(hex) A1BA	sysTrapLstGetNumberOfItems
(hex) A15F	sysTrapFldUndo	(hex) A1BB	sysTrapLstPopUpList
(hex) A160	sysTrapFldSetDirty	(hex) A1BC	sysTrapLstSetPosition
(hex) A161	sysTrapFldSendHeightChangeNotification	(hex) A1BD	sysTrapMenuInit
(hex) A162	sysTrapFldMakeFullyVisible	(hex) A1BE	sysTrapMenuDispose
(hex) A163	sysTrapFntGetFont	(hex) A1BF	sysTrapMenuHandleEvent
(hex) A164	sysTrapFntSetFont	(hex) A1C0	sysTrapMenuDrawMenu
(hex) A165	sysTrapFntGetFontPtr	(hex) A1C1	sysTrapMenuEraseStatus
(hex) A166	sysTrapFntBaseLine	(hex) A1C2	sysTrapMenuGetActiveMenu
(hex) A167	sysTrapFntCharHeight	(hex) A1C3	sysTrapMenuSetActiveMenu
(hex) A168	sysTrapFntLineHeight	(hex) A1C4	sysTrapRctSetRectangle
(hex) A169	sysTrapFntAverageCharWidth	(hex) A1C5	sysTrapRctCopyRectangle
(hex) A16A	sysTrapFntCharWidth	(hex) A1C6	sysTrapRctInsetRectangle
(hex) A16B	sysTrapFntCharsWidth	(hex) A1C7	sysTrapRctOffsetRectangle
(hex) A16C	sysTrapFntDescenderHeight	(hex) A1C8	sysTrapRctPtInRectangle
(hex) A16D	sysTrapFntCharsInWidth	(hex) A1C9	sysTrapRctGetIntersection
(hex) A16E	sysTrapFntLineWidth	(hex) A1CA	sysTrapTblDrawTable
(hex) A16F	sysTrapFrmInitForm	(hex) A1CB	sysTrapTblEraseTable
(hex) A170	sysTrapFrmDeleteForm	(hex) A1CC	sysTrapTblHandleEvent
(hex) A171	sysTrapFrmDrawForm	(hex) A1CD	sysTrapTblGetItemBounds
(hex) A172	sysTrapFrmEraseForm	(hex) A1CE	sysTrapTblSelectItem
(hex) A173	sysTrapFrmGetActiveForm	(hex) A1CF	sysTrapTblGetItemInt
(hex) A174	sysTrapFrmSetActiveForm	(hex) A1D0	sysTrapTblSetItemInt
(hex) A175	sysTrapFrmGetActiveFormID	(hex) A1D1	sysTrapTblSetItemStyle
(hex) A176	sysTrapFrmGetUserModifiedState	(hex) A1D2	sysTrapTblUnhighlightSelection
(hex) A177	sysTrapFrmSetNotUserModified	(hex) A1D3	sysTrapTblSetRowUsable
(hex) A178	sysTrapFrmGetFocus	(hex) A1D4	sysTrapTblGetNumberOfRows
(hex) A179	sysTrapFrmSetFocus	(hex) A1D5	sysTrapTblSetCustomDrawProcedure
(hex) A17A	sysTrapFrmHandleEvent	(hex) A1D6	sysTrapTblSetRowSelectable
(hex) A17B	sysTrapFrmGetFormBounds		
(hex) A17C	sysTrapFrmGetWindowHandle		